

<u>TITLE</u>

2.4/5GHz MIMO 2X2 FLEXIBLE ANTENNA

TABLE OF CONTENTS

1.0 SCOPE

- 2.0 PRODUCT DESCRIPTION
- **3.0 APPLICABLE DOCUMENTS**

4.0 ANTENNA PERFORMANCE

- 5.0 ASSEMBLY GUIDELINE
- 6.0 RF PERFORMANCE AS A FUNCTION OF IMPLEMENTATION

<u>REVISION:</u>	<u>ECR/ECN INFORMATION:</u> <u>EC No:</u> 606016 <u>DATE:</u> 2018/10/19	2.4/5GHz M Appli	<u>SHEET No.</u> 1 of 35		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	<u>APPROV</u>	/ED BY:
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong	2018/10/15



2.4/5GHz MIMO 2X2 FLEXIBLE ANTENNA

1.0 SCOPE

This specification describes the antenna application and surrounding. The information in this document is for reference and benchmark purposes only. The user is responsible for validating antenna RF performance based on the user's actual implementation.

Antenna illustrations in this document are generic representations. They are not intended to be an image of any antenna listed in the scope.

2.0 PRODUCT DESCRIPTION

2.1 PRODUCT NAME AND SERIES NUMBER (S)

Product name: 2.4/5GHz MIMO 2X2 Flexible Antenna Series Number: 208482

2.2 DESCRIPTION

Series 208482 is a 2*MIMO flexible dipole type antenna for high speed WiFi network. It's made from Poly-flexible material, size form 55.20mm x 19.20mm x 0.16mm with double sided TESA adhesive for "peel and stick" easy mounting. Potential application is High speed HD video streaming, high capacity communication network, like router, gateway, set-top box...

2.3 PRODUCT STRUCTURE INFORMATION

Please refer to PS-2084820100 for full information.



Molex 208482100 2.4/5GHz MIMO 2x2 FLEXIBLE ANTENNA 3D VIEW

<u>REVISION:</u>	ECR/ECN INFORMATION: EC No: 606016 DATE: 2018/10/19	2.4/5GHz M Appli	<u>SHEET No.</u> 2 of 35		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	APPROV	<u>'ED BY:</u>
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong	2018/10/15



3.0 APPLICABLE DOCUMENTS

DOCUMENT	NUMBER	DESCRIPTION
Sale Drawing(SD)	SD-2084820100	Mechanical Dimension of the product
Product Specification (PS)	PS-2084820100	Product Specification
Packing Drawing(PK)	PK-2084820100	Product packaging specifications

4.0 ANTENNA PERFORMANCE

4.1 RF TEST CONDITIONS

All measurements are done of the antenna mounted on a PC/ABS material block of 1.5mm thickness with VNA Agilent E5071C and Over-The-Air (OTA) chamber. All measurements in this document are done with the part No. 2084820100 with a cable length of 100mm.



FIGURE4.1.1 ANTENNA LOADED WITH PC/ABS BLOCK OF 1.5MM THICKNESS

REVISION:	ECR/ECN INFORMATION:	TITLE:			SHEET No.
۸	<u>EC No:</u> 606016	2.4/5GHz MIMO 2x2 Flexible Antenna		2 .4 25	
A	<u>DATE:</u> 2018/10/19	Арри	3 OT 33		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	<u>APPROV</u>	/ED BY:
AS-2084820100		Liu Hai 2018/10/15 Cheng Kang 2018/10/15 Chris Zho		Chris Zhong	2018/10/15





REVISION:	ECR/ECN INFORMATION:	TITLE:			SHEET No.	
Δ	<u>EC No:</u> 606016	2.4/5GHz M Appli	2.4/5GHz MIMO 2x2 Flexible Antenna Application Specification			
~	<u>DATE:</u> 2018/10/19	Т	Application Specification			
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	<u>APPROV</u>	/ED BY:	
AS-2084820100		Liu Hai 2018/10/15 Cheng Kang 2018/10/15 Chris Zhe		Chris Zhong	2018/10/15	





DOCUMENT NUMBE	<u>R:</u>	CREATED / REVISED BY:	CHECKED BY:	APPROVED BY:
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong 2018/10/15



4.2 ANTENNA PERFORMANCE

Description	Equipment	Requirement (100mm)				
Description	Equipment	Por	t 1	Port 2		
Frequency Range	VNA E5071C	2.4-2.5GHz	5.15- 5.85GHz	2.4-2.5GHz	5.15- 5.85GHz	
Return Loss	VNA E5071C	<-8dB	<-13dB	<-9dB	<-13dB	
Peak Gain (Max)	OTA Chamber	2.9 dBi	5.0 dBi	3.4 dBi	5.9 dBi	
Average Total Efficiency	OTA Chamber	65%	75%	75%	70%	
Polarization	OTA Chamber	Linear				
Input Impedance	VNA E5071C		50 c	ohms		

Note that the above antenna performance is measured with just the antenna mounted on a PC/ABS block to similar a free-space condition. When implement into the system, the frequency resonant might be off-tune due to the loading of surrounding components especially metal plane. This off-tune can be compensated through matching. Although module manufacturers specify a peak gain limit, it is based on free-space conditions. The peak gain will be degraded by 1 to 2dBi in the actual implementation as the radiation pattern will change due to the surround components. As such, during selection of antenna, you can select one with high peak gain to compensate for the loss. Molex can offer assistant to choose the best location and best tuning in-order to meet this peak gain requirement.

<u>REVISION:</u>	<u>ECR/ECN INFORMATION:</u> <u>EC No:</u> 606016 <u>DATE:</u> 2018/10/19	2.4/5GHz M Appli	<u>SHEET No.</u> 6 of 35		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	<u>APPROV</u>	/ED BY:
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong	2018/10/15



4.3 RETURN LOSS PLOT

All measurements in this document are done with cable length of 100mm.



FIGURE 4.3.1 RETURN LOSS OF ANTENNA AT 2.4GHZ BAND OF PORT1 IN FREE SPACE



REVISION:	ECR/ECN INFORMATION: EC No: 606016 DATE: 2018/10/19	2.4/5GHz M Appli	<u>SHEET No.</u> 7 of 35		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	APPROVED BY:	
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong	2018/10/15



FIGURE 4.3.3 RETURN LOSS OF ANTENNA AT 2.4GHZ BAND OF PORT 2 IN FREE SPACE



FIGURE 4.3.4 RETURN LOSS OF ANTENNA AT 5GHZ BAND OF PORT 2 IN FREE SPACE

REVISION:	ECR/ECN INFORMATION: EC No: 606016	<u>TITLE:</u> 2.4/5GHz M	2.4/5GHz MIMO 2x2 Flexible Antenna			
Α	<u>DATE:</u> 2018/10/19	Appli	Application Specification			
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	APPROVED BY:		
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong	2018/10/15	



4.4 EFFICIENCY PLOT



FIGURE 4.4.1 EFFICIENCY OF ANTENNA AT 2.4GHZ BAND OF PORT 1 IN FREE SPACE





FIGURE 4.4.3 EFFICIENCY OF ANTENNA AT 2.4GHZ BAND OF PORT 2 IN FREE SPACE



A	<u>ECR/ECN INFORMATION:</u> EC No: 606016 DATE: 2018/10/19	2.4/5GHz M Appli	10 of 35		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	<u>APPROV</u>	<u>'ED BY:</u>
AS-2084820100		Liu Hai 2018/10/15 Cheng Kang 2018/10/15 Chris Zho		Chris Zhong	2018/10/15













REVISION:	ECR/ECN INFORMATION:	TITLE:			SHEET No.
٨	<u>EC No:</u> 606016	2.4/5GHz MIMO 2x2 Flexible Antenna		ntenna	13 of 35
A	<u>DATE:</u> 2018/10/19	Appi	13 01 33		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	<u>APPROV</u>	/ED BY:
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong	2018/10/15

REVISION: ECR/ECN INFORMATION: TITLE.









'nole









'nole





5.0 ASSEMBLY GUIDELINE

The flex antenna comes with an adhesive TESA for assemble onto the plastic wall of the system. The surface should be smooth with Ra<1.6um, and need to clean the surface before sticking this product. The antenna cannot be placed on a metallic surface.

5.1 HOW TO TEAR FLEX RELEASE PAPER



1. Find cut line on flex back side



2. Bend flex slight along cut line



3. Tear release paper

REVISION:	ECR/ECN INFORMATION:	TITLE:	L <u>E:</u>		SHEET No.
۸	<u>EC No:</u> 606016	2.4/5GHz MIMO 2x2 Flexible Antenna		40 (25	
A	<u>DATE:</u> 2018/10/19	Application Specification			19 of 35
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	APPROVED BY:	
AS-2084820100		Liu Hai 2018/10/15	Cheng Kang 2018/10/15	Chris Zhong 2018/10/15	



5.2 CABLE BENDING

During the assembly of the antenna in a device, the cable needs to be positioned away from the antenna flex to achieve best performance. The cable must be away from the pattern at least 5mm as shown in figure 5.2.1. If the cable crosses into the antenna flex, the antenna performance will be degraded.





6.0 PERFORMANCE AS A FUNCTION OF IMPLEMENTATION

6.1 ANTENNA RF PERFORMANCE AS A FUNCTION OF DIFFERENT LOCATIONS WITH PARALLEL PLANE GROUND

Four locations with parallel plane ground have been evaluated and these locations are shown in figure 6.1.0. The plane ground size is 90mm*90mm and we move the plane ground to four locations for each test. The antenna performance is better with larger distance between antenna and parallel plane ground at high band. The minimum distance between antenna and plane ground is recommended to be 15mm to achieve acceptable RF performance.







Cheng Kang 2018/10/15



Liu Hai 2018/10/15

AS-2084820100

TEMPLATE FILENAME: APPLICATION_SPEC[SIZE_A](V.1).DOC

Cheng Kang 2018/10/15

Chris Zhong 2018/10/15









6.2 ANTENNA RF PERFORMANCE AS A FUNCTION OF DIFFERENT LOCATIONS WITH VERTICAL PLANE GROUND

Four locations with vertical plane ground have been evaluated and these locations are shown in figure 6.2.0. The plane ground size is 90mm*90mm and we move the plane ground to four locations for each test. The distance between antenna and vertical plane ground affect the antenna performance slightly. We still suggest the minimum distance between antenna and plane ground is recommended to be 5mm.



















6.3 ANTENNA RF PERFORMANCE AS A FUNCTION OF DIFFERENT DISTANCES WITH PARALLEL PLANE GROUND

Four locations with the parallel plane ground have been evaluated and these locations are shown in figure 6.3.0. The plane ground size is 90mm*90mm and we move the plane ground to four locations for each test. The distance between the antenna and the parallel plane ground affect the antenna performance slightly. We still suggest the minimum distance between the antenna and the plane ground is recommended to be 5mm.















