SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

- High-Performance Static CMOS Technology
- Includes the T320C2xLP Core CPU
 - Object Compatible With the TMS320C2xx
 - Source Code Compatible With TMS320C25
 - Upwardly Compatible With TMS320C5x
 - 132-Pin Plastic Quad Flat Package (PQ Suffix)
 - 50-ns Instruction Cycle Time
- Industrial and Automotive Temperature Available
- Memory
 - 544 Words × 16 Bits of On-Chip Data/Program Dual-Access RAM
 - 16K Words × 16 Bits of On-Chip Program Flash EEPROM
 - 224K Words × 16 Bits of Total Memory Address Reach (64K Data, 64K Program and 64K I/O, and 32K Global Memory Space)
- Event-Manager Module
 - 12 Compare/Pulse-Width Modulation (PWM) Channels
 - Three 16-Bit General-Purpose Timers With Six Modes, Including Continuous Upand Up/Down Counting
 - Three 16-Bit Full-Compare Units With Deadband
 - Three 16-Bit Simple-Compare Units
 - Four Capture Units (Two With Quadrature Encoder-Pulse Interface Capability)

- Dual 10-Bit Analog-to-Digital Conversion Module
- 28 Individually Programmable, Multiplexed I/O Pins
- Phase-Locked-Loop (PLL)-Based Clock Module
- Watchdog Timer Module (With Real-Time Interrupt)
- Serial Communications Interface (SCI) Module
- Serial Peripheral Interface (SPI) Module
- Six External Interrupts (Power Drive Protect, Reset, NMI, and Three Maskable Interrupts)
- Four Power-Down Modes for Low-Power Operation
- Scan-Based Emulation
- Development Tools Available:
 - Texas Instruments (TI) ANSI
 C Compiler, Assembler/Linker, and
 C-Source Debugger
 - Scan-Based Self-Emulation (XDS510[™])
 - Third-Party Digital Motor Control and Fuzzy-Logic Development Support

description

The TMS320F240 (F240) device is a member of a family of DSP controllers based on the TMS320C2xx generation of 16-bit fixed-point digital signal processors (DSPs). This family is optimized for digital motor/motion control applications. The DSP controllers combine the enhanced TMS320 architectural design of the C2xLP core CPU for low-cost, high-performance processing capabilities and several advanced peripherals optimized for motor/motion control applications. These peripherals include the event manager module, which provides general-purpose timers and compare registers to generate up to 12 PWM outputs, and a dual10-bit analog-to-digital converter (ADC), which can perform two simultaneous conversions within 6.1 µs. See the functional block diagram.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

XDS510 is a trademark of Texas Instruments. Other trademarks are the property of their respective owners.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.



Copyright © 2002, Texas Instruments Incorporated

Table of Contents

Description 1 PQ Package (Top View) 4 Terminal Functions 5 Functional Block Diagram 11 Architectural Overview 12 System-Level Functions 12 Device Memory Map 12 Peripheral Memory Map 14
Digital I/O and Shared Pin Functions
Digital I/O Control Registers 17
Device Reset and Interrupts 17
Clock Generation
Low-Power Modes 28
Functional Block Diagram of the
TMS320F240 DSP CPU 29
F240 DSP Core CPU 32
Internal Memory 36



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

REVISION	DATE	PRODUCT STATUS	HIGHLIGHTS
E	November 2002	Production Data	Removed TMS320C240 as it is an obsolete device. Updated descriptions of the following pins in the Terminal Functions table: - <u>PWM1/CMP1-PWM6/CMP6</u> - <u>OSCBYP</u> - TRST Updated the following figures: - Figure 3, Shared Pin Configuration - Figure 6, System Module Interrupt Structure - Figure 12, Analog-to-Digital Converter Module - Figure 16, TMS320 Device Nomenclature - Figure 20, Recommended Crystal/Clock Connection Added the following figures: - Figure 31, Case With Crystal - Figure 32, Case With External Oscillator Updated the following tables: - Table 15, Development Support Tools - Table 16, TMS320F240-Specific Development Tools - Table 20, Register File Compilation [ADCTRL1 and ADCTRL2] Updated the following sections: - Low-Power Modes - Flash EEPROM - Capture Unit - Analog-to-Digital Converter (ADC) Module [Digital Value equation] - Development Support - External Reference Crystal With PLL-Circuit-Enabled Clock Option - 10-Bit Dual Analog-to-Digital Converter (ADC)

REVISION HISTORY



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002





SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

Terminal Functions

TERMI NAME	NAL NO.	TYPET	DESCRIPTION				
	EXTERNAL INTERFACE DATA/ADDRESS SIGNALS						
A0 (LSB) A1 A2 A3 A4 A5 A6 A7 A8 A9 A10 A11 A12 A13 A14 A15 (MSB)	110 111 112 114 115 116 117 118 119 122 123 124 125 126 127 128	O/Z	Parallel address bus A0 [least significant bit (LSB)] through A15 [most significant bit (MSB)]. A15–A0 are multiplexed to address external data/program memory or I/O. A15–A0 are placed in high-impedance state when EMU1/OFF is active low and hold their previous states in power-down modes.				
D0 (LSB) D1 D2 D3 D4 D5 D6 D7 D8 D9 D10 D11 D12 D13 D14 D15 (MSB)	9 10 11 12 15 16 17 18 19 22 23 24 25 26 27 28	I/O/Z	Parallel data bus D0 (LSB) through D15 (MSB). D15–D0 are multiplexed to transfer data between the TMS320F240 and external data/program memory and I/O space (devices). D15–D0 are placed in the high-impedance state when not outputting, when in power-down mode, when reset (RS) is asserted, or when EMU1/OFF is active low.				
			EXTERNAL INTERFACE CONTROL SIGNALS				
DS PS IS	129 131 130	O/Z	Data, program, and I/O space select signals. DS, PS, and IS are always high unless low-level asserted for communication to a particular external space. They are placed in the high-impedance state during reset, power down, and when EMU1/OFF is active low.				
READY	36	I	Data ready. READY indicates that an external device is prepared for the bus transaction to be completed. If the device is not ready (READY is low), the processor waits one cycle and checks READY again.				
R/W	4	O/Z	Read/write signal. R/W indicates transfer direction during communication to an external device. It is normally in read mode (high), unless low level is asserted for performing a write operation. It is placed in the high-impedance state during reset, power down, and when EMU1/OFF is active low.				
STRB	6	O/Z	Strobe. STRB is always high unless asserted low to indicate an external bus cycle. It is placed in the high-impedance state during reset, power down, and when EMU1/OFF is active low.				
WE	1	O/Z	Write enable. The falling edge of WE indicates that the device is driving the external data but (D15–D0). Data can be latched by an external device on the rising edge of WE. WE is active on a external program, data, and I/O writes. WE goes in the high-impedance state following reset and whe EMU1/OFF is active low.				
W/R	132	O/Z	Write/read. W/R is an inverted form of R/W and can connect directly to the output enable of external devices. W/R is placed in the high-impedance state following reset and when EMU1/OFF is active low.				

SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

Terminal Functions (Continued)

TERMINAL NAME NO.		TYPET	DESCRIPTION				
EXTERNAL INTERFACE CONTROL SIGNALS (CONTINUED)							
BR	5	O/Z	Bus request. BR is asserted during access of external global data memory space. BR can be used to extend the data memory address space by up to 32K words. BR goes in the high-impedance state during reset, power down, and when EMU1/OFF is active low.				
V _{CCP} /WDDIS	50	Γ	Flash-programming voltage supply. If V _{CCP} = 5 V, then WRITE/ERASE can be made to the ENTIRE on-chip flash memory block—that is, for programming the flash. If V _{CCP} = 0 V, then WRITE/ERASE of the flash memory is not allowed, thereby protecting the entire memory block from being overwritten. V _{CCP} /WDDIS also functions as a hardware watchdog disable. The watchdog timer is disabled when V _{CCP} /WDDIS = 5 V and bit 6 in WDCR is set to 1.				
		-	ADC INPUTS (UNSHARED)				
ADCIN2	74	I					
ADCIN3	75	Ι					
ADCIN4	76	-	Analog inputs to the first ADC				
ADCIN5	77	-	Analog inputs to the first ADC				
ADCIN6	78	-					
ADCIN7	79	I					
ADCIN10	89	I					
ADCIN11	88	I					
ADCIN12	83	I					
ADCIN13	82	I	Analog inputs to the second ADC				
ADCIN14	81	I					
ADCIN15	80	I					
			BIT I/O AND SHARED FUNCTIONS PINS				
ADCIN0/IOPA0	72	I/O	Bidirectional digital I/O. Analog input to the first ADC. ADCIN0/IOPA0 is configured as a digital input by all device resets.				
ADCIN1/IOPA1	73	I/O	Bidirectional digital I/O. Analog input to the first ADC. ADCIN1/IOPA1 is configured as a digital input by all device resets.				
ADCIN9/IOPA2	90	I/O	Bidirectional digital I/O. Analog input to the second ADC. ADCIN9/IOPA2 is configured as a digital input by all device resets.				
ADCIN8/IOPA3	91	I/O	Bidirectional digital I/O. Analog input to the second ADC. ADCIN8/IOPA3 is configured as a digital input by all device resets.				
PWM7/CMP7/IOPB0	100	I/O/Z	Bidirectional digital I/O. Simple compare/PWM 1 output. The state of PWM7/CMP7/IOPB0 is determined by the simple compare/PWM and the simple action control register (SACTR). It goes to the high-impedance state when unmasked PDPINT goes active low. PWM7/CMP7/IOPB0 is configured as a digital input by all device resets.				
PWM8/CMP8/IOPB1	101	I/O/Z	Bidirectional digital I/O. Simple compare/PWM 2 output. The state of PWM8/CMP8/IOPB1 is determined by the simple compare/PWM and the SACTR. It goes to the high-impedance state when unmasked PDPINT goes active low. PWM8/CMP8/IOPB1 is configured as a digital input by all device resets.				
PWM9/CMP9/IOPB2	102	I/O/Z	Bidirectional digital I/O. Simple compare/PWM 3 output. The state of PWM9/CMP9/IOPB2 is determined by the simple compare/PWM and SACTR. It goes to the high-impedance state when unmasked PDPINT goes active low. PWM9/CMP9/IOPB2 is configured as a digital input by all device resets.				

SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

Terminal Functions (Continued)

TERMINAL NAME NO.		TYPET	DESCRIPTION				
	BIT I/O AND SHARED FUNCTIONS PINS (CONTINUED)						
T1PWM/T1CMP/ IOPB3	105	I/O/Z	Bidirectional digital I/O. Timer 1 compare output. T1PWM/T1CMP/IOPB3 goes to the high- impedance state when unmasked PDPINT goes active low. This pin is configured as a digital input by all device resets.				
T2PWM/T2CMP/ IOPB4	106	I/O/Z	Bidirectional digital I/O. Timer 2 compare output. T2PWM/T2CMP/IOPB4 goes to the high- impedance state when unmasked PDPINT goes active low. This pin is configured as a digital input by all device resets.				
T3PWM/T3CMP/ IOPB5	107	I/O/Z	Bidirectional digital I/O. Timer 3 compare output. T3PWM/T3CMP/IOPB5 goes to the high- impedance state when unmasked PDPINT goes active low. This pin is configured as a digital input by all device resets.				
TMRDIR/IOPB6	108	I/O	Bidirectional digital I/O. Direction signal for the timers. Up-counting direction if TMRDIR/IOPB6 is low, down-counting direction if this pin is high. This pin is configured as a digital input by all device resets.				
TMRCLK/IOPB7	109	I/O	Bidirectional digital I/O. External clock input for general-purpose timers. This pin is configured as a digital input by all device resets.				
ADCSOC/IOPC0	63	I/O	Bidirectional digital I/O. External start of conversion input for ADC. This pin is configured as a digital input by all device resets.				
CAP1/QEP1/IOPC4	67	I/O	Bidirectional digital I/O. Capture 1 or QEP 1 input. This pin is configured as a digital input by all device resets.				
CAP2/QEP2/IOPC5	68	I/O	Bidirectional digital I/O. Capture 2 or QEP 2 input. This pin is configured as a digital input by all device resets.				
CAP3/IOPC6	69	I/O	Bidirectional digital I/O. Capture 3 input. This pin is configured as a digital input by all device resets.				
CAP4/IOPC7	70	I/O	Bidirectional digital I/O. Capture 4 input. This pin is configured as a digital input by all device resets.				
XF/IOPC2	65	I/O	Bidirectional digital I/O. External flag output (latched software-programmable signal). XF is used for signaling other processors in multiprocessing configurations or as a general-purpose output pin. This pin is configured as an external flag output by all device resets.				
BIO/IOPC3	66	I/O	Bidirectional digital I/O. Branch control input. BIO is polled by the BIOZ instruction. If BIO is low, the CPU executes a branch. If BIO is not used , it should be pulled high. This pin is configured as a branch-control input by all device resets.				
CLKOUT/IOPC1	64	I/O	Bidirectional digital I/O. Clock output. Clock output is selected by the CLKSRC bits in the SYSCR register. This pin is configured as a DSP clock output by a power-on reset.				
		SERIAL C	OMMUNICATIONS INTERFACE (SCI) AND BIT I/O PINS				
SCITXD/IO	44	I/O	SCI asynchronous serial port transmit data, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.				
SCIRXD/IO	43	I/O	SCI asynchronous serial port receive data, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.				



Terminal Functions (Continued)

NAME NO. SERIAL PERIPHERAL INTERFACE (SPI) AND BIT //O PINS SPISIMO/IO 45 I/O SPI slave in, master out, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPISOM/IO 48 I/O SPI slave out, master in, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPISOM/IO 48 I/O SPI slave out, master in, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPISTE/IO 51 I/O SPI slave out master in, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. CMMARCMP2 95 V/O SPI slave out master in or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. VMMI/CMP1 94 V/O SPI slave out master in or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. VMMI/CMP2 95 V/O Compare or PWM outputs. The state of these pins is determined by the compare/PWM and the full action corrutor legister (ACTR). CMP1-CMP6 go to the high-impedance state when unmasked PDPINT geges adure by all advice is and status bits. RT 0/O O/Z Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS i	TERMINAL		TYPET	DESCRIPTION			
SPEKAL PERMITIVAL INTERVACE (SPI AND BIT ND PINS SPISIMO/IO 45 I/O SPI slave in, master out, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPISIMO/IO 48 I/O SPI slave out, master out, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPICLK/IO 49 I/O SPI clock, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPISTE/IO 51 I/O SPI slave transmit enable (optional), or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. COMPARE SIGNALS Compare or PVMM outputs. The state of these pins is determined by the compare/PVM and the full action control register (ACTR). CMP1-CMP6 go to the high-impedance state when un- montexed PDPINT geose active iow. MVMMC/MP5 98 Compare or PVM outputs. The state of these pins is determined by the compare/PVM and the full action control register (ACTR). CMP1-CMP6 go to the high-impedance once the internal clock is stable (see Figure 31 and Figure 32). MVMMC/MP5 98 Compare or PVM outputs. The state of these pins is determined by the compare/PVM and the full action control registers and status bits. RS 35 V/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is bronght no a high level, execution begins at locatio	NAME	NO.					
SPISIMO/IO 45 V/O SPI slave in, master out, or general-purpose bidirectional V/O. This pin is configured as a digital input by all device resets. SPISOM//O 48 V/O SPI slave out, master in, or general-purpose bidirectional V/O. This pin is configured as a digital input by all device resets. SPICLK/IO 49 V/O SPI clock, or general-purpose bidirectional V/O. This pin is configured as a digital input by all device resets. SPISTE/IO 51 V/O SPI slave transmit enable (optional), or general-purpose bidirectional V/O. This pin is configured as a digital input by all device resets. VVMV1/CMP1 94 Compare or PWM outputs. The state of these pins is determined by the compare/PWM and the full action control register CACTB). CMP1-CMP6 go to the high-impedance state when unmasked PDPINT goes active low. VVMV4/CMP3 97 Q/Z Compare or PWM outputs. The state of these pins are high-impedance once the internal clock is stable (see Figure 31 and Figure 32). VVMV4/CMP6 99 Q/Z Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bins. RS 35 V//O Reset input. When NM is activated, the device is interrupted regardless of the state of the INTM bit of the INTM bit of the status registers and status bits.	SERIAL PERIPHERAL INTERFACE (SPI) AND BIT I/O PINS						
SPISOM/I/O 48 I/O SPI slave out, master in, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPICLK/IO 49 I/O SPI clock, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPISTE/IO 51 I/O SPI slave transmit enable (optional), or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. VMMI/CMP1 94 PWMM2/CMP2 95 96 O/Z OVE Compare or PWM outputs. The state of these pins is determined by the compare/PWM and the full action control register (ACTR). CMP1-CMP6 go to the high-impedance state when un- masked PDPINT gene active low. After power up and PORESET is high, the PWM/CMP pins are high-impedance once the internal clock is stable (see Figure 31 and Figure 32). INTERRUPT AND MISCELLANEOUS SIGNALS RS 35 MP/MC 37 1 MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is select dI. If its high, external program memory is select. NMI 40 1 Normaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. MI has programmable polarity. PORESET 41 Neweron reset	SPISIMO/IO	45	I/O	SPI slave in, master out , or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.			
SPICLK/IO 49 I/O SPI clock, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. SPISTE/IO 51 I/O SPI stave transmit enable (optional), or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. COMPARE SIGNALS COMPARE SIGNALS PWM4/CMP1 94 PWM3/CMP2 95 PWM3/CMP3 96 PVM4/CMP4 97 PVM4/CMP5 99 PVM6/CMP6 93 PVM6/CMP6 94 I Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is to zero/ various registers and status bits. RS 35	SPISOMI/IO	48	I/O	SPI slave out, master in, or general-purpose bidirectional I/O. This pin is configured as a digita input by all device resets.			
SPISTE/IO 51 I/O SPI slave transmit enable (optional), or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. COMPARE SIGNALS COMPARE SIGNALS PVMM3/CMP2 95 Compare or PVM outputs. The state of these pins is determined by the compare/PVM and the full action control register (ACTR). CMP1-CMP6 go to the high-impedance state when unmasked PDPINT goes active low. After power up and PORESET is high, the PVM/CMP pins are high-impedance once the internal clock is stable (see Figure 31 and Figure 32). INTERUPT AND MISCELLANEOUS SIGNALS RS 35 I/O Reset input. RS causes the TM3320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC informoroessory/microcomputer yealed. If MP/MC is low, internal program memory is selected. If it is high, external program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. NIT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. <	SPICLK/IO	49	I/O	SPI clock, or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.			
COMPARE SIGNALS PWM1/CMP1 94 PWM2/CMP2 95 95 96 PWM3/CMP3 O/Z Compare or PWM outputs. The state of these pins is determined by the compare/PWM and the full action control register (ACTR), CMP1-CMP6 go to the high-impedance state when un- masked PDPINT goes active low. After power up and PORESET is high, the PWM/CMP pins are high-impedance once the internal clock is stable (see Figure 31 and Figure 32). INTERRUPT AND MISCELLANEOUS SIGNALS INTERRUPT AND MISCELLANEOUS SIGNALS RS 35 I/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC is low, internal program memory is selected. If it is high, external program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I POwer-on reset.PORESET acueses the TMS320F240 to terminate execution and sets PC = 0. When PORESET in target interrupt no. 1. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT1 53 I External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.	SPISTE/IO	51	I/O	SPI slave transmit enable (optional), or general-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.			
PWM1/CMP1 94 PVM3/CMP2 95 PVM4/CMP3 96 PVM3/CMP3 C/Z Compare or PVM outputs. The state of these pins is determined by the compare/PVM and the full action control register (ACTR). CMP1-CMP6 go to the high-impedance state when un- masked PDPINT goes active low. After power up and PORESET is high, the PVM/CMP pins are high-impedance once the internal clock is stable (see Figure 31 and Figure 32). RS 35 I/O INTERRUPT AND MISCELLANEOUS SIGNALS RS 35 I/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I PORESET falses the TMS320F240 to terminate execution and sets PC = 0. When <u>PORESET</u> is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET falses (or sets to zero) the same registers and status bits as RS. In addi- tion, PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a ligh level, execution begins at location zero of program memor				COMPARE SIGNALS			
PWM2/CMP2 95 Compare or PVM0 outputs. The state of mess tabetermined by the compare/PVM and the full action control register ACTR). CMP1-CMP6 go to the high-impedance state when un-masked PDPINT goes active low. PVM4/CMP4 97 PVM6/CMP5 98 PVM6/CMP5 98 PVM6/CMP5 98 PVM6/CMP5 98 PVM6/CMP5 99 INTERRUPT AND MISCELLANEOUS SIGNALS RS 35 IVO Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 1 MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. NMI 40 1 Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the status registers. PORESET 41 1 Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET initializes the PLL control registers. XINT1 53 1 External user interrupt no. 1 XINT2/IO 54 I/O	PWM1/CMP1	94					
PWMA/CMP3 96 O/Z PWMA/CMP4 97 PWMA/CMP5 98 PWMS/CMP5 98 PWMS/CMP6 99 Internal addressing and PDPINT goes active low. After power up and PORESET is high, the PWM/CMP pins are high-impedance once the internal clock is stable (see Figure 31 and Figure 32). INTERRUPT AND MISCELLANEOUS SIGNALS RS 35 I/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) selected. IMP/MC is low, internal program memory is selected. selected. If it is high, external program memory is selected. selected. If it is brought to a high level, execution begins at location zero of program memory is selected. PORESET 41 I Nonmaskable interrupt. When NMI is activated, the device is interrupt regardless of the state of the INTM bit of the status register. NMI has programmable polarity. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is c	PWM2/CMP2	95		Compare of PWW outputs. The state of these pins is determined by the compare/PWW and			
PWMA/CMP4 97 Intervent of the state PDFINI gues active town. PWMA/CMP5 98 PWMA/CMP6 99 INTERRUPT AND MISCELLANEOUS SIGNALS RS 35 I/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory. RS affects (or sets to zero) various registers and status bits. MNI 40 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution and sets PC = 0. When PGRESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution all/O. This pin is configured as a digital input by all device resets. XINT1 53 I Exterma	PWM3/CMP3	96	0/7	Ine full action control register (ACTR). CMP I-CMP6 go to the high-impedance state when un-			
PWM6/CMP5 98 Finite power of and registers Intermal clock is stable (see Figure 31 and Figure 32). RS 35 I/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Power-on reset. PORESET allects (or sets to zero) the same registers and status bits as RS. In addition, PORESET is brought to a high level, execution begins at location zero of program memory is selected. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impe	PWM4/CMP4	97	0/2	After power up and PORESET is high the PW/M/CMP pins are high-impedance once the			
PWM6/CMP6 99 Interfet dock is static (see Fight ST and Fight St): INTERRUPT AND MISCELLANEOUS SIGNALS Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brough to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. If it is high, external program memory is selected. NMI 40 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. PORESET 41 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. VNII 40 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. VMNI 40 I Normaskable interrupt. Nen NMI is activated, the device is interrupt rogram memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets	PWM5/CMP5	98		internal clock is stable (see Figure 31 and Figure 32)			
INTERRUPT AND MISCELLANEOUS SIGNALS RS 35 I/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. If it is high, external program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 52 I Maskable power-drive protection interrupt. If PDPINT Sumasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This	PWM6/CMP6	99					
RS 35 I/O Reset input. RS causes the TMS320F240 to terminate execution and sets PC = 0. When RS is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. If it is high, external program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. VTAL2 57<			11	ITERRUPT AND MISCELLANEOUS SIGNALS			
RS 35 I/O is brought to a high level, execution begins at location zero of program memory. RS affects (or sets to zero) various registers and status bits. MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. NMI 40 I MP/MC (microprocessor/microcomputer) selected. MP/MC is low, internal program memory is selected. PORESET 41 I Power-on reset. PORESET causes the TMS3205/240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is brought to a high level, execution level. This pin site configured as a digital input by all device resets. XINT2/IO54<			I/O	Reset input. \overline{RS} causes the TMS320F240 to terminate execution and sets PC = 0. When \overline{RS}			
MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET is to cave the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XTAL2 57 O PLL oscillator output. XTAL1/CLKIN is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal when the device is noplatow bypass mode (OSCBYP ≤ VIL). This pin go	RS	35		is brought to a high level, execution begins at location zero of program memory. RS affects (or			
MP/MC 37 I MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET initializes the PLL control registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. YTAL2 57 O Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low.				sets to zero) various registers and status bits.			
MIP/MC 37 1 selected. If it is high, external program memory is selected. NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ V _L). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLK	140	07		MP/MC (microprocessor/microcomputer) select. If MP/MC is low, internal program memory is			
NMI 40 I Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 I Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP < VIL). This pin goes in the high-impedance state when EMU1/OFF is active low.	MP/MC	37		selected. If it is high, external program memory is selected.			
NMI 40 1 of the INTM bit of the status register. NMI has programmable polarity. PORESET 41 1 Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 1 External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), This pin can be left unconnected in oscillator bypass mode (OSCBYP < VIL).				Nonmaskable interrupt. When NMI is activated, the device is interrupted regardless of the state			
PORESET 41 I Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0. When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). OSCERYP 56 I Bypass on-chip oscillator if low	NMI	40		of the INTM bit of the status register. NMI has programmable polarity.			
PORESET 41 I When PORESET is brought to a high level, execution begins at location zero of program memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ V _{IL}). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ V _{IL}). OSCBYP 56 I Bypass on-chip oscillator if low				Power-on reset. PORESET causes the TMS320F240 to terminate execution and sets PC = 0.			
PORESET 41 1 memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addition, PORESET initializes the PLL control registers. XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. CLOCK SIGNALS CLOCK SIGNALS XTAL2 57 O VITAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (OSCBYP ≤ V _L). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (OSCBYP ≤ V _L). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z Bynass on-chip oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (OSCBYP ≤ V _L). OSCBYP	DODECET	44	I	When PORESET is brought to a high level, execution begins at location zero of program			
tion, $\overrightarrow{PORESET}$ initializes the PLL control registers.XINT153IXINT2/IO54I/OExternal user interrupt no. 1.XINT3/IO54I/OExternal user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.XINT3/IO55I/OExternal user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.XINT3/IO55I/OExternal user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.PDPINT52IMaskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state.CLOCK SIGNALSXTAL257OPLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low.XTAL1/CLKIN58I/ZPLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL).OSCBYP56I	PORESEI	41		memory. PORESET affects (or sets to zero) the same registers and status bits as RS. In addi-			
XINT1 53 I External user interrupt no. 1 XINT2/IO 54 I/O External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. VELOCK SIGNALS VL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). OSCBYP 56 I Bypass on-chip oscillator if low				tion, PORESET initializes the PLL control registers.			
XINT2/IO54I/OExternal user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.XINT3/IO55I/OExternal user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets.PDPINT52IMaskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state.VCLOCK SIGNALSXTAL257OPLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP \leq VIL). This pin goes in the high-impedance state when EMU1/OFF is active low.XTAL1/CLKIN58I/ZPLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP \leq VIL).QSCBYP56IBypass on-chip oscillator is poscillator input.	XINT1	53	I	External user interrupt no. 1			
XINT2/IO 54 I/O digital input by all device resets. XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. VEXTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). QSCBYP 56 I Bypass on-chip oscillator if low		E A	1/0	External user interrupt no. 2. General-purpose bidirectional I/O. This pin is configured as a			
XINT3/IO 55 I/O External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. VEXTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). QSCBYP 56 I Bypass on-chip oscillator if low	XIN12/IO	54	1/0	digital input by all device resets.			
XIN13/IO 55 I/O digital input by all device resets. PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. CLOCK SIGNALS XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). QSCBYP 56 I Bypass on-chip oscillator if low	VINTO/IO		1/0	External user interrupt no. 3. General-purpose bidirectional I/O. This pin is configured as a			
PDPINT 52 I Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the timer compare outputs immediately go to the high-impedance state. CLOCK SIGNALS XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). OSCBYP 56 I Bxpass on-chip oscillator if low	XINT3/IO	55	1/0	digital input by all device resets.			
PDPINT 52 1 timer compare outputs immediately go to the high-impedance state. CLOCK SIGNALS XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). OSCBYP 56 I Bypass on-chip oscillator if low	DDDINT	50		Maskable power-drive protection interrupt. If PDPINT is unmasked and it goes active low, the			
CLOCK SIGNALS XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). OSCBYP 56 I Bypass on-chip oscillator if low	PDPINI	52	1	timer compare outputs immediately go to the high-impedance state.			
XTAL2 57 O PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6). This pin can be left unconnected in oscillator bypass mode (OSCBYP ≤ VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ VIL). OSCBYP 56 I Bypass on-chip oscillator if low			•	CLOCK SIGNALS			
XTAL2 57 O mode (CLKMD[1:0] = 1x, CKCR0.7-6). This pin can be left unconnected in oscillator bypass mode (OSCBYP \leq VIL). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7-6), or is connected to an external clock source in oscillator bypass mode (OSCBYP \leq VIL). QSCBYP 56 I Bypass on-chip oscillator if low				PLL oscillator output. XTAL2 is tied to one side of a reference crystal when the device is in PL			
XTAL2 57 O mode (OSCBYP ≤ V _{IL}). This pin goes in the high-impedance state when EMU1/OFF is active low. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ V _{IL}). OSCBYP 56 I Bypass on-chip oscillator if low	VTALO		~	mode (CLKMD[1:0] = 1x, CKCR0.7-6). This pin can be left unconnected in oscillator bypass			
Iow. XTAL1/CLKIN 58 I/Z PLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP ≤ V _{IL}). OSCBYP 56 I/Z Bypass on-chip oscillator if low	XTAL2	57	0	mode (OSCBYP \leq VII). This pin goes in the high-impedance state when EMU1/OFF is active			
XTAL1/CLKIN58I/ZPLL oscillator input. XTAL1/CLKIN is tied to one side of a reference crystal in PLL mode (CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode ($\overline{OSCBYP} \leq V_{ L}$).OSCBYP56LBypass on-chip oscillator if low	low.						
XTAL1/CLKIN58I/Z(CLKMD[1:0] = 1x, CKCR0.7–6), or is connected to an external clock source in oscillator bypass mode (OSCBYP $\leq V_{ L}$).OSCBYP56IBypass on-chip oscillator if low	PLL oscillator input XTAL1/CLKIN is tied to one side of a reference crystal in PLL in						
$\frac{ }{ } = \frac{ }{ } = \frac{ }{ } = \frac{ }{ } = \frac{ }{ } = \frac{ }{ } = \frac{ }{ } = \frac{ }{ } = \frac{ }{ } = \frac{ }{ $	XTAL1/CLKIN	58	I/Z	(CLKMD[1:0] = 1x, CKCR0.7-6), or is connected to an external clock source in oscillator			
OSCBYP 56 L Bypass on-chip oscillator if low			"_	bypass mode ($OSCBYP \le V_{II}$).			
	OSCBYP	56	I	Bypass on-chip oscillator if low			



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

Terminal Functions (Continued)

TERM NAME	IINAL NO.	TYPE [†]	DESCRIPTION			
SUPPLY SIGNALS						
CVSS	8	I	Digital core logic ground reference			
VSS	3 14 20 29 46 59 61 71 92 104 113 120	I	Digital logic ground reference			
V _{SSA}	87	I	Analog ground reference			
DVDD	2 13 21 47 62 93 103 121	1	Digital I/O logic supply voltage			
CV _{DD}	7 60	I	Digital core logic supply voltage			
VCCA	84	I	Analog supply voltage			
VREFHI	85	I	ADC analog voltage reference high			
VREFLO	86	I	ADC analog voltage reference low			
			TEST SIGNALS			
тск	30	I	JTAG test clock. TCK is normally a free-running clock signal with a 50% duty cycle. The changes on test-access port (TAP) input signals (TMS and TDI) are clocked into the TAP controller, instruction reg- ister, or selected test data register of the C2xx core on the rising edge of TCK. Changes at the TAP output signal (TDO) occur on the falling edge of TCK.			
TDI	31	I	JTAG test data input (TDI). TDI is clocked into the selected register (instruction or data) on a rising edge of TCK.			
TDO	34	O/Z	JTAG test data output (TDO). The contents of the selected register (instruction or data) are shifted out of TDO on the falling edge of TCK. TDO is in the high-impedance state when OFF is active low.			
TMS	33	I	JTAG test mode select. This serial control input is clocked into the TAP controller on the rising edge of TCK.			



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

ТЕРМИ			
		TYPE [†]	DESCRIPTION
NAME	NO.		
			TEST SIGNALS (CONTINUED)
TRST	32	I	JTAG test reset with internal pulldown. TRST, when driven high, gives the scan system control of the operations of the device. If this signal is not connected or driven low, the device operates in its functional mode, and the test reset signals are ignored.
EMU0	38	I/O/Z	Emulator pin 0. When TRST is driven low, EMU0 must be high for activation of the /OFF condition. When TRST is driven high, EMU0 is used as an interrupt to or from the emulator system and is defined as input/output through the scan.
EMU1/OFF	39	I/O/Z	Emulator pin 1/disable all outputs. When TRST is driven high, EMU1/OFF is used as an interrupt to or from the emulator system and is defined as input/output through JTAG scan. When TRST is driven low, this pin is configured as OFF. When EMU1/OFF is active low, it puts all output drivers in the high-impedance state. OFF is used exclusively for testing and emulation purposes (not for multiprocessing applications); therefore, for OFF condition, the following conditions apply: TRST = low, EMU0 = high, EMU1/OFF = low
RESERVED	42		Reserved for test. This pin has an internal pulldown and must be left unconnected.

Terminal Functions (Continued)



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

functional block diagram





SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

description (continued)

ON-	CHIP MEMORY (W	ORDS)			
RAM		FLASH EEPROM	POWER SUPPLY	CYCLE TIME	PACKAGE TYPE BIN COUNT
DATA	DATA/PROG	PROG	(*)	(115)	
288	256	16K	5	50	PQ 132–P

Table 1. Characteristics of the TMS320F240 DSP Controller

architectural overview

The functional block diagram provides a high-level description of each component in the F240 DSP controller. The TMS320F240 device is composed of three main functional units: a C2xx DSP core, internal memory, and peripherals. In addition to these three functional units, there are several system-level features of the F240 that are distributed. These system features include the memory map, device reset, interrupts, digital input/output (I/O), clock generation, and low-power operation.

system-level functions

device memory map

The TMS320F240 implements three separate address spaces for program memory, data memory, and I/O. Each space accommodates a total of 64K 16-bit words. Within the 64K words of data space, the 256 to 32K words at the top of the address range can be defined to be external global memory in increments of powers of two, as specified by the contents of the global memory allocation register (GREG). Access to global memory is arbitrated using the global memory bus request (BR) signal.

On the F240, the first 96 (0–5Fh) data memory locations are either allocated for memory-mapped registers or are reserved. This memory-mapped register space contains various control and status registers including those for the CPU.

All the on-chip peripherals of the F240 device are mapped into data memory space. Access to these registers is made by the CPU instructions addressing their data-memory locations. Figure 1 shows the memory map.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



Figure 1. TMS320F240 Memory Map



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

peripheral memory map

The TMS320F240 system and peripheral control register frame contains all the data, status, and control bits to operate the system and peripheral modules on the device (excluding the event manager).

....

				Hex
			Reserved	0000
			Interrupt-Mask Register	0003
Hex 0000 —			Global-Memory Allocation Register	0005
	Memory-Mapped Registers and Reserved		Interrupt Flag Register	0006
005F 0060 007F 0080	On-Chip DARAM B2		Emulation Registers and Reserved	0007 005F
	Reserved		lliegal	7000-700F
01FF			System Configuration and Control Registers	7010–701F
0200	On-Chip DARAM B0 (CNF = 0)		Watchdog Timer and	 7020–702F
02FF	Reserved (CNF = 1)	_ /		7020-7025
0300	On-Chip		SPI	
03FF		- /	SCI	7040-704F
	Describe		lllegal	7060-706F
	Reserved		External-Interrupt Registers	7070-707F
07FF 0800	Wawal	-/	lliegal	7080-708F
6FFF	illegal		Digital-I/O Control Registers	
73FF	Peripheral Frame 1		lllegal	70A0-73FF
7400	Peripheral Frame 2			_
743F 7440 77FF	Reserved		General-Purpose Timer Registers	7400–7400
7FFF	lllegal		Reserved	740D-7410
8000			Compare, PWM, and Deadband Registers	7411–7410
			Reserved	741D-741
	External	\backslash	Capture & QEP Registers	7420-7426
			Reserved	7427–742E
			Interrupt Mask, Vector and Flag Registers	742C-7434
		\backslash	Reserved	7435–743F





digital I/O and shared pin functions

A total of 28 pins are shared between primary functions and I/Os. These pins are divided into two groups:

- Group1 Primary functions shared with I/Os belonging to dedicated I/O ports, Port A, Port B, and Port C.
- Group2 Primary functions belonging to peripheral modules which also have a built-in I/O feature as a secondary function (for example, SCI, SPI, external interrupts, and PLL clock modules).

description of group1 shared I/O pins

The control structure for Group1 type shared I/O pins is shown in Figure 3. The only exception to this configuration is the CLKOUT/IOPC1 pin. In Figure 3, each pin has three bits that define its operation:

- Mux control bit this bit selects between the primary function (1) and I/O function (0) of the pin.
- I/O direction bit if the I/O function is selected for the pin (mux control bit is set to 0), this bit determines whether the pin is an input (0) or an output (1).
- I/O data bit if the I/O function is selected for the pin (mux control bit is set to 0) and the direction selected is an input, data is read from this bit; if the direction selected is an output, data is written to this bit.

The mux control bit, I/O direction bit, and I/O data bit are in the I/O control registers.



Figure 3. Shared Pin Configuration

A summary of Group1 pin configurations and associated bits is shown in Table 2.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

description of group1 shared I/O pins (continued)

	MUX CONTROL	PIN FUNCTION SELECTED		I/O PORT DATA AND DIRECTION [†]		
PIN #	(name.bit #)	(CRx.n = 1)	(CRx.n = 0)	REGISTER	DATA BIT #	DIR BIT #
72	OCRA.0	ADCIN0	IOPA0	PADATDIR	0	8
73	OCRA.1	ADCIN1	IOPA1	PADATDIR	1	9
90	OCRA.2	ADCIN9	IOPA2	PADATDIR	2	10
91	OCRA.3	ADCIN8	IOPA3	PADATDIR	3	11
100	OCRA.8	PWM7/CMP7	IOPB0	PBDATDIR	0	8
101	OCRA.9	PWM8/CMP8	IOPB1	PBDATDIR	1	9
102	OCRA.10	PWM9/CMP9	IOPB2	PBDATDIR	2	10
105	OCRA.11	T1PWM/T1CMP	IOPB3	PBDATDIR	3	11
106	OCRA.12	T2PWM/T2CMP	IOPB4	PBDATDIR	4	12
107	OCRA.13	T3PWM/T3CMP	IOPB5	PBDATDIR	5	13
108	OCRA.14	TMRDIR	IOPB6	PBDATDIR	6	14
109	OCRA.15	TMRCLK	IOPB7	PBDATDIR	7	15
63	OCRB.0	ADCSOC	IOPC0	PCDATDIR	0	8
64	SYSCR.7–6					
	0 0	IOPC ²	1	PCDATDIR	1	9
	0 1	WDCL	К	—	—	
	10	SYSCL	K	—	—	-
	11	CPUCL	.K	—	—	-
65	OCRB.2	IOPC2	XF	PCDATDIR	2	10
66	OCRB.3	IOPC3	BIO	PCDATDIR	3	11
67	OCRB.4	CAP1/QEP1	IOPC4	PCDATDIR	4	12
68	OCRB.5	CAP2/QEP2	IOPC5	PCDATDIR	5	13
69	OCRB.6	CAP3	IOPC6	PCDATDIR	6	14
70	OCRB.7	CAP4	IOPC7	PCDATDIR	7	15

Table 2. Group1 Shared Pin Configurations

[†] Valid only if the I/O function is selected on the pin.



description of group2 shared I/O pins

Group2 shared pins belong to peripherals that have built-in general-purpose I/O capability. Control and configuration for these pins are achieved by setting the appropriate bits within the control and configuration registers of the peripherals. Table 3 lists the Group2 shared pins.

PIN #	PRIMARY FUNCTION	REGISTER	ADDRESS	PERIPHERAL MODULE
43	SCIRXD	SCIPC2	705Eh	SCI
44	SCITXD	SCIPC2	705Eh	SCI
45	SPISIMO	SPIPC2	704Eh	SPI
48	SPISOMI	SPIPC2	704Eh	SPI
49	SPICLK	SPIPC1	704Dh	SPI
51	SPISTE	SPIPC1	704Dh	SPI
54	XINT2	XINT2CR	7078h	External Interrupts
55	XINT3	XINT3CR	707Ah	External Interrupts

Table 3. Group2 Shared Pin Configurations

digital I/O control registers

Table 4 lists the registers available to the digital I/O module. As with other F240 peripherals, the registers are memory-mapped to the data space.

ADDRESS	REGISTER	NAME
7090h	OCRA	I/O mux control register A
7092h	OCRB	I/O mux control register B
7098h	PADATDIR	I/O port A data and direction register
709Ah	PBDATDIR	I/O port B data and direction register
709Ch	PCDATDIR	I/O port C data and direction register

Table 4. Addresses of Digital I/O Control Registers

device reset and interrupts

The TMS320F240 software-programmable interrupt structure supports flexible on-chip and external interrupt configurations to meet real-time interrupt-driven application requirements. The F240 recognizes three types of interrupt sources:

- **Reset** (hardware- or software-initiated) is unarbitrated by the CPU and takes immediate priority over any other executing functions. All maskable interrupts are disabled until the reset service routine enables them.
- Hardware-generated interrupts are requested by external pins or by on-chip peripherals. There are two types:
 - External interrupts are generated by one of five external pins corresponding to the interrupts XINT1, XINT2, XINT3, PDPINT, and NMI. The first four can be masked both by dedicated enable bits and by the CPU's interrupt mask register (IMR), which can mask each maskable interrupt line at the DSP core. NMI, which is not maskable, takes priority over peripheral interrupts and software-generated interrupts. It can be locked out only by an already executing NMI or a reset.
 - Peripheral interrupts are initiated internally by these on-chip peripheral modules: the event manager, SPI, SCI, watchdog/real-time interrupt (WD/RTI), and ADC. They can be masked both by enable bits for each event in each peripheral and by the CPU's IMR, which can mask each maskable interrupt line at the DSP core.



device reset and interrupts (continued)

- Software-generated interrupts for the F240 device include:
 - The INTR instruction. This instruction allows initialization of any F240 interrupt with software. Its
 operand indicates to which interrupt vector location the CPU branches. This instruction globally
 disables maskable interrupts (sets the INTM bit to 1).
 - The NMI instruction. This instruction forces a branch to interrupt vector location 24h, the same location used for the nonmaskable hardware interrupt NMI. NMI can be initiated by driving the NMI pin low or by executing an NMI instruction. This instruction globally disables maskable interrupts.
 - The TRAP instruction. This instruction forces the CPU to branch to interrupt vector location 22h. The TRAP instruction does *not* disable maskable interrupts (INTM is not set to 1); therefore, when the CPU branches to the interrupt service routine, that routine can be interrupted by the maskable hardware interrupts.
 - An emulator trap. This interrupt can be generated with either an INTR instruction or a TRAP instruction.

reset

The reset operation ensures an orderly startup sequence for the device. There are five possible causes of a reset, as shown in Figure 4. Three of these causes are internally generated; the other two causes, the $\overline{\text{RS}}$ and $\overline{\text{PORESET}}$ pins, are controlled externally.



Figure 4. Reset Signals

The five possible reset signals are generated as follows:

- Watchdog timer reset. A watchdog-timer-generated reset occurs if the watchdog timer overflows or an improper value is written to either the watchdog key register or the watchdog control register. (Note that when the device is powered on, the watchdog timer is automatically active.)
- **Software-generated reset.** This is implemented with the system control register (SYSCR). Clearing the RESET0 bit (bit 14) or setting the RESET1 bit (bit 15) causes a system reset.
- Illegal address reset. The system and peripheral module control register frame address map contains unimplemented address locations in the ranges labeled illegal. Any access to an address located in the Illegal ranges generate an illegal-address reset.
- **Reset pin active.** To generate an external reset pulse on the RS pin, a low-level pulse duration of as little as a few nanoseconds is usually effective; however, pulses of one SYSCLK cycle are necessary to ensure that the device recognizes the reset signal.
- **Power-on reset pin active.** To generate a power-on reset pulse on the **PORESET** pin, a low-level pulse of one SYSCLK cycle is necessary to ensure that the device recognizes the reset signal.

Once a reset source is activated, the external \overline{RS} pin is driven (active) low for a minimum of eight SYSCLK cycles. This allows the TMS320F240 device to reset external system components. Additionally, if a brown-out condition (V_{CC} < V_{CC}min for several microseconds causing PORESET to go low) occurs or the \overline{RS} pin is held low, then the reset logic holds the device in a reset state for as long as these actions are active.



reset (continued)

The occurrence of a reset condition causes the TMS320F240 to terminate program execution and affects various registers and status bits. During a reset, RAM contents remain unchanged, and all control bits that are affected by a reset are initialized to their reset state. In the case of a power-on reset, the PLL control registers are initialized to zero. The program needs to recognize power-on resets and configure the PLL for correct operation.

After a reset, the program can check the power-on reset flag (PORST flag, SYSSR.15), the illegal address flag (ILLADR flag, SYSSR.12), the software reset flag (SWRST flag, SYSSR.10), and the watchdog reset flag (WDRST flag, SYSSR.9) to determine the source of the reset. A reset does not clear these flags.

 $\overline{\text{RS}}$ and $\overline{\text{PORESET}}$ must be held low until the clock signal is valid and V_{CC} is within the operating range. In addition, $\overline{\text{PORESET}}$ must be driven low when V_{CC} drops below the minimum operating voltage.

hardware-generated interrupts

All the hardware interrupt lines of the DSP core are given a priority rank from 1 to 10 (1 being highest). When more than one of these hardware interrupts is pending acknowledgment, the interrupt of highest rank gets acknowledged first. The others are acknowledged in order after that. Of those ten lines, six are for maskable interrupt lines (INT1–INT6) and one is for the nonmaskable interrupt (NMI) line. INT1–INT6 and NMI have the priorities shown in Table 5.

INTERRUPT	PRIORITY AT THE DSP CORE
RESET	1
TI RESERVED [†]	2
NMI	3
INT1	4
INT2	5
INT3	6
INT4	7
INT5	8
INT6	9
TI RESERVED [†]	10

Table 5. Interrupt Priorities at the Level of the DSP Core

[†]TI Reserved means that the address space is reserved for Texas Instruments.

The inputs to these lines are controlled by the system module and the event manager as summarized in Table 6 and shown in Figure 5.

Table 6. Interrupt Lines Controlled by the System Module and Event Manager

PERIPHERAL	INTERRUPT LINES
System Module	INT1 INT5 NMI INT6
Event Manager	INT2 INT3 INT4



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

hardware-generated interrupts (continued)



Figure 5. DSP Interrupt Structure

At the level of the system module and the event manager, each of the maskable interrupt lines (INT1–INT6) is connected to multiple maskable interrupt sources. Sources connected to interrupt line INT1 are called Level 1 interrupts; sources connected to interrupt line INT2 are called Level 2 interrupts; and so on. For each interrupt line, the multiple sources also have a set priority ranking. The source with the highest priority has its interrupt request responded to by the DSP core first.

Figure 6 shows the sources and priority ranking for the interrupts controlled by the system module. For each interrupt chain, the interrupt source of highest priority is at the top. Priority decreases from the top of the chain to the bottom. Figure 7 shows the interrupt sources and priority ranking for the event manager interrupts.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



Figure 6. System Module Interrupt Structure



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002







hardware-generated interrupts (continued)

Each of the interrupt sources has its own control register with a flag bit and an enable bit. When an interrupt request is received, the flag bit in the corresponding control register is set. If the enable bit is also set, a signal is sent to arbitration logic, which can simultaneously receive similar signals from one or more of the other control registers. The arbitration logic compares the priority level of competing interrupt requests, and it passes the interrupt of highest priority to the CPU. The corresponding flag is set in the interrupt flag register (IFR), indicating that the interrupt is pending. The CPU then must decide whether to acknowledge the request. Maskable hardware interrupts are acknowledged only after certain conditions are met:

- **Priority is highest.** When more than one hardware interrupt is requested at the same time, the F240 services them according to the set priority ranking.
- **INTM bit is 0.** The interrupt mode (INTM) bit, bit 9 of status register ST0, enables or disables all maskable interrupts:
 - When INTM = 0, all unmasked interrupts are enabled.
 - When INTM = 1, all unmasked interrupts are disabled.

INTM is set to 1 automatically when the CPU acknowledges an interrupt (except when initiated by the TRAP instruction) and at reset. It can be set and cleared by software.

• **IMR mask bit is 1.** Each of the maskable interrupt lines has a mask bit in the interrupt mask register (IMR). To unmask an interrupt line, set its IMR bit to 1.

When the CPU acknowledges a maskable hardware interrupt, it jams the instruction bus with the INTR instruction. This instruction forces the PC to the appropriate address from which the CPU fetches the software vector. This vector leads to an interrupt service routine.

Usually, the interrupt service routine reads the peripheral-vector-address offset from the peripheral-vectoraddress register (see Table 7) to branch to code that is meant for the specific interrupt source that initiated the interrupt request. The F240 includes a phantom-interrupt vector offset (0000h), which is a system interrupt integrity feature that allows a controlled exit from an improper interrupt sequence. If the CPU acknowledges a request from a peripheral when, in fact, no peripheral has requested an interrupt, the phantom-interrupt vector is read from the interrupt-vector register.

Table 7 summarizes the interrupt sources, overall priority, vector address/offset, source, and function of each interrupt available on the TMS320F240.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

hardware-generated interrupts (continued)

INTERRUPT NAME	OVERALL PRIORITY	DSP-CORE INTERRUPT, AND ADDRESS	PERIPHERAL VECTOR ADDRESS	PERIPHERAL VECTOR ADDRESS OFFSET	MASKABLE?	SOURCE PERIPHERAL MODULE	FUNCTION INTERRUPT	
RS	1 Highest	RS 0000h	N/A		Ν	Core, SD	External, system reset (RESET)	
RESERVED	2	INT7 0026h	N/A	N/A	Ν	DSP Core	Emulator trap	
NMI	3	NMI 0024h	N/A	0002h	Ν	Core, SD	External user interrupt	
XINT1 XINT2 XINT3	4 5 6			0001h 0011h 001Fh	Y	SD	High-priority external user interrupts	
SPIINT	7	INT1		0005h	Y	SPI	High-priority SPI interrupt	
RXINT	8	0002h (Svetom)	SYSIVR (701Eh)	0006h	Y	SCI	SCI receiver interrupt (high priority)	
TXINT	9	(Oystein)		0007h	Y	SCI	SCI transmitter interrupt (high priority)	
WDTINT	10			0010h	Y	WDT	Watchdog timer interrupt	
PDPINT	11			0020h	Y	External	Power-drive protection Int.	
CMP1INT	12			0021h	Y	EV.CMP1	Full Compare 1 interrupt	
CMP2INT	13			0022h	Y	EV.CMP2	Full Compare 2 interrupt	
CMP3INT	14			0023h	Y	EV.CMP3	Full Compare 3 interrupt	
SCMP1INT	15	INT2 0004h		0024h	Υ	EV.CMP4	Simple compare 1 interrupt	
SCMP2INT	16	(Event	EVIVRA (7432h)	0025h	Υ	EV.CMP5	Simple compare 2 interrupt	
SCMP3INT	17	Manager Group A)	Manager Group A)		Y	EV.CMP6	Simple compare 3 interrupt	
TPINT1	18			0027h	Y	EV.GPT1	Timer1-period interrupt	
TCINT1	19			0028h	Y	EV.GPT1	Timer1-compare interrupt	
TUFINT1	20			0029h	Y	EV.GPT1	Timer1-underflow interrupt	
TOFINT1	21			002Ah	Y	EV.GPT1	Timer1-overflow interrupt	
TPINT2	22			002Bh	Y	EV.GPT2	Timer2-period interrupt	
TCINT2	23			002Ch	Y	EV.GPT2	Timer2-compare interrupt	
TUFINT2	24	INT3		002Dh	Y	EV.GPT2	Timer2-underflow interrupt	
TOFINT2	25	000011	EVIVRB	002Eh	Y	EV.GPT2	Timer2-overflow interrupt	
TPINT3	26	(Event	(7433h)	002Fh	Y	EV.GPT3	Timer3-period interrupt	
TCINT3	27	Manager Group B)		0030h	Y	EV.GPT3	Timer3-compare interrupt	
TUFINT3	28			0031h	Y	EV.GPT3	Timer3-underflow interrupt	
TOFINT3	29			0032h	Y	EV.GPT3	Timer3-overflow interrupt	
CAPINT1	30	INT4		0033h	Y	EV.CAP1	Capture 1 interrupt	
CAPINT2	31	0008h	EVIVRC	0034h	Y	EV.CAP2	Capture 2 interrupt	
CAPINT3	32	(Event Manager	(7434h)	0035h	Y	EV.CAP3	Capture 3 interrupt	
CAPINT4	33	Group C)		0036h	Y	EV.CAP4	Capture 4 interrupt	

Table 7. Interrupt Locations and Priorities



hardware-generated interrupts (continued)

INTERRUPT NAME	OVERALL PRIORITY	DSP-CORE INTERRUPT, AND ADDRESS	PERIPHERAL VECTOR ADDRESS OFFSET		MASKABLE?	SOURCE PERIPHERAL MODULE	FUNCTION INTERRUPT	
SPIINT	34	INT5		0005h	Y	SPI	Low-priority SPI interrupt	
RXINT	35	000Ah	(701Eh)	0006h	Y	SCI	SCI receiver interrupt (low priority)	
TXINT	36	(System)		0007h	Y	SCI	SCI transmitter interrupt (low priority)	
ADCINT	37	INT6	SYSIVR	0004h	Y	ADC	Analog-to-digital interrupt	
XINT1 XINT2 XINT3	38 39 40	000Ch (System)	(701Eh)	0001h 0011h 001Fh	YYY	External pins	Low-priority external user interrupts	
RESERVED	41	000Eh	N/A		Y	DSP Core	Used for analysis	
TRAP	N/A	0022h	N/A		N/A		TRAP instruction vector	

 Table 7. Interrupt Locations and Priorities (Continued)

external interrupts

The F240 has five external interrupts. These interrupts include:

- XINT1. Type A interrupt. The XINT1 control register (at 7070h) provides control and status for this interrupt. XINT1 can be used as a high-priority (Level 1) or low-priority (Level 6) maskable interrupt or as a general-purpose input pin. XINT1 can also be programmed to trigger an interrupt on either the rising or the falling edge.
- NMI. Type A interrupt. The NMI control register (at 7072h) provides control and status for this interrupt. NMI is a nonmaskable external interrupt or a general-purpose input pin. NMI can also be programmed to trigger an interrupt on either the rising or the falling edge.
- XINT2. Type C interrupt. The XINT2 control register (at 7078h) provides control and status for this interrupt. XINT2 can be used as a high-priority (Level 1) or low-priority (Level 6) maskable interrupt or a general-purpose I/O pin. XINT2 can also be programmed to trigger an interrupt on either the rising or the falling edge.
- XINT3. Type C interrupt. The XINT3 control register (at 707Ah) provides control and status for this interrupt. XINT3 can be used as a high-priority (Level 1) or low-priority (Level 6) maskable interrupt or as a general-purpose I/O pin. XINT3 can also be programmed to trigger an interrupt on either the rising or the falling edge.
- PDPINT. This interrupt is provided for safe operation of the power converter and motor drive. This maskable
 interrupt can put the timers and PWM output pins in the high-impedance state and inform the CPU in case
 of motor drive abnormalities such as overvoltage, overcurrent, and excessive temperature rise. PDPINT is
 a Level 2 interrupt.



external interrupts (continued)

Table 8 is a summary of the external interrupt capability of the F240.

EXTERNAL INTERRUPT	ERNAL CONTROL CONTROL REGISTER REGISTER NAME ADDRESS		INTERRUPT TYPE	CAN DO NMI?	DIGITAL I/O PIN	MASKABLE?
XINT1	XINT1CR	7070h	А	No	Input only	Yes (Level 1 or 6)
NMI	NMICR	7072h	А	Yes	Input only	No
XINT2	XINT2CR	7078h	С	No	I/O	Yes (Level 1 or 6)
XINT3	XINT3CR	707Ah	С	No	I/O	Yes (Level 1 or 6)
PDPINT	EVIMRA	742Ch	N/A	N/A	N/A	Yes (Level 2)

Table 8. External Interrupt Types and Functions

clock generation

The TMS320F240 has an on-chip, PLL-based clock module. This module provides all the necessary clocking signals for the device, as well as control for low-power mode entry. The only external component necessary for this module is an external fundamental crystal, or oscillator.

The PLL-based clock module provides two basic modes of operation: oscillator mode and clock-in mode.

oscillator mode

This mode allows the use of a 4-, 6-, or 8-MHz external reference crystal to provide the time base to the device. The internal oscillator circuitry is initialized by software to select the desired CPUCLK frequency, which can be the input clock frequency, the input clock frequency divided by 2 (default), or a clock frequency determined by the PLL.

Clock-in mode

This mode allows the internal crystal oscillator circuitry to be bypassed. The device clocks are generated from an external clock source input on the XTAL1/CLKIN pin. The device can be configured by software to operate on the input clock frequency, the input clock frequency divided by 2, or a clock frequency determined by the PLL.

The F240 runs on two clock frequencies: the CPU clock (CPUCLK) frequency, and the system clock (SYSCLK) frequency. The CPU, memories, external memory interface, and event manager run at the CPUCLK frequency. All other peripherals run at the SYSCLK frequency. The CPUCLK runs at 2x or 4x the frequency of the SYSCLK; for example, for 2x, CPUCLK = 20 MHz and SYSCLK = 10 MHz. There is also a clock for the watchdog timer, WDCLK. This clock has a nominal frequency of 16384 Hz (214 Hz) when XTAL1/CLKIN is a power of two or a sum of two powers of two; for example, 4194304 Hz (222 Hz), 6291456 (222 + 221 Hz), or 8388608 Hz (223 Hz).

The clock module includes three external pins:

- 1. XTAL1/CLKIN clock source/crystal input
- 2. XTAL2 output to crystal
- 3. OSCBYP oscillator bypass

For the external pins, if $\overrightarrow{OSCBYP} \ge V_{IH}$, then the oscillator is enabled and if $\overrightarrow{OSCBYP} \le V_{IL}$, then the oscillator is bypassed and the device is in clock-in mode. In clock-in mode, an external TTL clock must be applied to the XTAL1/CLKIN pin. The XTAL2 pin can be left unconnected.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



clock generation (continued)

Figure 8. PLL Clock Module Block Diagram



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

low-power modes

The TMS320F240 has four low-power modes (IDLE 1, IDLE 2, PLL power down, and oscillator power down). The low-power modes reduce the operating power by reducing or stopping the activity of various modules (by stopping their clocks). The two PLLPM bits of the clock module control register, CKCR0, select which of the low-power modes the device enters when executing an IDLE instruction. Reset or an unmasked interrupt from any source causes the device to exit from IDLE 1 low-power mode. A real-time interrupt from the watchdog timer module causes the device to exit from all low-power modes except oscillator power down. This is a wake-up interrupt. When enabled, reset or any of the four external interrupts (NMI, XINT1, XINT2, or XINT3) causes the device to exit from any of the low-power modes (IDLE 1, IDLE 2, PLL power down, and oscillator power down). The external interrupts are all wake-up interrupts. The maskable external interrupts (XINT1, XINT2, and XINT3) must be enabled individually and globally to bring the device out of a low-power mode properly. It is, therefore, important to ensure that the desired low-power-mode exit path is enabled before entering a low-power mode. Figure 9 shows the wake-up sequence from a power down. Table 9 summarizes the low-power modes.



Figure 9. Waking Up the Device From Power Down

Table	9	I ow-Power	Modes
abic	υ.		Moucs

LOW- POWER MODE	LOW- PLLPM(x) POWER BITS IN STATUS MODE CKCR0[2:3]		SYSCLK STATUS	WDCLK STATUS	PLL STATUS	OSC STATUS	EXIT CONDITION	TYPICAL POWER
Run	XX	On	On	On	On	On	-	80 mA
Idle 1	00	Off	On	On	On	On	Any interrupt or reset	50 mA
Idle 2	01	Off	Off	On	On	On	Wake-up interrupt or reset	7 mA
PLL Power Down	10	Off	Off	On	Off	On	Wake-up interrupt or reset	1 mA
OSC Power Down	11	Off	Off	Off	Off	Off	Wake-up interrupt or reset	400 μA



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

functional block diagram of the TMS320F240 DSP CPU



NOTES: A. Symbol descriptions appear in Table 10.

B. For clarity the data and program buses are shown as single buses although they include address and data bits.



Table 10. Legend for the F240 Internal Hardware Functional Block Diagram

SYMBOL	NAME	DESCRIPTION
ACC	Accumulator	32-bit register that stores the results and provides input for subsequent CALU operations. Also includes shift and rotate capabilities
ARAU	Auxiliary Register Arithmetic Unit	An unsigned, 16-bit arithmetic unit used to calculate indirect addresses using the auxiliary registers as inputs and outputs
AUX REGS	Auxiliary Registers 0–7	These 16-bit registers are used as pointers to anywhere within the data space address range. They are operated upon by the ARAU and are selected by the auxiliary register pointer (ARP). AR0 can also be used as an index value for AR updates of more than one and as a compare value to AR.
BR	Bus Request Signal	BR is asserted during access of the external global data memory space. READY is asserted to the device when the global data memory is available for the bus transaction. BR can be used to extend the data memory address space by up to 32K words.
с	Carry	Register carry output from CALU. C is fed back into the CALU for extended arithmetic operation. The C bit resides in status register 1 (ST1), and can be tested in conditional instructions. C is also used in accumulator shifts and rotates.
CALU	Central Arithmetic Logic Unit	32-bit-wide main arithmetic logic unit for the TMS320C2xx core. The CALU executes 32-bit operations in a single machine cycle. CALU operates on data coming from ISCALE or PSCALE with data from ACC, and provides status results to PCTRL.
DARAM	Dual Access RAM	If the on-chip RAM configuration control bit (CNF) is set to 0, the reconfigurable data dual-access RAM (DARAM) block B0 is mapped to data space; otherwise, B0 is mapped to program space. Blocks B1 and B2 are mapped to data memory space only, at addresses 0300–03FF and 0060–007F, respectively. Blocks 0 and 1 contain 256 words, while Block 2 contains 32 words.
DP	Data Memory Page Pointer	The 9-bit DP register is concatenated with the seven LSBs of an instruction word to form a direct memory address of 16 bits. DP can be modified by the LST and LDP instructions.
GREG	Global Memory Allocation Register	GREG specifies the size of the global data memory space.
IMR	Interrupt Mask Register	IMR individually masks or enables the seven interrupts.
IFR	Interrupt Flag Register	The 7-bit IFR indicates that the TMS320C2xx has latched an interrupt from one of the seven maskable interrupts.
INT#	Interrupt Traps	A total of 32 interrupts by way of hardware and/or software are available.
ISCALE	Input Data-Scaling Shifter	16 to 32-bit barrel left-shifter. ISCALE shifts incoming 16-bit data 0 to16 positions left, relative to the 32-bit output within the fetch cycle; therefore, no cycle overhead is required for input scaling operations.
MPY	Multiplier	16×16 -bit multiplier to a 32-bit product. MPY executes multiplication in a single cycle. MPY operates either signed or unsigned 2s-complement arithmetic multiply.
MSTACK	Micro Stack	MSTACK provides temporary storage for the address of the next instruction to be fetched when program address-generation logic is used to generate sequential addresses in data space.
MUX	Multiplexer	Multiplexes buses to a common input
NPAR	Next Program Address Register	NPAR holds the program address to be driven out on the PAB on the next cycle.
OSCALE	Output Data-Scaling Shifter	16 to 32-bit barrel left-shifter. OSCALE shifts the 32-bit accumulator output 0 to 7 bits left for quantization management and outputs either the 16-bit high- or low-half of the shifted 32-bit data to the Data-Write Data Bus (DWEB).
PAR	Program Address Register	PAR holds the address currently being driven on PAB for as many cycles as it takes to complete all memory operations scheduled for the current bus cycle.
PC	Program Counter	PC increments the value from NPAR to provide sequential addresses for instruction-fetching and sequential data-transfer operations.
PCTRL	Program Controller	PCTRL decodes instruction, manages the pipeline, stores status, and decodes conditional operations.



Table 10. Legend for the F240 Internal Hardware Functional Block Diagram (Continued)

SYMBOL	NAME	DESCRIPTION
PREG	Product Register	32-bit register holds results of 16×16 multiply.
PSCALE	Product-Scaling Shifter	0-, 1- or 4-bit left shift, or 6-bit right shift of multiplier product. The left-shift options are used to manage the additional sign bits resulting from the 2s-complement multiply. The right-shift option is used to scale down the number to manage overflow of product accumulation in the CALU. PSCALE resides in the path from the 32-bit product shifter and from either the CALU or the Data-Write Data Bus (DWEB), and requires no cycle overhead.
STACK	Stack	STACK is a block of memory used for storing return addresses for subroutines and interrupt-service routines, or for storing data. The C20x stack is 16-bit wide and eight-level deep.
TREG	Temporary Register	16-bit register holds one of the operands for the multiply operations. TREG holds the dynamic shift count for the LACT, ADDT, and SUBT instructions. TREG holds the dynamic bit position for the BITT instruction.



F240 DSP core CPU

The TMS320F240 device uses an advanced Harvard-type architecture that maximizes processing power by maintaining two separate memory bus structures — program and data — for full-speed execution. This multiple bus structure allows data and instructions to be read simultaneously. Instructions support data transfers between program memory and data memory. This architecture permits coefficients that are stored in program memory to be read in RAM, thereby eliminating the need for a separate coefficient that are ROM. This, coupled with a four-deep pipeline, allows the F240 device to execute most instructions in a single cycle.

status and control registers

Two status registers, ST0 and ST1, contain the status of various conditions and modes. These registers can be stored into data memory and loaded from data memory, thereby allowing the status of the machine to be saved and restored for subroutines.

The load status register (LST) instruction is used to write to ST0 and ST1. The store status register (SST) instruction is used to read from ST0 and ST1 — except for the INTM bit, which is not affected by the LST instruction. The individual bits of these registers can be set or cleared when using the SETC and CLRC instructions. Figure 10 shows the organization of status registers ST0 and ST1, indicating all status bits contained in each. Several bits in the status registers are reserved and are read as logic 1s. Table 11 lists status register field definitions.

	15		13	12	11	10	9	8	7	6	5	4	3	2	1	0
ST0		ARP		٥V	OVM	1	INTM					DP				
	15		13	12	11	10	9	8	7	6	5	4	3	2	1	0
ST1		ARB		CNF	тс	SXM	С	1	1	1	1	XF	1	1		РМ

Figure 10. Status and Control Register Organization

Table 11. Status	Register	Field	Definitions
------------------	----------	-------	-------------

FIELD	FUNCTION
ARB	Auxiliary register pointer buffer. When the ARP is loaded into ST0, the old ARP value is copied to the ARB except during an LST instruction. When the ARB is loaded by way of an LST #1 instruction, the same value is also copied to the ARP.
ARP	Auxiliary register (AR) pointer. ARP selects the AR to be used in indirect addressing. When the ARP is loaded, the old ARP value is copied to the ARB register. ARP can be modified by memory-reference instructions when using indirect addressing, and by the LARP, MAR, and LST instructions. The ARP is also loaded with the same value as ARB when an LST #1 instruction is executed.
с	Carry bit. C is set to 1 if the result of an addition generates a carry, or reset to 0 if the result of a subtraction generates a borrow. Otherwise, C is reset after an addition or set after a subtraction, except if the instruction is ADD or SUB with a 16-bit shift. In these cases, the ADD can only set and the SUB only reset the carry bit, but cannot affect it otherwise. The single bit shift and rotate instructions also affect C, as well as the SETC, CLRC, and LST #1 instructions. Branch instructions have been provided to branch on the status of C. C is set to 1 on a reset.
CNF	On-chip RAM configuration control bit. If CNF is set to 0, the reconfigurable data dual-access RAM blocks are mapped to data space; otherwise, they are mapped to program space. The CNF can be modified by the SETC CNF, CLRC CNF, and LST #1 instructions. RS sets the CNF to 0.
DP	Data memory page pointer. The 9-bit DP register is concatenated with the seven LSBs of an instruction word to form a direct memory address of 16 bits. DP can be modified by the LST and LDP instructions.
INTM	Interrupt mode bit. When INTM is set to 0, all unmasked interrupts are enabled. When set to 1, all maskable interrupts are disabled. INTM is set and reset by the SETC INTM and CLRC INTM instructions. RS and IACK also set INTM. INTM has no effect on the unmaskable RS and NMI interrupts. Note that INTM is unaffected by the LST instruction. This bit is set to 1 by reset. It is also set to 1 when a maskable interrupt trap is taken.
OV	Overflow flag bit. As a latched overflow signal, OV is set to 1 when overflow occurs in the arithmetic logic unit (ALU). Once an overflow occurs, the OV remains set until a reset, BCND/D on OV/NOV, or LST instructions clear OV.



status and control registers (continued)

FIELD	FUNCTION
OVM	Overflow mode bit. When OVM is set to 0, overflowed results overflow normally in the accumulator. When set to 1, the accumulator is set to either its most positive or negative value upon encountering an overflow. The SETC and CLRC instructions set and reset this bit, respectively. LST can also be used to modify the OVM.
PM	Product shift mode. If these two bits are 00, the multiplier's 32-bit product is loaded into the ALU with no shift. If PM = 01, the PREG output is left-shifted one place and loaded into the ALU, with the LSB zero-filled. If PM = 10, PREG output is left-shifted by four bits and loaded into the ALU, with the LSBs zero-filled. PM = 11 produces a right shift of six bits, sign-extended. Note that the PREG contents remain unchanged. The shift takes place when transferring the contents of the PREG to the ALU. PM is loaded by the SPM and LST #1 instructions. PM is cleared by \overline{RS} .
SXM	Sign-extension mode bit. SXM = 1 produces sign extension on data as it is passed into the accumulator through the scaling shifter. SXM = 0 suppresses sign extension. SXM does not affect the definitions of certain instructions; for example, the ADDS instruction suppresses sign extension regardless of SXM. SXM is set by the SETC SXM and reset by the CLRC SXM instructions, and can be loaded by the LST #1. SXM is set to 1 by reset.
тс	Test/control flag bit. TC is affected by the BIT, BITT, CMPR, LST #1, and NORM instructions. TC is set to a 1 if a bit tested by BIT or BITT is a 1, if a compare condition tested by CMPR exists between AR (ARP) and AR0, if the exclusive-OR function of the two MSBs of the accumulator is true when tested by a NORM instruction. The conditional branch, call, and return instructions can execute based on the condition of TC.
XF	XF pin status bit. XF indicates the state of the XF pin, a general-purpose output pin. XF is set by the SETC XF and reset by the CLRC XF instructions. XF is set to 1 by reset.

Table 11. Status Register Field Definitions (Continued)

central processing unit

The TMS320F240 central processing unit (CPU) contains a 16-bit scaling shifter, a 16 x 16-bit parallel multiplier, a 32-bit central arithmetic logic unit (CALU), a 32-bit accumulator, and additional shifters at the outputs of both the accumulator and the multiplier. This section describes the CPU components and their functions. The functional block diagram shows the components of the CPU.

input scaling shifter

The TMS320F240 provides a scaling shifter with a 16-bit input connected to the data bus and a 32-bit output connected to the CALU. This shifter operates as part of the path of data coming from program or data space to the CALU and requires no cycle overhead. It is used to align the 16-bit data coming from memory to the 32-bit CALU. This is necessary for scaling arithmetic as well as aligning masks for logical operations.

The scaling shifter produces a left shift of 0 to 16 on the input data. The LSBs of the output are filled with zeros; the MSBs can either be filled with zeros or sign-extended, depending upon the value of the SXM bit (sign-extension mode) of status register ST1. The shift count is specified by a constant embedded in the instruction word or by a value in TREG. The shift count in the instruction allows for specific scaling or alignment operations specific to that point in the code. The TREG base shift allows the scaling factor to be adaptable to the system's performance.

multiplier

The TMS320F240 device uses a 16 x 16-bit hardware multiplier that is capable of computing a signed or an unsigned 32-bit product in a single machine cycle. All multiply instructions, except the MPYU (multiply unsigned) instruction, perform a signed multiply operation. That is, two numbers being multiplied are treated as 2s-complement numbers, and the result is a 32-bit 2s-complement number. Two registers are associated with the multiplier:

- 16-bit temporary register (TREG) that holds one of the operands for the multiplier
- 32-bit product register (PREG) that holds the product

Four product shift modes (PM) are available at the PREG output (PSCALE). These shift modes are useful for performing multiply/accumulate operations, performing fractional arithmetic, or justifying fractional products. The PM field of status register ST1 specifies the PM shift mode, as shown in Table 12.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

multiplier (continued)

РМ	SHIFT	DESCRIPTION
00	No shift	Product feed to CALU or data bus with no shift
01	Left 1	Removes the extra sign bit generated in a 2s-complement multiply to produce a Q31 product
10	Left 4	Removes the extra 4 sign bits generated in a 16x13 2s-complement multiply to a produce a Q31 product when using the multiply by a 13-bit constant
11	Right 6	Scales the product to allow up to 128 product accumulation without the possibility of accumulator overflow

Table 12. PSCALE Product Shift Modes

The product can be shifted one bit to compensate for the extra sign bit gained in multiplying two 16-bit 2s-complement numbers (MPY instruction). A four-bit shift is used in conjunction with the MPY instruction with a short immediate value (13 bits or less) to eliminate the four extra sign bits gained in multiplying a 16-bit number by a 13-bit number. Finally, the output of PREG can be right-shifted 6 bits to enable the execution of up to 128 consecutive multiply/accumulates without the possibility of overflow.

The LT (load TREG) instruction normally loads TREG to provide one operand (from the data bus), and the MPY (multiply) instruction provides the second operand (also from the data bus). A multiplication also can be performed with a 13-bit immediate operand when using the MPY instruction. Then a product is obtained every two cycles. When the code is executing multiple multiplies and product sums, the CPU supports the pipelining of the TREG load operations with CALU operations using the previous product. The pipeline operations that run in parallel with loading the TREG include: load ACC with PREG (LTP); add PREG to ACC (LTA); add PREG to ACC and shift TREG input data (DMOV) to next address in data memory (LTD); and subtract PREG from ACC (LTS).

Two multiply/accumulate instructions (MAC and MACD) fully utilize the computational bandwidth of the multiplier, allowing both operands to be processed simultaneously. The data for these operations can be transferred to the multiplier each cycle by way of the program and data buses. This facilitates single-cycle multiply/accumulates when used with the repeat (RPT) instruction. In these instructions, the coefficient addresses are generated by program address generation (PAGEN) logic, while the data addresses are generated by data address generation (DAGEN) logic. This allows the repeated instruction to access the values from the coefficient table sequentially and step through the data in any of the indirect addressing modes.

The MACD instruction, when repeated, supports filter constructs (weighted running averages) so that as the sum-of-products is executed, the sample data is shifted in memory to make room for the next sample and to throw away the oldest sample.

The MPYU instruction performs an unsigned multiplication, which greatly facilitates extended-precision arithmetic operations. The unsigned contents of TREG are multiplied by the unsigned contents of the addressed data memory location, with the result placed in PREG. This process allows the operands of greater than 16 bits to be broken down into 16-bit words and processed separately to generate products of greater than 32 bits. The SQRA (square/add) and SQRS (square/subtract) instructions pass the same value to both inputs of the multiplier for squaring a data memory value.

After the multiplication of two 16-bit numbers, the 32-bit product is loaded into the 32-bit product register (PREG). The product from PREG can be transferred to the CALU or to data memory by way of the SPH (store product high) and SPL (store product low). Note: the transfer of PREG to either the CALU or data bus passes through the PSCALE shifter, and therefore is affected by the product shift mode defined by PM. This is important when saving PREG in an interrupt-service-routine context save as the PSCALE shift effects cannot be modeled in the restore operation. PREG can be cleared by executing the MPY #0 instruction. The product register can be restored by loading the saved low half into TREG and executing a MPY #1 instruction. The high half, then, is loaded using the LPH instruction.



central arithmetic logic unit

The TMS320F240 central arithmetic logic unit (CALU) implements a wide range of arithmetic and logical functions, the majority of which execute in a single clock cycle. This ALU is referred to as central to differentiate it from a second ALU used for indirect-address generation called the auxiliary register arithmetic unit (ARAU). Once an operation is performed in the CALU, the result is transferred to the accumulator (ACC) where additional operations, such as shifting, can occur. Data that is input to the CALU can be scaled by ISCALE when coming from one of the data buses (DRDB or PRDB) or scaled by PSCALE when coming from the multiplier.

The CALU is a general-purpose arithmetic/logic unit that operates on 16-bit words taken from data memory or derived from immediate instructions. In addition to the usual arithmetic instructions, the CALU can perform Boolean operations, facilitating the bit manipulation ability required for a high-speed controller. One input to the CALU is always provided from the accumulator, and the other input can be provided from the product register (PREG) of the multiplier or the output of the scaling shifter (that has been read from data memory or from the ACC). After the CALU has performed the arithmetic or logical operation, the result is stored in the accumulator.

The TMS320F240 device supports floating-point operations for applications requiring a large dynamic range. The NORM (normalization) instruction is used to normalize fixed-point numbers contained in the accumulator by performing left shifts. The four bits of the TREG define a variable shift through the scaling shifter for the LACT/ADDT/SUBT (load/add to /subtract from accumulator with shift specified by TREG) instructions. These instructions are useful in floating-point arithmetic where a number needs to be denormalized — that is, floating-point to fixed-point conversion. They are also useful in execution of an automatic gain control (AGC) going into a filter. The BITT (bit test) instruction provides testing of a single bit of a word in data memory based on the value contained in the four LSBs of TREG.

The CALU overflow saturation mode can be enabled/disabled by setting/resetting the OVM bit of ST0. When the CALU is in the overflow saturation mode and an overflow occurs, the overflow flag is set and the accumulator is loaded with either the most positive or the most negative value representable in the accumulator, depending on the direction of the overflow. The value of the accumulator at saturation is 07FFFFFFF (positive) or 080000000h (negative). If the OVM (overflow mode) status register bit is reset and an overflow occurs, the overflowed results are loaded into the accumulator with modification. (Logical operations cannot result in overflow.)

The CALU can execute a variety of branch instructions that depend on the status of the CALU and the accumulator. These instructions can be executed conditionally based on any meaningful combination of these status bits. For overflow management, these conditions include the OV (branch on overflow) and EQ (branch on accumulator equal to zero). In addition, the BACC (branch to address in accumulator) instruction provides the ability to branch to an address specified by the accumulator (computed goto). Bit test instructions (BIT and BITT), which do not affect the accumulator, allow the testing of a specified bit of a word in data memory.

The CALU also has an associated carry bit that is set or reset depending on various operations within the device. The carry bit allows more efficient computation of extended-precision products and additions or subtractions. It also is useful in overflow management. The carry bit is affected by most arithmetic instructions as well as the single-bit shift and rotate instructions. It is not affected by loading the accumulator, logical operations, or other such non-arithmetic or control instructions.

The ADDC (add to accumulator with carry) and SUBB (subtract from accumulator with borrow) instructions use the previous value of carry in their addition/subtraction operation.

The one exception to the operation of the carry bit is in the use of ADD with a shift count of 16 (add to high accumulator) and SUB with a shift count of 16 (subtract from high accumulator) instructions. This case of the ADD instruction can set the carry bit only if a carry is generated, and this case of the SUB instruction can reset the carry bit only if a borrow is generated; otherwise, neither instruction affects it.



central arithmetic logic unit (continued)

Two conditional operands, C and NC, are provided for branching, calling, returning, and conditionally executing, based upon the status of the carry bit. The SETC, CLRC, and LST #1 instructions also can be used to load the carry bit. The carry bit is set to one on a hardware reset.

accumulator

The 32-bit accumulator is the registered output of the CALU. It can be split into two 16-bit segments for storage in data memory. Shifters at the output of the accumulator provide a left shift of 0 to 7 places. This shift is performed while the data is being transferred to the data bus for storage. The contents of the accumulator remain unchanged. When the post-scaling shifter is used on the high word of the accumulator (bits 16–31), the MSBs are lost and the LSBs are filled with bits shifted in from the low word (bits 0–15). When the post-scaling shifter is used on the low word (bits 0–15).

The SFL and SFR (in-place one-bit shift to the left/right) instructions and the ROL and ROR (rotate to the left/right) instructions implement shifting or rotating of the contents of the accumulator through the carry bit. The SXM bit affects the definition of the SFR (shift accumulator right) instruction. When SXM = 1, SFR performs an arithmetic right shift, maintaining the sign of the accumulator data. When SXM = 0, SFR performs a logical shift, shifting out the LSBs and shifting in a zero for the MSB. The SFL (shift accumulator left) instruction is not affected by the SXM bit and behaves the same in both cases, shifting out the MSB and shifting in a zero. Repeat (RPT) instructions can be used with the shift and rotate instructions for multiple-bit shifts.

auxiliary registers and auxiliary-register arithmetic unit (ARAU)

The F240 provides a register file containing eight auxiliary registers (AR0–AR7). The auxiliary registers are used for indirect addressing of the data memory or for temporary data storage. Indirect auxiliary-register addressing allows placement of the data memory address of an instruction operand into one of the auxiliary registers. These registers are referenced with a 3-bit auxiliary register pointer (ARP) that is loaded with a value from 0 through 7, designating AR0 through AR7, respectively. The auxiliary registers and the ARP can be loaded from data memory, the ACC, the product register, or by an immediate operand defined in the instruction. The contents of these registers also can be stored in data memory or used as inputs to the CALU.

The auxiliary register file (AR0–AR7) is connected to the ARAU. The ARAU can autoindex the current auxiliary register while the data memory location is being addressed. Indexing either by ± 1 or by the contents of the AR0 register can be performed. As a result, accessing tables of information does not require the CALU for address manipulation; therefore, the CALU is free for other operations in parallel.

internal memory

The TMS320F240 device is configured with the following memory modules:

- Dual-access random-access memory (DARAM)
- Flash EEPROM

dual-access RAM (DARAM)

There are 544 words \times 16 bits of DARAM on the F240 device. The F240 DARAM allows writes to and reads from the RAM in the same cycle. The DARAM is configured in three blocks: block 0 (B0), block 1 (B1), and block 2 (B2). Block 1 contains 256 words and block 2 contains 32 words, and both blocks are located only in data memory space. Block 0 contains 256 words, and can be configured to reside in either data or program memory space.

The SETC CNF (configure B0 as data memory) and CLRC CNF (configure B0 as program memory) instructions allow dynamic configuration of the memory maps through software. When using block 0 as program memory, instructions can be downloaded from external program memory into on-chip RAM and then executed. When using on-chip RAM, or high-speed external memory, the F240 runs at full speed with no wait states. The ability of the DARAM to allow two accesses to be performed in one cycle coupled with the parallel nature of the F240


dual-access RAM (DARAM) (continued)

architecture enables the device to perform three concurrent memory accesses in any given machine cycle. Externally, the READY line can be used to interface the F240 to slower, less expensive external memory. Downloading programs from slow off-chip memory to on-chip RAM can speed processing while cutting system costs.

flash EEPROM

Flash EEPROM provides an attractive alternative to masked program ROM. Like ROM, flash is nonvolatile; however, it has the advantage of "in-target" reprogrammability. The TMS320F240 incorporates one 16K \times 16-bit flash EEPROM module in program space. This type of memory expands the capabilities of the TMS320F240 in the areas of prototyping, early field-testing, and single-chip applications.

Unlike most discrete flash memory, the F240 flash does not require a dedicated state machine, because the algorithms for programming and erasing the flash are executed by the DSP core. This enables several advantages, including: reduced chip size and sophisticated, adaptive algorithms. For production programming, the IEEE Standard 1149.1[†] (JTAG) scan port provides easy access to the on-chip RAM for downloading the algorithms and flash code. Other key features of the flash include zero-wait-state access rate and single 5-V power supply.

An erased bit in the TMS320F240 flash is read as a logic 1, and a programmed bit is read as a logic 0. The flash requires a block-erase of the entire 16K module; however, any combination of bits can be programmed. The following four algorithms are required for flash operations: clear, erase, flash-write, and program. For an explanation of these algorithms and a complete description of the flash EEPROM, see the *TMS320F20x/F24x DSP Embedded Flash Memory Technical Reference* (literature number SPRU282).

flash serial loader

The on-chip flash is shipped with a serial bootloader code programmed at the following addresses: 0x0000–0x00FFh. All other flash addresses are in an erased state. The serial bootloader can be used to program the on-chip Flash memory with user's code. During the Flash programming sequence, the on-chip data RAM is used to load and execute the clear, erase, and program algorithms.

flash control mode register

The flash control mode register is located at I/O address FF0Fh. This register offers two options: register access mode and array access mode. Register access mode gives access to the four control registers in the memory space decoded for the flash module. These registers are used to control erasing, programming, and testing of the flash array. Register access mode is enabled by activating an OUT command with dummy data.

The OUT xxxx, FF0Fh instruction makes the flash registers accessible for reads and/or writes. After executing OUT xxxx, FF0Fh, the flash control registers are accessed in the memory space decoded for the flash module and the flash array cannot be accessed. The four registers are repeated every four address locations within the flash module's decoded range.

After completing all the necessary reads and/or writes to the control registers, an IN XXXX, FF0Fh instruction (with dummy data) is executed to place the flash array back in array access mode. After executing the IN XXXX, FF0Fh instruction, the flash array is accessed in the decoded space and the flash registers are not available. Switching between the register access mode and the array access mode is done by issuing the IN and OUT instructions. The memory content in these instructions (denoted by XXXX) is not relevant. Refer to the *TMS320F20x/F24x DSP Embedded Flash Memory Technical Reference* (literature number SPRU282) for a detailed description of the flash programming algorithms.

[†] IEEE Standard 1149.1–1990, IEEE Standard Test-Access Port



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

peripherals

The integrated peripherals of the TMS320F240 are described in the following subsections:

- External memory interface
- Event manager (EV)
- Dual analog-to-digital converter (ADC)
- Serial peripheral interface (SPI)
- Serial communications interface (SCI)
- Watchdog timer (WD)

external memory interface

The TMS320F240 can address up to 64K words \times 16 bits of memory or registers in each of the program, data, and I/O spaces. On-chip memory, when enabled, removes some of this off-chip range. In data space, the high 32K words can be mapped dynamically as either local or global using the GREG register. A data-memory access mapped as global asserts \overline{BR} low (with timing similar to the address bus).

The CPU of the TMS320F240 schedules a program fetch, data read, and data write on the same machine cycle. This is because, from on-chip memory, the CPU can execute all three of these operations in the same cycle. However, the external interface multiplexes the internal buses to one address and one data bus. The external interface sequences these operations to complete the data write first, then the data read, and finally the program read.

The F240 supports a wide range of system interfacing requirements. Program, data, and I/O address spaces provide interface to memory and I/O, maximizing system throughput. The full 16-bit address and data bus, along with the PS, DS, and IS space-select signals allow addressing of 64K 16-bit words in program and I/O space. Due to the on-chip peripherals, external data space is addressable to 32K 16-bit words.

I/O design is simplified by having I/O treated the same way as memory. I/O devices are mapped into the I/O address space using the processor's external address and data buses in the same manner as memory-mapped devices.

The F240 external parallel interface provides control signals to facilitate interfacing to the device. The R/W output signal is provided to indicate whether the current cycle is a read or a write. The STRB output signal provides a timing reference for all external cycles.

Interface to memory and I/O devices of varying speeds is accomplished by using the READY input. When transactions are made with slower devices, the F240 processor waits until the other device completes its function and signals the processor by way of the READY input. Once a ready indication is provided from the external device, execution continues. On the F240 device, the READY input must be driven (active high) to complete reads or writes to internal data I/O-memory-mapped registers and all external addresses.

The bus request (BR) signal is used in conjunction with the other F240 interface signals to arbitrate external global-memory accesses. Global memory is external data-memory space in which the BR signal is asserted at the beginning of the access. When an external global-memory device receives the bus request, it responds by asserting the ready signal after the global-memory access is arbitrated and the global access is completed.

The TMS320F240 supports zero-wait-state reads on the external interface. However, to avoid bus conflicts, writes take two cycles. This allows the F240 to buffer the transition of the data bus from input to output (or output to input) by a half cycle. In most systems, TMS320F240 ratio of reads to writes is significantly large to minimize the overhead of the extra cycle on writes.

Wait states can be generated when accessing slower external resources. The wait states operate on machine-cycle boundaries and are initiated either by using the ready signal or using the software wait-state generator. Ready can be used to generate any number of wait states.



event-manager (EV) module

The event-manager module includes general-purpose (GP) timers, full compare units, capture units, and quadrature-encoder pulse (QEP) circuits. Figure 11 shows the functions of the event manager.

general-purpose (GP) timers

There are three GP timers on the TMS320F240. The GP timer x (for x = 1, 2, 3) includes:

- A 16-bit timer up-, up/down-counter, TxCNT for reads or writes
- A 16-bit timer-compare register (double-buffered with shadow register), TxCMPR for reads or writes
- A 16-bit timer-period register (double-buffered with shadow register), TxPR for reads or writes
- A 16-bit timer-control register, TxCON for reads or writes
- Selectable internal or external input clocks
- A programmable prescalar for internal or external clock inputs
- Control and interrupt logic for four maskable interrupts: underflow, overflow, timer compare, and period interrupts
- A timer-compare output pin with configurable active-low and active-high states, as well as forced-low and forced-high states.
- A selectable direction (TMRDIR) input pin (to count up or down when directional up-/down-count mode is selected)

The GP timers can be operated independently or synchronized with each other. A 32-bit GP timer also can be configured using GP timer 2 and 3. The compare register associated with each GP timer can be used for compare function and PWM-waveform generation. There are two single and three continuous modes of operation for each GP timer in up- or up/down-counting operations. Internal or external input clocks with programmable prescaler is used for each GP timer. The state of each GP timer/compare output is configurable by the general-purpose timer-control register (GPTCON). GP timers also provide the time base for the other event-manager submodules: GP timer 1 for all the compares and PWM circuits, GP timer 1 or 2 for the simple compares to generate additional compare or PWMs, GP timer 2 or 3 for the capture units and the quadrature-pulse counting operations.

Double buffering of the period and compare registers allows programmable change of the timer (PWM) period and the compare/PWM pulse width as needed.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002







full compare units

There are three full compare units on TMS320F240. These compare units use GP timer1 as the timebase and generate six outputs for compare and PWM-waveform generation using programmable deadband circuit. The state of each of the six outputs is configured independently. The compare registers of the compare units are double-buffered, allowing programmable change of the compare/PWM pulse widths as needed.

programmable-deadband generator

The deadband generator circuit includes three 8-bit counters and an 8-bit compare register. Desired deadband value (from 0 to $102 \,\mu$ s) can be programmed into the compare register for the outputs of the three compare units. The deadband generation can be enabled/disabled for each compare unit output individually. The deadband-generator circuit produces two outputs (with or without deadband zone) for each compare unit output signal. The output states of the deadband generator are configurable and changeable as needed by way of the double-buffered ACTR register.

simple compares

TMS320F240 is equipped with three simple compares that can be used to generate three additional independent compare or high-precision PWM waveforms. GP timer1 or 2 can be selected as the timebase for the three simple compares. The states of the outputs of the three simple compares are configurable as low-active, high-active, forced-low, or forced-high independently. Simple compare registers are double-buffered, allowing programmable change of the compare/PWM pulse widths as needed. The state of the simple-compare outputs is configurable and changeable as needed by way of the double-buffered SACTR register.

compare/PWM waveform generation

Up to 12 compare and/or PWM waveforms (outputs) can be generated simultaneously by TMS320F240: three independent pairs (six outputs) by the three full compare units with *programmable deadbands*, three independent compares or PWMs (three outputs) by the simple compares, and three independent compare and PWMs (three outputs) by the GP-timer compares.

compare/PWMs characteristics

Characteristics of the compare/PWMs are as follow:

- 16-bit, 50-ns resolutions
- Programmable deadband for the PWM output pairs, from 0 to 102 μs
- Minimum deadband width of 50 ns
- Change of the PWM carrier frequency for PWM frequency wobbling as needed
- Change of the PWM pulse widths within and after each PWM period as needed
- External maskable power and drive-protection interrupts
- Pulse-pattern-generator circuit, for programmable generation of asymmetric, symmetric, and four-space vector PWM waveforms
- Minimized CPU overhead using auto-reload of the compare and period registers

capture unit

The capture unit provides a logging function for different events or transitions. The values of the GP timer 2 counter and/or GP timer 3 counter are captured and stored in the two-level first-in first-out (FIFO) stacks when selected transitions are detected on capture input pins, CAPx for x = 1, 2, 3, or 4. The capture unit of the TMS320F240 consists of four capture circuits.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

capture unit (continued)

- The capture unit includes the following features:
 - One 16-bit capture-control register, CAPCON, for reads or writes
 - One 16-bit capture-FIFO status register, CAPFIFO, with eight MSBs for read-only operations, and eight LSBs for write-only operations
 - Optional selection of GP timer 2 and/or GP timer 3 through two 16-bit multiplexers (MUXs). One MUX selects a GP timer for capture circuits 3 and 4, and the other MUX selects a GP timer for capture circuits 1 and 2.
 - Four 16 bit x 2 FIFO stack registers, one two-level FIFO stack register per capture circuit. The top register of each stack is a read-only register, FIFOx, where x = 1, 2, 3, or 4.
 - Four capture-input pins (CAPx, x = 1 to 4) with one input pin per capture unit
 - The input pins CAP1 and CAP2 also can be used as inputs to the QEP circuit.
 - User-specified edge-detection mode at the input pins
 - Four maskable interrupts/flags, CAPINTx, where x = 1, 2, 3, or 4

quadrature-encoder pulse (QEP) circuit

Two capture inputs (CAP1 and CAP2) can be used to interface the on-chip QEP circuit with a quadrature encoder pulse. Full synchronization of these inputs is performed on-chip. Direction or leading-quadrature pulse sequence is detected, and GP timer 2 or 3 is incremented or decremented by the rising and falling edges of the two input signals (four times the frequency of either input pulse).

analog-to-digital converter (ADC) module

A simplified functional block diagram of the ADC module is shown in Figure 12. The ADC module consists of two 10-bit ADCs with two built-in sample-and-hold (S/H) circuits. A total of 16 analog input channels is available on the TMS320F240. Eight analog inputs are provided for each ADC unit by way of an 8-to-1 analog multiplexer. Minimum total conversion time for each ADC unit is 6.1 μ s. Total accuracy for each converter is ±1.5 LSB. Reference voltage for the ADC module needs to be supplied externally through the two reference pins, V_{REFHI} and V_{REFLO}. The digital result is expressed as:

Digital Value =
$$1023 \times \frac{\text{Input Analog Voltage} - V_{\text{REFLO}}}{V_{\text{REFHI}} - V_{\text{REFLO}}}$$

Functions of the ADC module include:

- Two input channels (one for each ADC unit) that can be sampled and converted simultaneously
- Each ADC unit can perform single or continuous S/H and conversion operations.
- Two 2-level-deep FIFO result registers for ADC units 1 and 2
- ADC module (both A/D converters) can start operation by software instruction, external signal transition on a device pin, or by event-manager events on each of the GP timer/compare output and the capture 4 pins.
- The ADC control register is double-buffered (with shadow register) and can be written to at any time. A new conversion of ADC can start immediately or when the previous conversion process is completed according to the control register bits.
- At the end of each conversion, an interrupt flag is set and an interrupt is generated if it is unmasked/enabled.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



analog-to-digital converter (ADC) module (continued)

Figure 12. Analog-to-Digital Converter Module



serial peripheral interface (SPI) module

The TMS320F240 device includes the four-pin serial peripheral interface (SPI) module. The SPI is a high-speed synchronous serial-I/O port that allows a serial bit stream of programmed length (one to eight bits) to be shifted into and out of the device at a programmable bit-transfer rate. Normally, the SPI is used for communications between the DSP controller and external peripherals or another processor. Typical applications include external I/O or peripheral expansion through devices such as shift registers, display drivers, and ADCs. Multidevice communications are supported by the master/slave operation of the SPI.

The SPI module features include the following:

- Four external pins:
 - SPISOMI: SPI slave-output/master-input pin, or general-purpose bidirectional I/O pin
 - SPISIMO: SPI slave-input/master-output pin, or general-purpose bidirectional I/O pin
 - SPISTE: SPI slave-transmit-enable pin, or general-purpose bidirectional I/O pin
 - SPICLK: SPI serial-clock pin, or general-purpose bidirectional I/O pin
- Two operational modes: master and slave
- Baud rate: 125 different programmable rates / 2.5 Mbps at 10-MHz SYSCLK
- Data word format: one to eight data bits
- Four clocking schemes controlled by clock polarity and clock-phase bits include:
 - Falling edge without phase delay: SPICLK active high. SPI transmits data on the falling edge of the SPICLK signal and receives data on the rising edge of the SPICLK signal.
 - Falling edge with phase delay: SPICLK active high. SPI transmits data one half-cycle ahead of the falling edge of the SPICLK signal and receives data on the falling edge of the SPICLK signal.
 - Rising edge without phase delay: SPICLK inactive low. SPI transmits data on the rising edge of the SPICLK signal and receives data on the falling edge of the SPICLK signal.
 - Rising edge with phase delay: SPICLK inactive low. SPI transmits data one half-cycle ahead of the falling edge of the SPICLK signal and receives data on the rising edge of the SPICLK signal.
- Simultaneous receive and transmit operations (transmit function can be disabled in software)
- Transmitter and receiver operations are accomplished through either interrupt-driven or polled algorithms.
- Ten SPI module control registers: Located in control register frame beginning at address 7040h.
- NOTE: All registers in this module are 8-bit registers that are connected to the 16-bit peripheral bus. When a register is accessed, the register data is in the lower byte (7–0), and the upper byte (15–8) is read as zeros. Writing to the upper byte has no effect.

Figure 13 is a block diagram of the SPI in slave mode.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

serial peripheral Interface (SPI) module (continued)



[†] The diagram is shown in the slave mode.

[‡] The SPISTE pin is shown as being disabled, meaning that data cannot be transmitted in this mode. Note that SW1, SW2, and SW3 are closed in this configuration.

Figure 13. Four-Pin Serial Peripheral Interface Module Block Diagram[†]



serial communications interface (SCI) module

The TMS320F240 device includes a serial communications interface (SCI) module. The SCI module supports digital communications between the CPU and other asynchronous peripherals that use the standard non-return-to-zero (NRZ) format. The SCI receiver and transmitter are double-buffered, and each has its own separate enable and interrupt bits. Both can be operated independently or simultaneously in the full-duplex mode. To ensure data integrity, the SCI checks received data for break detection, parity, overrun, and framing errors. The bit rate (baud) is programmable to over 65000 different speeds through a 16-bit baud-select register. Features of the SCI module include:

- Two external pins
 - SCITXD: SCI transmit-output pin or general-purpose bidirectional I/O pin
 - SCIRXD: SCI receive-input pin or general-purpose bidirectional I/O pin
- Baud rate programmable to 64K different rates
 - Up to 625 Kbps at 10-MHz SYSCLK
- Data word format
 - One start bit
 - Data word length programmable from one to eight bits
 - Optional even/odd/no parity bit
 - One or two stop bits
- Four error-detection flags: parity, overrun, framing, and break detection
- Two wake-up multiprocessor modes: idle-line and address bit
- Half- or full-duplex operation
- Double-buffered receive and transmit functions
- Transmitter and receiver operations can be accomplished through interrupt-driven or polled algorithms with status flags.
 - Transmitter: TXRDY flag (transmitter-buffer register is ready to receive another character) and TX EMPTY flag (transmitter-shift register is empty)
 - Receiver: RXRDY flag (receiver-buffer register is ready to receive another character), BRKDT flag (break condition occurred), and RX ERROR (monitoring four interrupt conditions)
- Separate enable bits for transmitter and receiver interrupts (except BRKDT)
- NRZ (non return-to-zero) format
- Eleven SCI module control registers located in the control register frame beginning at address 7050h

NOTE: All registers in this module are 8-bit registers that are interfaced to the 16-bit peripheral bus. When a register is accessed, the register data is in the lower byte (7–0), and the upper byte (15–8) is read as zeros. Writing to the upper byte has no effect.

Figure 14 shows the SCI module block diagram.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



serial communications interface (SCI) module (continued)

Figure 14. Serial Communications Interface (SCI) Module Block Diagram



watchdog (WD) and real-time interrupt (RTI) module

The TMS320F240 device includes a watchdog (WD) timer and a real-time interrupt (RTI) module. The WD function of this module monitors software and hardware operation by generating a system reset if it is not periodically serviced by software by having the correct key written. The RTI function provides interrupts at programmable intervals. See Figure 15 for a block diagram of the WD/RTI module. The WD/RTI module features include the following:

- WD Timer
 - Seven different WD overflow rates ranging from 15.63 ms to 1 s
 - A WD-reset key (WDKEY) register that clears the WD counter when a correct value is written, and generates a system reset if an incorrect value is written to the register
 - A WD flag (WD FLAG) that indicates whether the WD timer initiated a system reset
 - WD check bits that initiate a system reset if an incorrect value is written to the WD control register (WDCR)
- Automatic activation of the WD timer, once system reset is released
 - Three WD control registers located in control register frame beginning at address 7020h.
- Real-time interrupt (RTI):
 - Interrupt generation at a programmable frequency of 1 to 4096 interrupts per second
 - Interrupt or polled operation
 - Two RTI control registers located in control register frame beginning at address 7020h.
- NOTE: All registers in this module are 8-bit registers that are connected to the 16-bit peripheral bus. When a register is accessed, the register data is in the lower byte (7–0), and the upper byte (15–8) is read as zeros. Writing to the upper byte has no effect.

Figure 15 shows the WD/RTI block diagram.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



watchdog (WD) and real-time interrupt (RTI) module (continued)

[†]Writing to bits WDCR.5–3 with anything but the correct pattern (101) generates a system reset.

Figure 15. WD/RTI Module Block Diagram



scan-based emulation

TMS320F240 device uses scan-based emulation for code- and hardware-development support. Serial scan interface is provided by the test-access port. Scan-based emulation allows the emulator to control the processor in the system without the use of intrusive cables to the full pinout of the device.

TMS320F240 instruction set

The F240 microprocessor implements a comprehensive instruction set that supports both numeric-intensive signal-processing operations and general-purpose applications, such as multiprocessing and high-speed control. Source code for the C1x and C2x DSPs is upwardly compatible with the x2xx devices.

For maximum throughput, the next instruction is prefetched while the current one is being executed. Because the same data lines are used to communicate to external data, program, or I/O space, the number of cycles an instruction requires to execute varies, depending upon whether the next data operand fetch is from internal or external memory. Highest throughput is achieved by maintaining data memory on chip and using either internal or fast external program memory.

addressing modes

The TMS320F240 instruction set provides four basic memory-addressing modes: direct, indirect, immediate, and register.

In direct addressing, the instruction word contains the lower seven bits of the data memory address. This field is concatenated with the nine bits of the data memory page pointer (DP) to form the 16-bit data memory address. Therefore, in the direct-addressing mode, data memory is paged effectively with a total of 512 pages, each page containing 128 words.

Indirect addressing accesses data memory through the auxiliary registers. In this addressing mode, the address of the instruction operand is contained in the currently selected auxiliary register. Eight auxiliary registers (AR0–AR7) provide flexible and powerful indirect addressing. To select a specific auxiliary register, the auxiliary register pointer (ARP) is loaded with a value from 0 to 7 for AR0 through AR7, respectively.

There are seven types of indirect addressing: autoincrement or autodecrement, postindexing by adding or subtracting the contents of AR0, single-indirect addressing with no increment or decrement, and bit-reversed addressing [used in Fast Fourier Transforms (FFTs)] with increment or decrement. All operations are performed on the current auxiliary register in the same cycle as the original instruction, following which the current auxiliary register and ARP can be modified.

In immediate addressing, the actual operand data is provided in a portion of the instruction word or words. There are two types of immediate addressing: long and short. In short-immediate addressing, the data is contained in a portion of the bits in a single-word instruction. In long-immediate addressing, the data is contained in the second word of a two-word instruction. The immediate-addressing mode is useful for data that does not need to be stored or used more than once during the course of program execution (for example, initialization values or constants).

The register-addressing mode uses operands in CPU registers either explicitly, such as with a direct reference to a specific register, or implicitly, with instructions that intrinsically reference certain registers. In either case, operand reference is simplified because 16-bit values can be used without specifying a full 16-bit operand address or immediate value.



repeat feature

The repeat function can be used with instructions (as defined in Table 14) such as multiply/accumulates (MAC and MACD), block moves (BLDD and BLPD), I/O transfers (IN/OUT), and table read/writes (TBLR/TBLW). These instructions, although normally multicycle, are pipelined when the repeat feature is used, and they effectively become single-cycle instructions. For example, the table-read instruction can take three or more cycles to execute, but when the instruction is repeated, a table location can be read every cycle.

The repeat counter (RPTC) is loaded with the addressed data-memory location if direct or indirect addressing is used, and with an 8-bit immediate value if short-immediate addressing is used. The RPTC register is loaded by the RPT instruction. This results in a maximum of N + 1 executions of a given instruction. RPTC is cleared by reset. Once a repeat instruction (RPT) is decoded, all interrupts, including NMI (but excluding reset), are masked until the completion of the repeat loop.

instruction set summary

This section summarizes the operation codes (opcodes) of the instruction set for the F240 digital signal processors. This instruction set is a superset of the C1x and C2x instruction sets. The instructions are arranged according to function and are alphabetized by mnemonic within each category. The symbols in Table 13 are used in the instruction set summary table (Table 14). The TI C2xx assembler accepts C2x instructions.

The number of words that an instruction occupies in program memory is specified in column 3 of Table 14. Several instructions specify two values separated by a slash mark (/) for the number of words. In these cases, different forms of the instruction occupy a different number of words. For example, the ADD instruction occupies one word when the operand is a short-immediate value or two words if the operand is a long-immediate value.

The number of cycles that an instruction requires to execute is also in column 3 of Table 14. All instructions are assumed to be executed from internal program memory (RAM) and internal data dual-access memory. The cycle timings are for single-instruction execution, not for repeat mode.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

instruction set summary (continued)

Table 13. TWIS320F240 Opcode Symbols	Table 13	. TMS320F240	Opcode Symb	ols
--------------------------------------	----------	--------------	--------------------	-----

SYMBOL	DESCRIPTION					
А	Address					
ACC	Accumulator					
ACCB	Accumulator buffer					
ARx	Auxiliary register value (0-7)					
BITx	4-bit field that specifies which bit to test for the BIT instruction					
BMAR	Block-move address register					
DBMR	Dynamic bit-manipulation register					
I	Addressing-mode bit					
1111	Immediate operand value					
INTM	Interrupt-mode flag bit					
INTR#	Interrupt vector number					
К	Constant					
PREG	Product register					
PROG	Program memory					
RPTC	Repeat counter					
SHF, SHFT	3/4-bit shift value					
тс	Test-control bit					
	Two bits used by the conditional execution instructions to represent the conditions TC, NTC, and BIO. T P Meaning					
ТР						
	10 TC=0					
	1 1 None of the above conditions					
TREGn	Temporary register n (n = 0, 1, or 2)					
	 4-bit field representing the following conditions: Z: ACC = 0 L: ACC < 0 V: Overflow C: Carry A conditional instruction contains two of these 4-bit fields. The 4-LSB field of the instruction is a 4-bit mask field. A 1 in the 					
ZLVC	corresponding mask bit indicates that the condition is being tested. The second 4-bit field (bits 4–7) indicates the state of the conditions designated by the mask bits as being tested. For example, to test for ACC \geq 0, the Z and L fields are set while the V and C fields are not set. The next 4-bit field contains the state of the conditions to test. The Z field is set to indicate testing of the condition ACC = 0, and the L field is reset to indicate testing of the condition ACC \geq 0. The conditions possible with these 8 bits are shown in the BCND and CC instructions. To determine if the conditions are met, the 4-LSB bit mask is ANDed with the conditions. If any bits are set, the conditions are met.					



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

instruction set summary (continued)

F240	DECODIDION		OPCODE			
MNEMONIC	DESCRIPTION	CYCLES	MSB LSB			
ABS	Absolute value of accumulator	1/1	1011 1110 0000 0000			
	Add to accumulator with shift	1/1	0010 SHFT IADD RESS			
	Add to high accumulator	1/1	0110 0001 IADD RESS			
ADD	Add to accumulator short immediate	1/1	1011 1000 KKKK KKKK			
	Add to accumulator long immediate with shift	2/2	1011 1111 1001 SHFT			
ADDC	Add to accumulator with carry	1/1	0110 0000 IADD RESS			
ADDS	Add to low accumulator with sign extension suppressed	1/1	0110 0010 IADD RESS			
ADDT	Add to accumulator with shift specified by T register	1/1	0110 0011 IADD RESS			
ADRK	Add to auxiliary register short immediate	1/1	0111 1000 KKKK KKKK			
	AND with accumulator	1/1	0110 1110 IADD RESS			
AND	AND immediate with accumulator with shift	2/2	1011 1111 1011 SHFT 16-Bit Constant			
	AND immediate with accumulator with shift of 16	2/2	1011 1110 1000 0001 16-Bit Constant			
APAC	Add P register to accumulator	1/1	1011 1110 0000 0100			
В	Branch unconditionally	2/4	0111 1001 IADD RESS Branch Address			
BACC	Branch to address specified by accumulator	1/4	1011 1110 0010 0000			
BANZ	Branch on auxiliary register not zero	2/4/2	0111 1011 IADD RESS Branch Address			
	Branch if TC bit ≠ 0	2/4/2	1110 0001 0000 0000 Branch Address			
	Branch if TC bit = 0	2/4/2	1110 0010 0000 0000 Branch Address			
	Branch on carry	2/4/2	1110 0011 0001 0001 Branch Address			
	Branch if accumulator ≥ 0	2/4/2	1110 0011 1000 1100 Branch Address			
	Branch if accumulator > 0	2/4/2	1110 0011 0000 0100 Branch Address			
BCND	Branch on I/O status low	2/4/3	1110 0000 0000 0000 Branch Address			
	Branch if accumulator ≤ 0	2/4/2	1110 0011 1100 1100 Branch Address			
	Branch if accumulator < 0	2/4/2	1110 0011 0100 0100 Branch Address			
	Branch on no carry	2/4/2	1110 0011 0000 0001 Branch Address			
	Branch if no overflow	2/4/2	1110 0011 0000 0010 Branch Address			

Table 14. TMS320F240 Instruction Set Summary



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

instruction set summary (continued)

F240			OPCODE				
MNEMONIC	DESCRIPTION	CYCLES	MSB			LSB	
	Prese hi 'f annun helen i O	0/4/0	1110	0011	0000	1000	
	Branch if accumulator $\neq 0$	2/4/2		Branch	Address		
DOND	Branch on everflow	2/4/2	1110	0011	0010	0010	
BCIND	Branch on overnow	2/4/2		Branch	Address		
	Branch if accumulator – 0	2/4/2	1110	0011	1000	1000	
		2/4/2		Branch	Address		
BIT	Test bit	1/1	0100	BITx	IADD	RESS	
BITT	Test bit specified by TREG	1/1	0110	1111	IADD	RESS	
	Block move from data memory to data memory source immediate	2/2	1010	1000	IADD	RESS	
BIDDT	Block move from data memory to data memory source immediate	2/3		Branch	Address		
BLODI	Block move from data memory to data memory destination immediate	2/2	1010	1001	IADD	RESS	
	Block move nom data memory to data memory destination mimediate	2/3		Branch	Address		
	Block move from program memory to data memory	2/2	1010	0101	IADD	RESS	
DLFD	Block move nom program memory to data memory	2/3	Branch Address				
CALA	Call subroutine indirect	1/4	1011	1110	0011	0000	
CALL	Call subroutine 2	2/4	0111	1010	IADD	RESS	
		2/4		Routine	Address		
<u> </u>		2/4/2	1110	10TP	ZLVC	ZLVC	
			Routine Address				
	Configure block as data memory	1/1	1011	1110	0100	0100	
	Enable interrupt	1/1	1011	1110	0100	0000	
	Reset carry bit	1/1	1011	1110	0100	1110	
CLRC	Reset overflow mode	1/1	1011	1110	0100	0010	
	Reset sign-extension mode	1/1	1011	1110	0100	0110	
	Reset test/control flag	1/1	1011	1110	0100	1010	
	Reset external flag	1/1	1011	1110	0100	1100	
CMPL	Complement accumulator	1/1	1011	1110	0000	0001	
CMPR	Compare auxiliary register with auxiliary register AR0	1/1	1011	1111	0100	01CM	
DMOV	Data move in data memory	1/1	0111	0111	IADD	RESS	
IDLE	Idle until interrupt	1/1	1011	1110	0010	0010	
IN	Input data from port	2/2	1010	1111	IADD	RESS	
		/	16BIT	I/O	PORT	ADRS	
INTR	Software-interrupt	1/4	1011	1110	011K	KKKK	
	Load accumulator with shift	1/1	0001	SHFT	IADD	RESS	
	Load accumulator long immediate with shift	2/2	1011	1111	1000	SHFT	
LACC		2/2					
	Zero low accumulator and load high accumulator	1/1	0110	1010	IADD	RESS	

[†] In x240 devices, the BLDD instruction does not work with memory-mapped registers IMR, IFR, and GREG.



instruction set summary (continued)

Table 14.	TMS320F240	Instruction	Set	Summary	(Continued)
-----------	------------	-------------	-----	---------	-------------

F240	F240 DECODIDATION		OPCODE			
MNEMONIC	DESCRIPTION	CYCLES	MSB			LSB
	Load accumulator immediate short	1/1	1011	1001	KKKK	KKKK
	Zero accumulator	1/1	1011	1001	0000	0000
LACL	Zero low accumulator and load high accumulator	1/1	0110	1010	IADD	RESS
	Zero low accumulator and load low accumulator with no sign extension	1/1	0110	1001	IADD	RESS
LACT	Load accumulator with shift specified by T register	1/1	0110	1011	IADD	RESS
	Load auxiliary register	1/2	0000	0ARx	IADD	RESS
	Load auxiliary register short immediate	1/2	1011	0ARx	KKKK	KKKK
LAN	Load auxiliary register long immediate	2/2	1011	1111 16-Bit (0000 Constant	1ARx
	Load data-memory page pointer	1/2	0000	1101	IADD	RESS
LDP	Load data-memory page pointer immediate	1/2	1011	110P	AGEP	OINT
LPH	Load high-P register	1/1	0111	0101	IADD	RESS
	Load status register ST0	1/2	0000	1110	IADD	RESS
LST	Load status register ST1	1/2	0000	1111	IADD	RESS
LT	Load TREG	1/1	0111	0011	IADD	RESS
LTA	Load TREG and accumulate previous product	1/1	0111	0000	IADD	RESS
LTD	Load TREG, accumulate previous product, and move data	1/1	0111	0010	IADD	RESS
LTP	Load TREG and store P register in accumulator	1/1	0111	0001	IADD	RESS
LTS	Load TREG and subtract previous product	1/1	0111	0100	IADD	RESS
	Multiply and accumulate 2/3	0/0	1010	0010	IADD	RESS
MAC		2/3		16-Bit (Constant	
MACD	Multiply and accumulate with data mayo	0/0	1010	0011	IADD	RESS
MACD		2/3	16-Bit Constant			
MAR	Load auxiliary register pointer	1/1	1000	1011	1000	1ARx
WAIX	Modify auxiliary register	1/1	1000	1011	IADD	RESS
MPY	Multiply (with TREG, store product in P register)	1/1	0101	0100	IADD	RESS
	Multiply immediate	1/1	110C	KKKK	KKKK	KKKK
MPYA	Multiply and accumulate previous product	1/1	0101	0000	IADD	RESS
MPYS	Multiply and subtract previous product	1/1	0101	0001	IADD	RESS
MPYU	Multiply unsigned	1/1	0101	0101	IADD	RESS
NEG	Negate accumulator	1/1	1011	1110	0000	0010
NMI	Nonmaskable interrupt	1/4	1011	1110	0101	0010
NOP	No operation	1/1	1000	1011	0000	0000
NORM	Normalize contents of accumulator	1/1	1010	0000	IADD	RESS
	OR with accumulator	1/1	0110	1101	IADD	RESS
	OP immediate with accumulator with chift	2/2	1011	1111	1100	SHFT
OR		2/2	16-Bit Constant			
	OP immediate with accumulator with chift of 16	2/2	1011	1110	1000	0010
		2/2	16-Bit Constar			
OUT	Output data to port	2/3	0000 16BIT	1100 I/O	IADD PORT	RESS ADRS
PAC	Load accumulator with P register	1/1	1011	1110	0000	0011



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

instruction set summary (continued)

Table 14. TMS320F240 Instruction S	Set Summary (Continued)
------------------------------------	-------------------------

F240	F240	WORDS/	OPCODE			
MNEMONIC	IC DESCRIPTION		MSB			LSB
POP	Pop top of stack to low accumulator	1/1	1011	1110	0011	0010
POPD	Pop top of stack to data memory	1/1	1000	1010	IADD	RESS
PSHD	Push data-memory value onto stack	1/1	0111	0110	IADD	RESS
PUSH	Push low accumulator onto stack	1/1	1011	1110	0011	1100
RET	Return from subroutine	1/4	1110	1111	0000	0000
RETC	Conditional return from subroutine	1/4/2	1110	11TP	ZLVC	ZLVC
ROL	Rotate accumulator left	1/1	1011	1110	0000	1100
ROR	Rotate accumulator right	1/1	1011	1110	0000	1101
	Repeat instruction as specified by data-memory value	1/1	0000	1011	IADD	RESS
RPT	Repeat instruction as specified by immediate value	1/1	1011	1011	KKKK	KKKK
SACH	Store high accumulator with shift	1/1	1001	1SHF	IADD	RESS
SACL	Store low accumulator with shift	1/1	1001	0SHF	IADD	RESS
SAR	Store auxiliary register	1/1	1000	0ARx	IADD	RESS
SBRK	Subtract from auxiliary register short immediate	1/1	0111	1100	KKKK	KKKK
	Set carry bit	1/1	1011	1110	0100	1111
	Configure block as program memory	1/1	1011	1110	0100	0101
	Disable interrupt	1/1	1011	1110	0100	0001
SETC	Set overflow mode	1/1	1011	1110	0100	0011
	Set test/control flag	1/1	1011	1110	0100	1011
	Set external flag XF	1/1	1011	1110	0100	1101
	Set sign-extension mode	1/1	1011	1110	0100	0111
SFL	Shift accumulator left	1/1	1011	1110	0000	1001
SFR	Shift accumulator right	1/1	1011	1110	0000	1010
SPAC	Subtract P register from accumulator	1/1	1011	1110	0000	0101
SPH	Store high-P register	1/1	1000	1101	IADD	RESS
SPL	Store low-P register	1/1	1000	1100	IADD	RESS
SPM	Set P register output shift mode	1/1	1011	1111	IADD	RESS
SQRA	Square and accumulate	1/1	0101	0010	IADD	RESS
SQRS	Square and subtract previous product from accumulator	1/1	0101	0011	IADD	RESS
COT	Store status register ST0	1/1	1000	1110	IADD	RESS
551	Store status register ST1	1/1	1000	1111	IADD	RESS
	Store long immediate to date memory	2/2	1010	1110	IADD	RESS
SPLK	Store long inimediate to data memory	2/2		16-Bit C	Constant	
	Subtract from accumulator long immediate with shift	2/2	1011	1111	1010	SHFT
		212	16-Bit Constant			
SUB	Subtract from accumulator with shift	1/1	0011	SHFT	IADD	RESS
	Subtract from high accumulator	1/1	0110	0101	IADD	RESS
	Subtract from accumulator short immediate	1/1	1011	1010	KKKK	KKKK



instruction set summary (continued)

F240				OPC	ODE				
MNEMONIC	DESCRIPTION	CYCLES	MSB			LSB			
SUBB	Subtract from accumulator with borrow	1/1	0110	0100	IADD	RESS			
SUBC	Conditional subtract	1/1	0000	1010	IADD	RESS			
SUBS	Subtract from low accumulator with sign extension suppressed	1/1	0110	0110	IADD	RESS			
SUBT	Subtract from accumulator with shift specified by TREG	1/1	0110	0111	IADD	RESS			
TBLR	Table read	1/3	1010	0110	IADD	RESS			
TBLW	Table write	1/3	1010	0111	IADD	RESS			
TRAP	Software interrupt	1/4	1011	1110	0101	0001			
	Exclusive-OR with accumulator	1/1	0110	1100	IADD	RESS			
		0/0	1011	1111	1101	SHFT			
XOR	Exclusive-OR immediate with accumulator with shift		16-Bit Constant						
					1	1011	1110	1000	0011
	Exclusive-OR immediate with accumulator with shift of 16	2/2	16-Bit Constant						
ZALR	Zero low accumulator and load high accumulator with rounding	1/1	0110	1000	IADD	RESS			

Table 14. TMS320F240 Instruction Set Summary (Continued)

development support

Texas Instruments offers an extensive line of development tools for the x240 generation of DSPs, including tools to evaluate the performance of the processors, generate code, develop algorithm implementations, and fully integrate and debug software and hardware modules.

The following products support development of x240-based applications:

Software Development Tools:

Assembler/Linker Simulator Optimizing ANSI C compiler Application algorithms C/Assembly debugger and code profiler

Hardware Development Tools:

Emulator XDS510 (supports x240 multiprocessor system debug)

See Table 15 and Table 16 for complete listings of development-support tools for the F240. For information on pricing and availability, contact the nearest TI field sales office or authorized distributor.



development support (continued)

DEVELOPMENT TOOL	PLATFORM	PART NUMBER					
Software – Code Generation Tools							
Assembler/Linker	PC™, Windows™ 95	TMDS3242850-02					
C Compiler/Assembler/Linker	PC, Windows 95	TMDS3242855-02					
Software – Emulation Debug Tools							
LF2407 eZdsp™	PC	TMDS3P761119					
Code Composer 4.12, Code Generation 7.0	PC	TMDS324012xx					
Hardware – Emulation Debug Tools							
XDS510XL [™] Board (ISA card), w/JTAG cable	PC	TMDS00510					
XDS510PP™ Pod (Parallel Port) w/JTAG cable	PC	TMDS00510PP					

Table 15. Development Support Tools

Table 16. TMS320F240-Specific Development Tools

DEVELOPMENT TOOL	PLATFORM	PART NUMBER				
Hardware – Evaluation/Starter Kits						
TMS320LF2407A EVM	PC, Windows 95, Windows™ 98	TMDX3P701016				
TMS320F240 EVM	PC	TMDX326P124X				
TMS320F243 EVM	PC, Windows 95	TMDS3P604030				

device and development-support tool nomenclature

To designate the stages in the product development cycle, Texas Instruments assigns prefixes to the part numbers of all TMS320[™] DSP devices and support tools. Each TMS320 member has one of three prefixes: TMX, TMP, or TMS. Texas Instruments recommends two of three possible prefix designators for its support tools: TMDX and TMDS. These prefixes represent evolutionary stages of product development from engineering prototypes (TMX/TMDX) through fully qualified production devices/tools (TMS/TMDS). This development flow is defined below.

Device development evolutionary flow:

- **TMX** Experimental device that is not necessarily representative of the final device's electrical specifications
- **TMP** Final silicon die that conforms to the device's electrical specifications but has not completed quality and reliability verification
- **TMS** Fully qualified production device

Support tool development evolutionary flow:

- **TMDX** Development support product that has not completed TI's internal qualification testing
- TMDS Fully qualified development-support product

TMX and TMP devices and TMDX development-support tools are shipped against the following disclaimer:

"Developmental product is intended for internal evaluation purposes."

eZdsp is a trademark of Spectrum Digital, Inc.



XDS510XL, XDS510PP, and TMS320 are trademarks of Texas Instruments.

PC is a trademark of International Business Machines Corp.

Windows is a registered trademark of Microsoft Corporation.

device and development-support tool nomenclature (continued)

TMS devices and TMDS development-support tools have been fully characterized, and the quality and reliability of the device have been fully demonstrated. TI's standard warranty applies.

Predictions show that prototype devices (TMX or TMP) have a greater failure rate than the standard production devices. Texas Instruments recommends that these devices not be used in any production system because their expected end-use failure rate is still undefined. Only gualified production devices are to be used.

TI device nomenclature also includes a suffix with the device family name. This suffix indicates the package type (for example, PN, PQ, and PZ) and temperature range (for example, L). Figure 16 provides a legend for reading the complete device name for any TMS320x2xx family member.



[†] TQFP = Thin Quad Flat Package

Figure 16. TMS320 Device Nomenclature

documentation support

Extensive documentation supports all of the TMS320 family generations of devices from product announcement through applications development. The types of documentation available include: data sheets, such as this document, with design specifications; complete user's guides for all devices and development-support tools; and hardware and software applications. To receive copies of TMS320 literature, contact the Literature Response Center at 800/477-8924.

A series of DSP textbooks is published by Prentice-Hall and John Wiley & Sons to support DSP research and education. The TMS320 newsletter, *Details on Signal Processing*, is published quarterly and distributed to update TMS320 customers on product information. The TMS320 DSP bulletinboard service (BBS) provides access to a wealth of information pertaining to the TMS320 family, including documentation, source code, and object code for many DSP algorithms and utilities. The BBS can be reached at 281/274-2323.

Updated information on the TMS320 DSP controllers can be found on the worldwide web at: http://www.ti.com.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

absolute maximum ratings over operatin	ng free-air temperature range	e (unless otherwise noted) [†]
Supply voltage range, V _{DD} ‡		–0.3 V to 7 V
Input voltage range		–0.3 V to 7 V
Output voltage range		\ldots –0.3 V to 7 V
Operating free-air temperature range, T _A :	L version	\ldots 0°C to 70°C
	A version	–40°C to 85°C
	S, Q versions	40°C to125°C
Storage temperature range, T _{stg}		–55°C to 150°C

[†] Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

 \ddagger All voltage values are with respect to V_{SS}.

recommended operating conditions

			MIN	NOM	MAX	UNIT
V _{DD}	Supply voltage		4.5	5	5.5	V
VSS	Supply ground			0		V
VIH		XTAL1/CLKIN	3		V _{DD} + 0.3	
	High-level input voltage	PORESET, NMI, RS, and TRST	2.2		V _{DD} + 0.3	V
		All other inputs	2		V _{DD} + 0.3	
	Level level l'anot colle en	XTAL1/CLKIN	-0.3		0.7	
VIL	Low-level input voltage	All other inputs	-0.3		0.8	V
	High-level output current, V_{OH} = 2.4 V	RS			-19	
ЮН		See complete listing of pin names§			-16	mA
		All other outputs			-23	
		RS			8	
lol	Low-level output current, $V_{OL} = 0.6 V$	See complete listing of pin names§			7.5	mA
		All other outputs			14.5	
		L version	0		70	
ТĄ	Operating free-air temperature	A version	-40		85	°C
		S, Q versions	-40		125	
T _{FP}	Flash programming operating temperature	L, A, S, Q versions	-40		85	°C
Θ_{JA}	Thermal resistance, junction-to-ambient				40	°C/W
ΘJC	Thermal resistance, junction-to-case				9.9	°C/W

§IOPA[0:3], SCIRXD/IO, SCITXD/IO, XINT2/IO, XINT3/IO, ADCSOC/IOPC0, TMRDIR/IOPB6, TMRCLK/IOPB7 EMU0, EMU1/OFF



output current variation with output voltage: SPICE simulation results

Condition: Temperature : 150° C Voltage : 4.5 V

Table 17. Typical Output Source Current vs. Output Voltage High

	2.4 V	3.0 V	3.5 V	4.0 V
RS	–19 mA	–16 mA	–12 mA	-6 mA
See complete listing of pin names [†]	–16 mA	–13.5 mA	–9.5 mA	–5.0 mA
All other inputs	–23 mA	–18.5 mA	–13 mA	–6.5 mA

[†]IOPA[0:3], SCIRXD/IO, SCITXD/IO, XINT2/IO, XINT3/IO, ADCSOC/IOPC0, TMRDIR/IOPB6, TMRCLK/IOPB7 EMU0, EMU1/OFF

Table 18. Typical Output Sink Current vs. Output Voltage Low

	0.6 V	0.4 V	0.2 V
RS	8 mA	6 mA	3 mA
See complete listing of pin names [†]	7.5 mA	5 mA	2.5 mA
All other inputs	14.5 mA	10 mA	5.0 mA

TIOPA[0:3], SCIRXD/IO, SCITXD/IO, XINT2/IO, XINT3/IO, ADCSOC/IOPC0, TMRDIR/IOPB6, TMRCLK/IOPB7 EMU0, EMU1/OFF

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
VOH	High-level output voltage	5-V operation, I _{OH} = MAX	2.4			V
VOL	Low-level output voltage	5-V operation, I _{OL} = MAX			0.6	V
		TRST pin with internal pulldown	-10		500	
II.	Input current (V _I = V _{SS} or V _{DD})	EMU0, EMU1/OFF, TMS, TCK, and TDI, with internal pullup	-500		10	μA
		All other input pins	-10		10	
IOZ	Output current, high-impedance state (off-state)	$V_{O} = V_{DD} \text{ or } 0 V$	-5		5	μA
	Supply current, operating mode	5-V operation, t _{C(CO)} = 50 ns		80		
	Supply current, Idle 1 low-power mode	5-V operation, t _{C(CO)} = 50 ns		50		
IDD	Supply current, Idle 2 low-power mode	5-V operation, t _{C(CO)} = 50 ns		7		mA
	Supply current, PLL power-down mode	5-V operation, t _{C(CO)} = 50 ns		1		
	Supply current, OSC power-down mode	5-V operation, t _{c(CO)} = 50 ns		400		μA
Ci	Input capacitance			15		pF
Co	Output capacitance			15		pF
	Flash programming supply current	5-V operation, $t_{C(CO)} = 50$ ns		10		mA



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



Figure 17. Test Load Circuit

signal transition levels

The data in this section is shown for the 5-V version (C2xx). Note that some of the signals use different reference voltages, see the recommended operating conditions table. TTL-output levels are driven to a minimum logic-high level of 2.4 V and to a maximum logic-low level of 0.7 V.

Figure 18 shows the TTL-level outputs.



Figure 18. TTL-Level Outputs

TTL-compatible output transition times are specified as follows:

- For a *high-to-low transition*, the level at which the output is said to be no longer high is below 80% of the total voltage range and lower, and the level at which the output is said to be low is 20% of the total voltage range and lower.
- For a *low-to-high transition*, the level at which the output is said to be no longer low is 20% of the total voltage range and higher, and the level at which the output is said to be high is 80% of the total voltage range and higher.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

PARAMETER MEASUREMENT INFORMATION

Figure 19 shows the TTL-level inputs.



Figure 19. TTL-Level Inputs

TTL-compatible input transition times are specified as follows:

- For a *high-to-low transition* on an input signal, the level at which the input is said to be no longer high is 90% of the total voltage range and lower, and the level at which the input is said to be low is 10% of the total voltage range and lower.
- For a *low-to-high transition* on an input signal, the level at which the input is said to be no longer low is 10% of the total voltage range and higher, and the level at which the input is said to be high is 90% of the total voltage range and higher.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

PARAMETER MEASUREMENT INFORMATION

timing parameter symbology

Timing parameter symbols used are created in accordance with JEDEC Standard 100. To shorten the symbols, some of the pin names and other related terminology have been abbreviated as follows:

А	A[15:0]	MS	Memory strobe pins \overline{IS} , \overline{DS} , or \overline{PS}
CI	XTAL1/CLKIN	R	READY
СО	CLKOUT/IOPC1	RD	Read cycle or W/R
D	D[15:0]	RS	RS or PORESET
INT	NMI, XINT1, XINT2/IO, and XINT3/IO	W	Write cycle or \overline{WE}
Lowercase	e subscripts and their meanings:	Letters a	and symbols and their meanings:
а	access time	Н	High
С	cycle time (period)	L	Low
d	delay time	V	Valid
f	fall time	Х	Unknown, changing, or don't care level
h	hold time	Z	High impedance
r	rise time		
su	setup time		
t	transition time		
v	valid time		
w	pulse duration (width)		

general notes on timing parameters

All output signals from the TMS320F240 device (including CLKOUT) are derived from an internal clock such that all output transitions for a given half-cycle occur with a minimum of skewing relative to each other.

The signal combinations shown in the following timing diagrams may not necessarily represent actual cycles. For actual cycle examples, see the appropriate cycle description section of this data sheet.



NOTES: A. For the values of C1 and C2, see the crystal manufacturer's specification.

B. Use this configuration in conjunction with OSCBYP pin pulled low.

C. Texas Instruments recommends that customers have the resonator/crystal vendor characterize the operation of their device with the DSP chip. The resonator/crystal vendor has the equipment and expertise to tune the tank circuit. The vendor can also advise the customer regarding the proper tank component values that will ensure start-up and stability over the entire operating range.

Figure 20. Recommended Crystal/Clock Connection



CLOCK OPTIONS

clock options

PARAMETER	CLKMD[1:0]
Clock-in mode, divide-by-2	00
Clock-in mode, divide-by-1	01
PLL enabled, divide-by-2 before PLL lock	10
PLL enabled, divide-by-1 before PLL lock	11

timings with the PLL circuit disabled

	PARAMETER	TEST CONDITIONS	MIN	MAX	UNIT
f _X	Input clock frequency, divide-by-2 mode	$T_A = -40^{\circ}C$ to $125^{\circ}C$	0†	40	MHz
f _X	Input clock frequency, divide-by-1 mode	$T_A = -40^{\circ}C$ to $125^{\circ}C$	0†	20	MHz

[†] This device utilizes a fully static design and, therefore, can operate with input clock cycle time [t_{c(CI)}] approaching infinity. The device is characterized at frequencies approaching 0 Hz.

switching characteristics over recommended operating conditions [H = 0.5 $t_{c(CO)}$] (see Note 1 and Figure 21)

	PARAMETER	CLOCK MODE	MIN	TYP	MAX	UNIT
		CLKIN divide by 2		2t _{c(CI)}	†	
^t c(CPU)	Cycle time, CPUCLK	CLKIN divide by 1		^t c(Cl)		ns
		CPUCLK divide by 2		2t _{c(CPU)}	†	
^t c(SYS)	Cycle time, SYSCLK	CPUCLK divide by 4 [‡]		^{4t} c(CPU)		ns
	Cycle time, CLKOUT	CLKIN divide by 2		2t _{c(CI)}	†	
^t c(CO)		CLKIN divide by 1		^t c(Cl)	†	ns
^t d(CIH-CO)	Delay time, XTAL1/CLKIN high to CLKOUT high	jh/low	3	18	32	ns
^t f(CO)	Fall time, CLKOUT			5		ns
^t r(CO)	Rise time, CLKOUT			5		ns
^t w(COL)	Pulse duration, CLKOUT low		H–10	H–6	H–1	ns
^t w(COH)	Pulse duration, CLKOUT high		H+0	H+4	H+8	ns

[†] This device utilizes a fully static design and, therefore, can operate with input clock cycle time [t_{c(CI)}] approaching infinity. The device is characterized at frequencies approaching 0 Hz.

[‡] SYSCLK is initialized to divide-by-4 mode by any device reset.

NOTE 1: Timings assume CLKOUT is set to output CPUCLK. CLKOUT is initialized to CPUCLK by power-on reset.

timing requirements over recommended operating conditions (see Figure 21)

		CLOCK-IN MODE	MIN	MAX	UNIT
t _{C(CI)} Cycle		Divide by 2	25	†	
	Cycle time, X IAL1/CLKIN	Divide by 1	50	†	ns
^t f(CI)	(CI) Fall time, XTAL1/CLKIN			5	ns
^t r(CI)	tr(CI) Rise time, XTAL1/CLKIN			5	ns
tw(CIL) Pulse duration, XTAL1/CLKIN low as a percentage of t _{C(CI)}		45	55	%	
^t w(CIH)	Pulse duration, XTAL1/CLKIN high as a percentage of t_0	c(CI)	45	55	%

[†] This device utilizes a fully static design and, therefore, can operate with input clock cycle time [t_{c(CI)}] approaching infinity. The device is characterized at frequencies approaching 0 Hz.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



Figure 21. External Divide-by-Two Clock Timings

external reference crystal with PLL-circuit-enabled clock option

The internal oscillator is enabled by connecting \overline{OSCBYP} to V_{DD} and connecting a crystal across XTAL1/CLKIN and XTAL2 pins as shown in Figure 20. The crystal should be in either fundamental or overtone operation and parallel resonant, with an effective series resistance of 30 Ω and a power dissipation of 1 mW; it should be specified at a load capacitance of 20 pF.

timings with the PLL circuit enabled

	PARAMETER	EXTERNAL REFERENCE CRYSTAL	MIN	ТҮР	МАХ	UNIT
		4 MHz		4		
f _x	Input clock frequency	6 MHz	6		MHz	
		8 MHz		8		
C1, C2	Load capacitance			10		pF



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

switching characteristics over recommended operating conditions [H = $0.5 t_{c(CO)}$] (see Figure 22)

	PARAMETER	CLOCK MODE	MIN	TYP	MAX	UNIT
^t c(CPU)		before PLL lock, CLKIN divide by 2		2t _{c(CI)}	†	
	Cycle time, CPUCLK	before PLL lock, CLKIN divide by 1		^t c(CI)		ns
		after PLL lock		50		
		CPUCLK divide by 2		2t _c (CPU)	†	
^t c(SYS)	Cycle time, SYSCLK	CPUCLK divide by 4 [‡]		4t _c (CPU)		ns
tc(CO)	Cycle time, CLKOUT		50		†	ns
^t f(CO)	Fall time, CLKOUT			5		ns
^t r(CO)	Rise time, CLKOUT			5		ns
tw(COL)	Pulse duration, CLKOUT low		H–10	H–6	H–1	ns
^t w(COH)	Pulse duration, CLKOUT high		H+0	H+4	H+8	ns
tp	Transition time, PLL synchronized after	before PLL lock, CLKIN divide by 2			2000t _{C(CI)}	
	PLL enabled	before PLL lock, CLKIN divide by 1			1000t _{c(CI)}	ns

[†] This device utilizes a fully static design and, therefore, can operate with input clock cycle time [t_{c(CI)}] approaching infinity. The device is characterized at frequencies approaching 0 Hz.

[‡] SYSCLK is initialized to divide-by-4 mode by any device reset.

timing requirements over recommended operating conditions (see Note 1 and Figure 22)

		EXTERNAL REFERENCE CRYSTAL	MIN	MAX	UNIT
		4 MHz	250	†	
^t c(Cl)	Cycle time, XTAL1/CLKIN	6 MHz	167		ns
		8 MHz	125		
^t f(Cl)	CI) Fall time, XTAL1/CLKIN			5	ns
^t r(Cl)	(CI) Rise time, XTAL1/CLKIN			5	ns
^t w(CIL)	v(CIL) Pulse duration, XTAL1/CLKIN low as a percentage of t _{C(CI)}		40	60	%
^t w(CIH)	Pulse duration, XTAL1/CLKIN high as a percentage of $t_{\mbox{c(CI)}}$		40	60	%

[†] This device utilizes a fully static design and, therefore, can operate with input clock cycle time [t_{c(CI)}] approaching infinity. The device is characterized at frequencies approaching 0 Hz.

NOTE 1: Timings assume CLKOUT is set to output CPUCLK. CLKOUT is initialized to CPUCLK by power-on reset.



Figure 22. CLKIN-to-CLKOUT Timings for PLL Oscillator Mode, Multiply-by-5 Option With 4-MHz Crystal



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

low-power mode timings

switching characteristics over recommended operating conditions (see Figure 23, Figure 24, Figure 25, and Figure 26)

	PARAMETER	LOW-POWER MODES	MIN TYP	MAX	UNIT
^t d(WAKE-A)	Delay time, CLKOUT switching to	Idle 1 and Idle 2	15 X t _{c(CO)}		
	program execution resume (see Note 1)	PLL or OSC power down	15 X t _{C(CI)}		ns
^t d(IDLE-COH)	Delay time, Idle instruction executed to CLKOUT high (see Note 1)	Idle 2, PLL power down, OSC power down	500		ns
^t d(WAKE-LOCK)	Delay time, CLKOUT switching to PLL synchronized (see Note 1)	PLL or OSC power down	100		μs
^t d(WAKE-OSC)	Delay time, wakeup interrupt asserted to oscillator running	OSC power down	10		ms
^t d(IDLE-OSC)	Delay time, Idle instruction executed to oscillator power off	OSC power down	60		μs

NOTE 1: Timings assume CLKOUT is set to output CPUCLK. CLKOUT is initialized to CPUCLK by power-on reset.







SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



Figure 26. OSC Power-Down Entry and Exit Timings



memory and parallel I/O interface read timings

switching characteristics over recommended operating conditions for a memory read @5 V (see Figure 27)

	PARAMETER	MIN	MAX	UNIT
^t d(CO-A)RD	Delay time, CLKOUT/IOPC1 low to address valid		17	ns
td(CO-SL)RD	Delay time, CLKOUT/IOPC1 low to STRB low		10	ns
^t d(CO-SH)RD	Delay time, CLKOUT/IOPC1 low to STRB high		6	ns
^t d(CO-ACTL)RD	Delay time, CLKOUT/IOPC1 low to PS, DS, IS, and BR low		10	ns
td(CO-ACTH)RD	Delay time, CLKOUT/IOPC1 low to PS, DS, IS, and BR high		10	ns

timing requirements over recommended operating conditions for a memory read @ 5 V $[H = 0.5t_{C(CO)}]^{\dagger}$ (see Figure 27)

			MIN	MAX	UNIT
t _{a(A)}	Access time, from address valid to read data	0 wait state		2H – 32	ns
		1 wait state		4H – 32	
t _{su} (D-COL)RD	Setup time, data read before CLKOUT/IOPC1 low		15		ns
^t h(COL-D)RD	Hold time, data read after CLKOUT/IOPC1 low		2		ns

[†] All timings with respect to CLKOUT/IOPC1 assume CLKSRC[1:0] bits are set to select CPUCLK for output.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



memory and parallel I/O interface read timings (continued)





memory and parallel I/O interface write timings

switching characteristics over recommended operating conditions for a memory write $@ 5 V [H = 0.5t_{c(CO)}]^{\dagger}$ (see Figure 28)

	PARAMETER	MIN	MAX	UNIT
^t d(CO-A)W	Delay time, CLKOUT/IOPC1 high to address valid		17	ns
^t d(CO-D)	Delay time, CLKOUT/IOPC1 low to data bus driven		15	ns
^t h(WH-A)	Hold time, address valid after WE high	H – 8		ns
^t w(WH)	Pulse duration, WE high	2H – 11		ns
^t w(WL)	Pulse duration, WE low	2H – 11		
td(CO-WL)	Delay time, CLKOUT/IOPC1 low to WE low		9	ns
^t d(CO-WH)	Delay time, CLKOUT/IOPC1 low to WE high		9	ns
^t su(D-WH)	Setup time, write data valid before WE high	2H – 8		ns
^t hz(WH-D)	High-impedance time, WE high to data bus Hi-Z	0	5	ns
td(CO-SL)W	Delay time, CLKOUT/IOPC1 low to STRB low		10	ns
^t d(CO-SH)W	Delay time, CLKOUT/IOPC1 low to STRB high		6	ns
^t d(CO-ACTL)W	Delay time, CLKOUT/IOPC1 high to PS, DS, IS, and BR low		10	ns
^t d(CO-ACTH)W	Delay time, CLKOUT/IOPC1 high to PS, DS, IS, and BR high		10	ns
td(CO-RWL)	Delay time, CLKOUT/IOPC1 high to R/W low		10	ns
td(CO-RWH)	Delay time, CLKOUT/IOPC1 high to R/W high		10	ns

[†] All timings with respect to CLKOUT/IOPC1 assume CLKSRC[1:0] bits are set to select CPUCLK for output.


SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



memory and parallel I/O interface write timings (continued)

Figure 28. Memory Interface Write Timings



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

I/O timing variation with load capacitance: SPICE simulation results

Condition: Temperature :- 40 to 150° C Capacitance :5-125pF Voltage : 5.0 V

2.2 V 0.8 V

Figure 29. Rise and Fall Time Diagram

Table 19. Timing Variation With Load Capacitance: $[V_{CC} = 5 V, V_{OH} = 2.2 V, V_{OL} = 0.8 V]$

	– 40°C		27°C		150°C	
	RISE	FALL	RISE	FALL	RISE	FALL
5 pF	2.5 ns	3.6 ns	3.1 ns	4.5 ns	4.3 ns	6.2 ns
25 pF	3.1 ns	4.6 ns	4.0 ns	5.7 ns	5.6 ns	7.8 ns
50 pF	3.9 ns	5.9 ns	5.0 ns	7.3 ns	7.2 ns	9.9 ns
75 pF	4.7 ns	7.3 ns	6.1 ns	8.9 ns	8.8 ns	11.7 ns
100 pF	5.4 ns	8.9 ns	7.2 ns	10.6 ns	10.5 ns	13.8 ns
125 pF	6.2 ns	10.4 ns	8.3 ns	12.2 ns	12.1 ns	15.8 ns



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

READY timings

timing requirements over recommended operating conditions $[H = 0.5t_{c(CO)}]^{\dagger}$ (see Figure 30)

		MIN	MAX	UNIT
tsu(R-CO)	Setup time, READY low before CLKOUT/IOPC1 high	14		ns
^t h(CO-R)	Hold time, READY low after CLKOUT/IOPC1 high	0		ns
^t v(R)ARD	Valid time, READY after address valid on read		3H – 31	ns
^t v(R)AW	Valid time, READY after address valid on write		4H – 31	ns

[†] The READY timings are based on one software wait state. At full speed operation, the F240 does not allow for single READY-based wait states.



Figure 30. READY Timings



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

RS and **PORESET** timings

switching characteristics over recommended operating conditions for a reset $[H = 0.5t_{c(CO)}]$ (see Figure 31, Figure 32, and Figure 33)

	PARAMETER	MIN	MAX	UNIT
^t w(RSL1)	Pulse duration, RS low [†]	8t _{c(SYS)}		ns
^t d(RS)	Delay time, RS low to program address at reset vector	4H		ns
^t d(EX)	Delay time, RS high to reset vector executed	32H		ns
td(EX)	Delay time, RS high to reset vector executed	32H		

[†] The parameter $t_{W(RSL1)}$ refers to the time \overline{RS} is an output.

timing requirements over recommended operating conditions for a reset (see Figure 31, Figure 32, and Figure 33)

		MIN	MAX	UNIT
^t w(RSL)	Pulse duration, RS or PORESET low [‡]	5		ns

[‡] The parameter $t_{W(RSL)}$ refers to the time \overline{RS} is an input.



† PORESET is required to be driven low during power up to ensure all clock/PLL registers are reset to a known state.

After PORESET is high and oscillator starts up, it takes few clock edges (typically 4–8 oscillator cycles) for the I/Os to assume high-impedance state.

CLKOUT using on-chip oscillator.

Figure 31. Case With Crystal



 $[\]ddagger$ RS is a bidirectional (open-drain output) pin and can be optionally pulled low through an open-drain or open-collector drive circuit, or through a 2.7-k Ω resistor in series with a totem pole drive circuit. If RS is left undriven, then a 20-k Ω pullup resistor should be used.

[§] The start-up time of the on-chip oscillator depends on the crystal parameters, bypass capacitors, and board layout. Typical start-up time is about 10 ms.

SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

RS and **PORESET** timings (continued)



[†] PORESET is required to be driven low during power up to ensure all clock/PLL registers are reset to a known state.

 \ddagger RS is a bidirectional (open-drain output) pin and can be optionally pulled low through an open-drain or open-collector drive circuit, or through a 2.7-k Ω resistor in series with a totem pole drive circuit. If RS is left undriven, then a 20-k Ω pullup resistor should be used.

§ If external clock is used, after PORESET is high, it takes few valid clock edges (typically 4–8 clock-in cycles) for the I/Os to assume high-impedance state.

¶ CLKOUT using external oscillator.

Figure 32. Case With External Oscillator



[†] RS is driven low by any device reset, which includes asserting PORESET, RS, access to an illegal address, execution of a software reset, or a watchdog timer reset.

Figure 33. Power-On Reset Timings



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

XF, BIO, and MP/MC timings

switching characteristics over recommended operating conditions (see Figure 34)

	PARAMETER	MIN	MAX	UNIT
^t d(XF)	Delay time, CLKOUT high to XF high/low		11	ns

timing requirements over recommended operating conditions [H = $0.5t_{c(CO)}$] (see Figure 34)

		MIN	MAX	UNIT
^t w(BIOL)	Pulse duration, BIO low	2H + 16		ns
^t w(MPMCV)	Pulse duration, MP/MC valid [†]	2H + 24		ns

[†] This is the minimum time the MP/MC pin needs to be stable in order to be recognized by internal logic; however, for proper operation, the user must maintain a valid level for the duration of the entire memory access (or accesses) on- or off-chip.



[†] This is the minimum time the MP/MC pin needs to be stable in order to be recognized by internal logic; however, for proper operation, the user must maintain a valid level for the duration of the entire memory access (or accesses) on- or off-chip.

Figure 34. XF, BIO, and MP/MC Timings



TIMING EVENT MANAGER INTERFACE

PWM/CMP timings

PWM refers to PWM1/CMP1, PWM2/CMP2, PWM3/CMP3, PWM4/CMP4, PWM5/CMP5, PWM6/CMP6, T1PWM/T1CMP, T2PWM/T2CMP, T3PWM/T3CMP, PWM7/CMP7, PWM8/CMP8, and PWM9/CMP9.

switching characteristics over recommended operating conditions for PWM timing (see Figure 35)

	PARAMETER	MIN	MAX	UNIT
^t d(PWM)CO	Delay time, CLKOUT high to PWM output switching		12	ns

timing requirements over recommended operating conditions for PWM timing [H = $0.5t_{c(CO)}$] (see Figure 36 and Figure 37)

		MIN	MAX	UNIT
^t w(TMRDIR)	Pulse duration, TMRDIR low/high	4H + 12		ns
^t w(TMRCLKL)	Pulse duration, TMRCLK low as a percentage of TMRCLK cycle time	40	60	%
^t w(TMRCLKH)	Pulse duration, TMRCLK high as a percentage of TMRCLK cycle time	40	60	%
^t c(TMRCLK)	Cycle time, TMRCLK	$4 \times t_{c}(CPU)$		ns



Figure 35. PWM and Compare Output Timings



Figure 37. External Timer Direction Input Timings



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

capture and QEP timings

CAP refers to CAP1/QEP1/IOPC4, CAP2/QEP2/IOPC5, CAP3/IOPC6, and CAP4/IOPC7.

timing requirements over recommended operating conditions for CAP [H = $0.5t_{c(CO)}$] (see Figure 38)



Figure 38. Capture and QEP Input Timings



interrupt timings

PWM refers to PWM1/CMP1, PWM2/CMP2, PWM3/CMP3, PWM4/CMP4, PWM5/CMP5, PWM6/CMP6, T1PWM/T1CMP, T2PWM/T2CMP, T3PWM/T3CMP, PWM7/CMP7, PWM8/CMP8, and PWM9/CMP9.

INT refers to NMI, XINT1, XINT2/IO, and XINT3/IO. PDP refers to PDPINT.

switching characteristics over recommended operating conditions for interrupts (see Figure 40)

	PARAMETER	MIN	MAX	UNIT
^t d(PWM)PDP	Delay time, PDPINT low to PWM to high-impedance state	0	15	ns

timing requirements over recommended operating conditions for interrupts $[H = 0.5t_{c(CO)}]$ (see Figure 39 and Figure 40)

		MIN	MAX	UNIT
^t w(INT)	Pulse duration, INT input low/high	t _{c(SYS)} + 12		ns
^t w(PDP)	Pulse duration, PDPINT input low	2H + 18		ns
^t d(INT)	Delay time, INT low/high to interrupt-vector fetch	2t _{c(SYS)} + 4t _{c(CPU)}		ns



INT

Figure 39. External Interrupt Timings



Figure 40. Power-Drive Protection Interrupt Timings



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

general-purpose input/output timings

GPO refers to the digital output function of shared pins IOPA0-3, IOPB0-7, IOPC0-7, XINT2/IO, XINT3/IO.

GPI refers to the digital input function of shared pins IOPA0–3, IOPB0–7, IOPC0–7, XINT2/IO, XINT3/IO.

switching characteristics over recommended operating conditions for a GPI/O (see Figure 41)

PARAMETER			MIN	MAX	UNIT
	Delay time, CLKOUT low to GPO low/high	XINT2/IO, XINT3/IO, IOPB6, IOPB7, and IOPC0	33 35	ns	
		XINT2/IO, XINT3/IO, IOPB6, IOPB7, and IOPC033All other GPOs25			

timing requirements over recommended operating conditions for a GPI/O (see Figure 42)



Figure 42. General-Purpose Input Timings



SERIAL COMMUNICATIONS INTERFACE (SCI) I/O TIMINGS

timing characteristics	for SC	(see Note 2	2 and Figure	43)
------------------------	--------	-------------	--------------	-----

PARAMETER		(BRR - IS EVEN ANI	+ 1) D BRR = 0	(BRR + IS ODD AND	UNIT	
		MIN MAX		MIN	MAX	
tc(SCC)	Cycle time, SCICLK	16t _C	65536t _C	24t _C	65535t _C	ns
^t v(TXD)	Valid time, SCITXD data	t _{c(SCC)} -70	t _{c(SCC)} +70	t _{c(SCC)} -70	tc(SCC)+70	ns
t _{v(RXD)}	Valid time, SCIRXD data	16t _C		24t _C		ns

NOTE 2: t_c = system clock cycle time = 1/SYSCLK = $t_c(SYS)$



Figure 43. SCI Timings



SPI MASTER MODE TIMING PARAMETERS

SPI master mode timing information is listed in the following tables.

SPI master mode external timing parameters (clock phase = 0)[†] (see Figure 44)

		WHEN (SPIBRR + SPIBRR =	1) IS EVEN OR 0 OR 2	WHEN (SPIBRR + 1) IS ODD AND SPIBRR > 3		
		MIN	MAX	MIN	MAX	1
^t c(SPC)M	Cycle time, SPICLK	4tc‡	128t _c ‡	5tc‡	127t _C ‡	ns
^t w(SPCH)M [§]	Pulse duration, SPICLK high (clock polarity = 0)	0.5t _{c(SPC)M} -70	^{0.5t} c(SPC)M	0.5t _{C(SPC)M} -0.5t _C -70	0.5t _C (SPC)M -0.5t _C	
^t w(SPCL)M [§]	Pulse duration, SPICLK low (clock polarity = 1)	0.5t _{c(SPC)M} -70	^{0.5t} c(SPC)M	0.5t _{C(SPC)M} -0.5t _C -70	0.5t _C (SPC)M -0.5t _C	ns
^t w(SPCL)M [§]	Pulse duration, SPICLK low (clock polarity = 0)	0.5t _{C(SPC)M} -70	^{0.5t} c(SPC)M	0.5t _{C(SPC)M} +0.5t _C -70	0.5t _C (SPC)M + 0.5t _C	
^t w(SPCH)M [§]	Pulse duration, SPICLK high (clock polarity = 1)	0.5t _{c(SPC)M} -70	^{0.5t} c(SPC)M	0.5t _{C(SPC)M} +0.5t _C -70	$0.5t_{C}(SPC)M + 0.5t_{C}$	ns
^t d(SPCH-SIMO)M [§]	Delay time, SPICLK high (clock polarity = 0) to SPISIMO valid	- 10	10	- 10	10	
^t d(SPCL-SIMO)M [§]	Delay time, SPICLK low (clock polarity = 1) to SPISIMO valid	- 10	10	- 10	10	ns
^t v(SPCL-SIMO)M [§]	Valid time, SPISIMO data valid after SPICLK low (clock polarity =0)	0.5t _{c(SPC)M} -70		0.5t _c (SPC)M+0.5t _c -70		
^t v(SPCH-SIMO)M [§]	Valid time, SPISIMO data valid after SPICLK high (clock polarity =1)	0.5t _{c(SPC)M} -70		0.5t _c (SPC)M+0.5t _c -70		ns
^t su(SOMI-SPCL)M [§]	Setup time, SPISOMI before SPICLK low (clock polarity = 0)	0		0		
^t su(SOMI-SPCH)M [§]	Setup time, SPISOMI before SPICLK high (clock polarity = 1)	0		0		ns
^t v(SPCL-SOMI)M [§]	Valid time, SPISOMI data valid after SPICLK low (clock polarity = 0)	0.25t _{C(SPC)M} -70		0.5t _c (SPC)M-0.5t _c -70		
^t v(SPCH-SOMI)M [§]	Valid time, SPISOMI data valid after SPICLK high (clock polarity = 1)	0.25t _{c(SPC)M} -70		0.5t _{c(SPC)M} -0.5t _c -70		ns

[†] The MASTER/SLAVE bit (SPICTL.2) is set and the CLOCK PHASE bit (SPICTL.3) is cleared. [‡] t_c = system clock cycle time = 1/SYSCLK = $t_c(SYS)$ [§] The active edge of the SPICLK signal referenced is controlled by the CLOCK POLARITY bit (SPICCR.6).

SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



PARAMETER MEASUREMENT INFORMATION

[†] The SPISTE signal must be active before the SPI communication stream starts; the SPISTE signal must remain active until the SPI communication stream is complete.

Figure 44. SPI Master Mode External Timings (Clock Phase = 0)



		WHEN (SPIBRR + SPIBRR =	1) IS EVEN OR 0 OR 2	WHEN (SPIBRR + 1) IS ODD AND SPIBRR > 3		UNIT
		MIN	MAX	MIN	MAX	1
^t c(SPC)M	Cycle time, SPICLK	4t _c ‡	128t _c ‡	5tc‡	127t _C ‡	ns
^t w(SPCH)M [§]	Pulse duration, SPICLK high (clock polarity = 0)	0.5t _{c(SPC)M} -70	0.5t _C (SPC)M	0.5t _C (SPC)M-0.5t _C -70	0.5t _C (SPC)M -0.5t _C	ns
^t w(SPCL)M [§]	Pulse duration, SPICLK low (clock polarity = 1)	0.5t _{c(SPC)M} -70	0.5t _c (SPC)M	0.5t _{C(SPC)M} -0.5t _C -70	0.5t _{c(SPC)M} –0.5t _c	
^t w(SPCL)M [§]	Pulse duration, SPICLK low (clock polarity = 0)	0.5t _c (SPC)M-70	^{0.5t} c(SPC)M	0.5t _C (SPC)M+0.5t _C -70	$0.5t_{C}(SPC)M + 0.5t_{C}$	
^t w(SPCH)M [§]	Pulse duration, SPICLK high (clock polarity = 1)	0.5t _{c(SPC)M} -70	0.5t _C (SPC)M	0.5t _C (SPC)M+0.5t _C -70	$0.5t_{C}(SPC)M + 0.5t_{C}$	ns
^t su(SIMO-SPCH)M [§]	Setup time, SPISIMO data valid before SPICLK high (clock polarity = 0)	0.5t _{c(SPC)M} -70		0.5t _{c(SPC)M} -70		
^t su(SIMO-SPCL)M [§]	Setup time, SPISIMO data valid before SPICLK low (clock polarity = 1)	0.5t _{c(SPC)M} -70		0.5t _{c(SPC)M} –70		ns
^t v(SPCH-SIMO)M [§]	Valid time, SPISIMO data valid after SPICLK high (clock polarity =0)	0.5t _{c(SPC)M} -70		0.5t _{c(SPC)M} -70		
^t v(SPCL-SIMO)M [§]	Valid time, SPISIMO data valid after SPICLK low (clock polarity =1)	0.5t _{c(SPC)M} -70		0.5t _{c(SPC)M} -70		ns
^t su(SOMI-SPCH)M [§]	Setup time, SPISOMI before SPICLK high (clock polarity = 0)	0		0		
^t su(SOMI-SPCL)M [§]	Setup time, SPISOMI before SPICLK low (clock polarity = 1)	0		0		ns
^t v(SPCH-SOMI)M [§]	Valid time, SPISOMI data valid after SPICLK high (clock polarity = 0)	0.25t _{c(SPC)M} -70		0.5t _{C(SPC)M} -70		
^t v(SPCL-SOMI)M [§]	Valid time, SPISOMI data valid after SPICLK low (clock polarity = 1)	0.25t _{c(SPC)M} -70		0.5t _{c(SPC)M} -70		ns

SPI master mode external timing parameters (clock phase = 1)[†] (see Figure 45)

[†] The MASTER/SLAVE bit (SPICTL.2) is set and the CLOCK PHASE bit (SPICTL.3) is set. [‡] t_c = system clock cycle time = 1/SYSCLK = t_c(SYS) § The active edge of the SPICLK signal referenced is controlled by the CLOCK POLARITY bit (SPICCR.6).

DSP TMS320F240 CONTROLLER

POST OFFICE BOX 1443 • HOUSTON, TEXAS 77251-1443

SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



PARAMETER MEASUREMENT INFORMATION

[†] The SPISTE signal must be active before the SPI communication stream starts; the SPISTE signal must remain active until the SPI communication stream is complete.

Figure 45. SPI Master Mode External Timings (Clock Phase = 1)



SPI SLAVE MODE TIMING PARAMETERS

Slave mode timing information is listed in the following tables.

SPI slave mode external timing parameters (clock phase = 0)[†] (see Figure 46)

		MIN	MAX	UNIT
^t c(SPC)S	Cycle time, SPICLK	8tc‡		ns
^t w(SPCH)S [§]	Pulse duration, SPICLK high (clock polarity = 0)	0.5t _{c(SPC)S} -70	0.5t _{c(SPC)S}	
^t w(SPCL)S [§]	Pulse duration, SPICLK low (clock polarity = 1)	0.5t _{C(SPC)S} -70	0.5t _C (SPC)S	ns
^t w(SPCL)S [§]	Pulse duration, SPICLK low (clock polarity = 0)	0.5t _{C(SPC)S} -70	0.5t _C (SPC)S	
^t w(SPCH)S [§]	Pulse duration, SPICLK high (clock polarity = 1)	0.5t _{C(SPC)S} -70	0.5t _C (SPC)S	ns
^t d(SPCH-SOMI)S [§]	Delay time, SPICLK high (clock polarity = 0) to SPISOMI valid	0.375t _{C(SPC)S} -70		
^t d(SPCL-SOMI)S [§]	Delay time, SPICLK low (clock polarity = 1) to SPISOMI valid	0.375t _{C(SPC)S} -70		ns
^t v(SPCL-SOMI)S [§]	Valid time, SPISOMI data valid after SPICLK low (clock polarity =0)	0.75t _c (SPC)S		
^t v(SPCH-SOMI)S [§]	Valid time, SPISOMI data valid after SPICLK high (clock polarity =1)	0.75t _c (SPC)S		ns
^t su(SIMO-SPCL)S [§]	Setup time, SPISIMO before SPICLK low (clock polarity = 0)	0		
^t su(SIMO-SPCH)S [§]	Setup time, SPISIMO before SPICLK high (clock polarity = 1)	0		ns
tv(SPCL-SIMO)S§	Valid time, SPISIMO data valid after SPICLK low (clock polarity = 0)	0.5t _C (SPC)S		
^t v(SPCH-SIMO)S [§]	Valid time, SPISIMO data valid after SPICLK high (clock polarity = 1)	0.5t _C (SPC)S		115

[†] The MASTER/SLAVE bit (SPICTL.2) is cleared and the CLOCK PHASE bit (SPICTL.3) is cleared.

 t_{c} = system clock cycle time = 1/SYSCLK = $t_{c}(SYS)$ § The active edge of the SPICLK signal referenced is controlled by the CLOCK POLARITY bit (SPICCR.6).



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



PARAMETER MEASUREMENT INFORMATION

[†] The SPISTE signal must be active before the SPI communication stream starts; the SPISTE signal must remain active until the SPI communication stream is complete.

Figure 46. SPI Slave Mode External Timing (Clock Phase = 0)



SPI slave mode external timing parameters (clock phase = 1)[†] (see Figure 47)

		MIN	MAX	UNIT
^t c(SPC)S	Cycle time, SPICLK	8tc‡		ns
^t w(SPCH)S [§]	Pulse duration, SPICLK high (clock polarity = 0)	0.5t _c (SPC)S-70	0.5t _C (SPC)S	
^t w(SPCL)S [§]	Pulse duration, SPICLK low (clock polarity = 1)	0.5t _c (SPC)S-70	0.5t _c (SPC)S	ns
^t w(SPCL)S [§]	Pulse duration, SPICLK low (clock polarity = 0)	0.5t _c (SPC)S-70	0.5t _C (SPC)S	
^t w(SPCH)S [§]	Pulse duration, SPICLK high (clock polarity = 1)	0.5t _c (SPC)S-70	0.5t _C (SPC)S	ns
^t su(SOMI-SPCH)S [§]	Setup time, SPISOMI before SPICLK high (clock polarity = 0)	0.125t _{C(SPC)S}		
^t su(SOMI-SPCL)S [§]	Setup time, SPISOMI before SPICLK low (clock polarity = 1)	0.125t _{c(SPC)S}		ns
^t v(SPCH-SOMI)S [§]	Valid time, SPISOMI data valid after SPICLK high (clock polarity =0)	0.75t _c (SPC)S		
^t v(SPCL-SOMI)S [§]	Valid time, SPISOMI data valid after SPICLK low (clock polarity =1)	0.75t _c (SPC)S		ns
^t su(SIMO-SPCH)S [§]	Setup time, SPISIMO before SPICLK high (clock polarity = 0)	0		
^t su(SIMO-SPCL)S [§]	Setup time, SPISIMO before SPICLK low (clock polarity = 1)	0		ns
^t v(SPCH-SIMO)S [§]	Valid time, SPISIMO data valid after SPICLK high (clock polarity = 0)	0.5t _C (SPC)S		20
^t v(SPCL-SIMO)S [§]	Valid time, SPISIMO data valid after SPICLK low (clock polarity = 1)	0.5t _C (SPC)S		115

[†] The MASTER/SLAVE bit (SPICTL.2) is cleared and the CLOCK PHASE bit (SPICTL.3) is set. [‡] t_c = system clock cycle time = 1/SYSCLK = t_c(SYS) [§] The active edge of the SPICLK signal referenced is controlled by the CLOCK POLARITY bit (SPICCR.6).



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002



PARAMETER MEASUREMENT INFORMATION

[†] The SPISTE signal must be active before the SPI communication stream starts; the SPISTE signal must remain active until the SPI communication stream is complete.

Figure 47. SPI Slave Mode External Timing (Clock Phase = 1)



10-bit dual analog-to-digital converter (ADC)

recommended operating conditions

		MIN	NOM	MAX	UNIT
VCCA	Analog supply voltage	4.5	5	5.5	V
VSSA	Analog ground		0		V
VREFHI	Analog supply reference source [†]	VREFLO		VCCA	V
VREFLO	Analog ground reference source [†]	VSSA		VREFHI	V
V _{AI}	Analog input voltage, ADCIN0–ADCIN15	V _{SSA}		V _{CCA}	V

[†] VREFHI and VREFLO must be stable, within ±1/2 LSB of the required resolution, during the entire conversion time.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

	PARAMETER	DESCRIPT	DESCRIPTION		MAX	UNIT
			converting		5	
1004	Analog supply current	VCCA = 5.5 V	non-converting		2	m۵
		V _{CCA} = V _{REFHI} = 5.5 V	PLL or OSC power down		1	mA
I _{ref}	Input charge current, VREFHI or VREFLO	V _{CCA} = V _{CCD} = V _{REFHI} = 5	V _{CCA} = V _{CCD} = V _{REFHI} = 5.5 V, V _{REFLO} = 0 V		5	mA
_	Analog input capacitance	Typical capacitive load on	non-sampling		6	-
C _{ai} A		analog input pin	sampling	8	8	р⊢
Z _{AI}	Analog input source impedance	Analog input source impedance remain within specifications.	Analog input source impedance for conversions to remain within specifications.		9	kΩ
EDNL	Differential nonlinearity error	Difference between the actual value	Difference between the actual step width and the ideal value		1.5	LSB
E _{INL}	Integral nonlinearity error	Maximum deviation from the best straight line through the ADC transfer characteristics, excluding the quantization error			±1.5	LSB
^t d(PU)	Delay time, power-up to ADC valid	Time to stabilize analog stage	after power-up		10	μs

operating characteristics over recommended operating condition ranges[†]

⁺ Absolute resolution = 4.89 mV. At V_{REFHI} = 5 V and V_{REFLO} = 0 V, this is one LSB. As V_{REFHI} decreases, V_{REFLO} increases, or both, the LSB sizes decrease. Therefore, the absolute accuracy and differential/integral linearity errors in terms of LSBs increase.

The ADC module allows complete freedom in the design of the sources for the analog inputs. The period of the sample time is independent of the source impedance. The sample-and-hold period occurs in the first ADC clock after the ADCIMSTART bit or the ADCSOC bit of the ADC control register 1 (ADCTRL1, bits 13 and 0, respectively) is set to 1. The conversion then occurs during the next six ADC clock cycles. The digital result registers are updated on the next ADC clock cycle once the conversion is completed.

ADC input pin circuit

One of the most common A/D application errors is inappropriate source impedance. In practice, minimum source impedance should be used to limit the error as well as minimize the required sampling time; however, the source impedance must be smaller than Z_{AI} . A typical ADC input pin circuit is shown in Figure 48.







ADC timing requirements (see Figure 49)

		MIN	MAX	UNIT
^t c(AD)	Cycle time, ADC prescaled clock	1		μS
^t w(SHC)	Pulse duration, total sample/hold and conversion time (see Note 3)	6.1		μS
^t w(SH)	Pulse duration, sample and hold time	^t c(AD)		μS
t _{su(SH)}	Setup time, analog input stable before sample/hold start	0		ns
^t h(SH)	Hold time, analog input stable after sample/hold complete	0		ns
^t w(C)	Pulse duration, total conversion time	4.5t _C (AD)		μS
^t d(SOC-SH)	Delay time, start of conversion [†] to beginning of sample and hold	3t _{c(SYS)}		ns
td(EOC-FIFO)	Delay time, end of conversion to data loaded into result FIFO	3t _{c(SYS)}		ns

[†] Start of conversion is signaled by the ADCIMSTART bit or the ADCSOC bit set in software, the external start signal active (ADCSOC), or internal EVSOC signal active.

NOTE 3: The total sample/hold and conversion time is determined by the summation of $t_d(SOC-SH)$, $t_w(SH)$, $t_w(C)$, and $t_d(EOC-FIFO)$.



Figure 49. Analog-to-Digital Timing



flash EEPROM

switching characteristics over recommended operating conditions

PARAMETER	MIN	TYP	MAX	UNIT
Program-erase endurance	10K			Cycles
Program pulses per word [†]	1	10	150	Pulses
Erase pulses per array [†]	1	20	1000	Pulses
Flash-write pulses per array [†]	1	20	6000	Pulses

[†] These parameters are used in the flash programming algorithms. For a detailed description of the algorithms, see the *TMS320F20x/F24x DSP Embedded Flash Memory Technical Reference* (literature number SPRU282).

timing requirements over recommended operating conditions

		MIN	MAX	UNIT
^t d(BUSY)	Delay time, after mode deselect to stabilization [†]	10		μs
^t d(RD-VERIFY)	Delay time, verify read mode select to stabilization [†]	10		μs

[†] These parameters are used in the flash programming algorithms. For a detailed description of the algorithms, see the *TMS320F20x/F24x DSP Embedded Flash Memory Technical Reference* (literature number SPRU282).

programming operation

	PARAMETER	MIN	NOM	MAX	UNIT
^t w(PGM)	Pulse duration, programming algorithm †	95	100	105	μs
td(PGM-MODE)	Delay time, program mode select to stabilization [†]	10			μs

[†] These parameters are used in the flash programming algorithms. For a detailed description of the algorithms, see the *TMS320F20x/F24x DSP Embedded Flash Memory Technical Reference* (literature number SPRU282).

erase operation

	PARAMETER	MIN	NOM	MAX	UNIT
^t w(ERASE)	Pulse duration, erase algorithm †	6.65	7	7.35	ms
td(ERASE-MODE)	Delay time, erase mode select to stabilization [†]	10			μs

[†] These parameters are used in the flash programming algorithms. For a detailed description of the algorithms, see the *TMS320F20x/F24x DSP Embedded Flash Memory Technical Reference* (literature number SPRU282).

flash-write operation

	PARAMETER	MIN	NOM	MAX	UNIT
^t w(FLW)	Pulse duration, flash-write algorithm ^{†‡}	13.3	14	14.7	ms
^t d(FLW-MODE)	Delay time, flash-write mode select to stabilization ^{†‡}	10			μs

[†] These parameters are used in the flash programming algorithms. For a detailed description of the algorithms, see the *TMS320F20x/F24x DSP Embedded Flash Memory Technical Reference* (literature number SPRU282).

‡ Refer to the **recommended operating conditions** section for the flash programming operating temperature range when programming flash.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

register file compilation

Table 20 is a collection of all the programmable registers of the TMS320F240 (provided for a quick reference).

BIT 7 BIT 6 BIT 5 BIT 4 BIT 3 BIT 2 BIT 1 BIT 0 DATA MEMORY SPACE CPU STATUS REGISTERS CPU STATUS REGISTERS OV OVM 1 INTM DP(6) DP(7) DP(6) DP(6) DP(2) DP(1) DP(0) STI GLOBAL MEMORY AND CPU INTERRUPT REGISTERS OV OVM 1 1 MAR INTS MASK INTS FLAG INTS FLAG <th>ADDR</th> <th>BIT 15</th> <th>BIT 14</th> <th>BIT 13</th> <th>BIT 12</th> <th>BIT 11</th> <th>BIT 10</th> <th>BIT 9</th> <th>BIT 8</th> <th>REG</th>	ADDR	BIT 15	BIT 14	BIT 13	BIT 12	BIT 11	BIT 10	BIT 9	BIT 8	REG			
DATA MEMORY SPACE CPU STATUS REGISTERS CPU STATUS REGISTERS OV		BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0				
CPU STATUS REGISTERS ARP OV OV 1 INTM DP(8) STO DP(7) DP(6) DP(1) DP(3) DP(3) DP(3) DP(1) DP(0) STO ARB CNF TC SXM C 1 STO 1 1 1 XF 1 1 PM STO 00004h -			1		DATA MEN	ORY SPAC	E						
ARP OV OV OVM 1 INTM DP(8) STO DP(7) DP(6) DP(6) DP(7) DP(6) DP(7) DP(8) DP(7) DP(7) DP(8) DP(7) DP(7) DP(7) DP(8) DP(7) DP(7) DP(8) DP(7) DP(7) DP(8) DP(7) DP(7) DP(8) DP(7) DP(7) DP(7) DP(8) <					CPU STATU	IS REGISTERS							
DP(7) DP(6) DP(5) DP(4) DP(3) DP(2) DP(1) DP(0) STI ARB CNF TC SXM C 1 1 1 1 X F 1 PM STI 00004h - <t< td=""><td></td><td></td><td>ARP</td><td></td><td>OV</td><td>OVM</td><td>1</td><td>INTM</td><td>DP(8)</td><td>070</td></t<>			ARP		OV	OVM	1	INTM	DP(8)	070			
ARB CNF TC SXM C 1 1 1 M 1 1 1 XF 1 1 PM ST1 00004h — — — — — — — — — — — — — — — — — — — …		DP(7)	DP(6)	DP(5)	DP(4)	DP(3)	DP(2)	DP(1)	DP(0)	510			
1 1 XF 1 1 PM CT GLOBAL MEMORY AND CPU INTERRUPT REGISTERS O0004h -			ARB	-	CNF	TC	SXM	С	1	ST1			
$\begin{tabular}{ c c c c c } \hline \begin{tabular}{ c c c c c } \hline \begin{tabular}{ c c c c } \hline \begin{tabular}{ c c c } \hline \begin{tabular}{ c c c c } \hline \begin{tabular}{ c c c } \hline \begin{tabular}{ c c c c } \hline \hline \begin{tabular}{ c c c c c c } \hline \hline \begin{tabular}{ c c c c c } \hline \hline \begin{tabular}{ c c c c c c } \hline \hline \begin{tabular}{ c c c c c c c } \hline \hline \begin{tabular}{ c c c c c c c } \hline \hline \begin{tabular}{ c c c c c c c c c c c c c c c c c c c$		1	1	1	XF	1	1		PM	311			
00004h 00005h INTS MASK INTS MASK <td>-</td> <td></td> <td>1</td> <td>GLOBAL N</td> <td>IEMORY AND C</td> <td>PU INTERRUP</td> <td>T REGISTERS</td> <td>1</td> <td>I</td> <td></td>	-		1	GLOBAL N	IEMORY AND C	PU INTERRUP	T REGISTERS	1	I				
INTG MASK INTG MASK <td>00004h</td> <td>—</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>—</td> <td>—</td> <td>IMR</td>	00004h	—						—	—	IMR			
00005h - <td></td> <td>—</td> <td>—</td> <td>INT6 MASK</td> <td>INT5 MASK</td> <td>INT4 MASK</td> <td>INT3 MASK</td> <td>INT2 MASK</td> <td>INT1 MASK</td> <td></td>		—	—	INT6 MASK	INT5 MASK	INT4 MASK	INT3 MASK	INT2 MASK	INT1 MASK				
$\begin{tabular}{ c c c c c } \hline Contiguation Bits (7–0) & & & & & & & & $	00005h	0005h											
00006h - - - - - - - - INT INT <th< td=""><td>-</td><td></td><td></td><td>Glob</td><td>al Data Memory</td><td>Configuration B</td><td>Sits (7–0)</td><td></td><td></td><td>4</td></th<>	-			Glob	al Data Memory	Configuration B	Sits (7–0)			4			
- - INTS FLAG	00006h	—			-	—		-	—	IFR			
RESET1 RESET0 - <th< td=""><td></td><td>—</td><td>—</td><td>INT6 FLAG</td><td>INT5 FLAG</td><td>INT4 FLAG</td><td>INT3 FLAG</td><td>INT2 FLAG</td><td>INT1 FLAG</td><td>_</td></th<>		—	—	INT6 FLAG	INT5 FLAG	INT4 FLAG	INT3 FLAG	INT2 FLAG	INT1 FLAG	_			
RESE11 RESE10 - <th< td=""><td></td><td>550574</td><td></td><td>SYS</td><td>STEM CONFIGU</td><td>JRATION REGI</td><td>STERS</td><td>1</td><td>i</td><td>_</td></th<>		550574		SYS	STEM CONFIGU	JRATION REGI	STERS	1	i	_			
CLRSRC1 CLRSRC0 — … <	07018h	RESEI1	RESETO	-	—	—	—	—	—	SYSCR			
Reserved PORST - - ILLADR - SWRST WDRST - SYSSI 0701Ah - HPO - VCCAOR - - VECRD 0701Bh - Reserved - VECRD VECRD VECRD 0701Bh - 0	070105	CLKSKUI	Reserved										
PORST Image: Construction of the served of the	070190	DODST	1	1		served	CW/DCT	WDDST	1	-			
Image: Constraint of the	0701Ah	-		HPO			300631	WDR31		SYSSR			
Reserved Reserved 0001Dh 0 <td>0701Bh</td> <td></td> <td></td> <td>1110</td> <td></td> <td>VOUNOIN</td> <td></td> <td></td> <td>VEORD</td> <td>-</td>	0701Bh			1110		VOUNOIN			VEORD	-			
Or01Dh O <td>to</td> <td></td> <td></td> <td></td> <td>Re</td> <td>served</td> <td></td> <td></td> <td></td> <td></td>	to				Re	served							
0 0	0701Dh												
$\begin{tabular}{ c c c c c c c } \hline D7 & D6 & D5 & D4 & D3 & D2 & D1 & D0 \\ \hline $Reserved$ \\ \hline $Reserved$ \\ \hline $V020h$ & $VD/RTI CONTROL REGISTERS$ \\ \hline $VD/RTI CONTROL REGISTERS $	0701Eh	0	0	0	0	0	0	0	0	SYSIVR			
Reserved WD/RTI CONTROL REGISTERS O7020h Reserved 07020h Reserved 07021h D7 D6 D5 D4 D3 D2 D1 D0 RTICN 07022h Reserved 07022h Reserved 07024h Reserved 07024h Reserved WDCN 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDCN 07024h Reserved WDCN 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDCN 07026h Reserved 07027h RTI FLAG RTI ENA — — RTIPS2 RTIPS1 RTIPS0 RTICR 07028h WD FLAG WDDHX WDCHK2 WDCHK0 WDPS2 WDPS1 WDPS0 O702A <th< td=""><td></td><td>D7</td><td>D6</td><td>D5</td><td>D4</td><td>D3</td><td>D2</td><td>D1</td><td>D0</td><td>_</td></th<>		D7	D6	D5	D4	D3	D2	D1	D0	_			
WD/K IT CONTROL REGISTERS 07020h Reserved 07021h D7 D6 D5 D4 D3 D2 D1 D0 RTICN 07021h D7 D6 D5 D4 D3 D2 D1 D0 RTICN 07021h D7 D6 D5 D4 D3 D2 D1 D0 WDCN 07022h Reserved 07024h Centrol D5 D4 D3 D2 D1 D0 WDCN 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDKR 07026h Crospan="5">Centrol Reserved WDKR Colspan="5">Centrol Reserved 07027h RTI FLAG RTI ENA — — RTICR RTICR RTICR 07028h WD FLAG WDDIS WDCHK2 WDCHK1 WDCHK0 WDPS2 WDPS1 WDRS0 PLL CLOCK CONTROL REGISTERS Centrol </td <td>0701Fh</td> <td></td> <td></td> <td></td> <td>Re</td> <td>served</td> <td></td> <td></td> <td></td> <td>_</td>	0701Fh				Re	served				_			
Orozon Reserved O7021h D7 D6 D5 D4 D3 D2 D1 D0 RTICN O7022h Reserved O7023h D7 D6 D5 D4 D3 D2 D1 D0 MDCN O7024h Reserved WDCN O7024h Reserved WDCN O7025h D7 D6 D5 D4 D3 D2 D1 D0 WDCN O7026h Reserved WDCN O7027h RTI FLAG RTI ENA — — RTI RIS2 RTIPS1 RTIPS0 RTICR O7028h WD FLAG WDCHK2 WDCHK1 WDCHK0 WDPS2 WDPS1 WDPS0 WD72M Reserved O7028h CLKMD(1) CLKMD(1) PLL CLOCK CONTROL REGISTERS O7028h CLKMD(1) CLKMD(0) PLLOCK(0) PLLPM(1)	07000				WD/RTICONT		RS			-			
07021n D7 D6 D5 D4 D3 D2 D1 D0 RTICK 07022h	07020n	D7	DC	Dr	Re:	servea	Do	D 4	D 0	DTIONIT			
Or022h Image: Constraint of the served Reserved WDCN 07023h D7 D6 D5 D4 D3 D2 D1 D0 WDCN 07024h Image: Constraint of the served Reserved Image: Constraint of the served WDCN 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDKE 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDKE 07026h Image: Constraint of the served RTIFS2 RTIPS1 RTIPS0 RTICR 07028h Image: Constraint of the served Image: Constraint of the	07021h	D7	D6	D5	D4	D3	D2	D1	D0	RHCNI			
D7 D6 D5 D4 D5 D2 D1 D0 WDCK 07024h Reserved 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDCK 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDKE 07026h Reserved 07027h RTI FLAG RTI ENA — — RTIPS2 RTIPS1 RTIPS0 RTICR 07028h REserved 07029h WD FLAG WDCHK2 WDCHK1 WDCHK0 WDPS2 WDPS0 WDCR 07028h CLKMD(1) CLKMD(0) PLL CLOCK CONTROL REGISTERS 07028h CLKMD(1) CLKMD(0) PLLOCK(1) PLLOCK(0) PLLPM(0) ACLKENA PLLPS CKCR 07020h Reserved	070220	D7	De	D5			D2	D1	DO				
Or02411 Image: Constraint of the served Reserved WDKE 07025h D7 D6 D5 D4 D3 D2 D1 D0 WDKE 07026h Image: Constraint of the served Reserved RTIPS2 RTIPS1 RTIPS0 RTICR 07028h Image: Constraint of the served Image: Constraint of the served <td< td=""><td>070230</td><td>DI</td><td>Do</td><td>D5</td><td>D4 Po</td><td>Do</td><td>DZ</td><td>DI</td><td>D0</td><td>WDCNI</td></td<>	070230	DI	Do	D5	D4 Po	Do	DZ	DI	D0	WDCNI			
07025h D7 D6 D5 D4 D3 D2 D1 D0 WDRE 07026h Reserved 07027h RTI FLAG RTI ENA — — RTIPS2 RTIPS1 RTIPS0 RTICR 07028h Reserved 07029h WD FLAG WDCHK2 WDCHK1 WDCHK0 WDPS2 WDPS1 WDPS0 WDCR PLL CLOCK CONTROL REGISTERS 07028h CLKMD(1) CLKMD(0) PLLOCK(1) PLLOK(0) PLLPM(0) ACLKENA PLLPS CKCR	07024n	DZ	DC	DE		Served	Da	D1	Do				
Orderin Reserved RTIPS2 RTIPS1 RTIPS0 RTICR 07027h RTI FLAG RTI ENA — — — RTIPS2 RTIPS1 RTIPS0 RTICR 07028h RTIAG WDDIS WDCHK2 WDCHK1 WDCHK0 WDPS2 WDPS1 WDPS0 WDCR Reserved 07028h CLKMD(1) CLKMD(0) PLLOCK(1) PLLOCK(0) PLLPM(1) PLLPS CKCR	0702511	וט	סים	60	D4	LU3	UZ	וט	DU				
OTOLINI INTERC	070201	RTI FI AG	RTI FNA	_			RTIPS2	RTIPS1	RTIPSO	RTICP			
OTO201h WD FLAG WDDIS WDCHK2 WDCHK1 WDCHK0 WDPS2 WDPS1 WDPS0 PLL CLOCK CONTROL REGISTERS 07028h CLKMD(1) CLKMD(0) PLLOCK(0) PLLPS CKCR0 07028h CLKMD(1) CLKMD(0) PLLOCK(1) PLLPS CKCR0	07028h	NTT LAG			 	served	IVER OZ	INTE OT	INTE OU				
VIDENT VIDENT<	0702011 07029h	WD FLAG	WDDIS	WDCHK2			WDPS2	WDPS1	WDPS0	WDCR			
0702Ah	0702011												
0702Bh CLKMD(1) CLKMD(0) PLLOCK(1) PLLOCK(0) PLLPM(1) PLLPM(0) ACLKENA PLLPS CKCRU	0702Ab				Re: 01000000	served				-			
	0702Bh	CLKMD(1)	CLKMD(0)	PLLOCK(1)	PLLOCK(0)	PLLPM(1)	PLLPM(0)	ACLKENA	PLI PS	CKCR0			
V/VZGITT Reserved	0702Ch		32		Re	served	(3)		0				

Table 20. Register File Compilation



register file compilation (continued)

ADDR	BIT 15	BIT 14	BIT 13	BIT 12	BIT 11	BIT 10	BIT 9	BIT 8	REG
	BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0	
			PLL CL	OCK CONTROL	REGISTERS (C	ONTINUED)			
0702Dh	CKINF(3)	CKINF(2)	CKINF(1)	CKINF(0)	PLLDIV(2)	PLLFB(2)	PLLFB(1)	PLLFB(0)	CKCR1
0702Eh				De	o o m co d				
το 07031h				Re	served				
			A-1	o-D MODULE C	ONTROL REGI	STERS			
07032h	SUSPEND- SOFT	SUSPEND- FREE	ADCIM- START	ADC2EN	ADC1EN	ADCCON- RUN	ADCINTEN	ADCINTFLAG	ADCTRL1
	ADCEOC ADC2CHSEL ADC1CHSEL ADCSOC								
07033h		1	1	Re	served	1	•	1	_
07034h	_	—	—	—	—	ADCEVSOC	ADCEXTSOC	—	ADCTRI 2
0100	ADCF	FIFO2	—	ADCF	FIFO1		ADCPSCALE		
07035h				Re	served	T		1	_
07036h	D9	D8	D7	D6	D5	D4	D3	D2	ADCFIF01
	D1	D0	0	0	0	0	0	0	_
07037h				Re	served				
07038h	D9	D8	D7	D6	D5	D4	D3	D2	ADCFIFO2
07000	D1	D0	0	0	0	0	0	0	_
07039h to				Re	served				
0703Fh									
		SERIAL	PERIPHERAL II	NTERFACE (SPI) CONFIGURAT	ION CONTROL F	REGISTERS	1	
07040h	SPI SW RESET	CLOCK POLARITY	—	_	_	SPI CHAR2	SPI CHAR1	SPI CHAR0	SPICCR
07041h	_	_	—	OVERRUN INT ENA	CLOCK PHASE	MASTER/ SLAVE	TALK	SPI INT ENA	SPICTL
07042h	RECEIVER OVERRUN	SPI INT FLAG	—	—	—	_	_	—	SPISTS
07043h		1	1	Re	served	1	T	ſ	_
07044h	—	SPI BIT RATE 6	SPI BIT RATE 5	SPI BIT RATE 4	SPI BIT RATE 3	SPI BIT RATE 2	SPI BIT RATE 1	SPI BIT RATE 0	SPIBRR
07045h		I	I	Re	served	T	T	Γ	_
07046h	ERCVD7	ERCVD6	ERCVD5	ERCVD4	ERCVD3	ERCVD2	ERCVD1	ERCVD0	SPIEMU
07047h	RCVD7	RCVD6	RCVD5	RCVD4	RCVD3	RCVD2	RCVD1	RCVD0	SPIBUF
07048h				Re	served	1			
07049h	SDAT7	SDAT6	SDAT5	SDAT4	SDAT3	SDAT2	SDAT1	SDAT0	SPIDAT
0704Ah to 0704Ch	Reserved								
0704Dh	SPISTE DATA IN	SPISTE DATA OUT	SPISTE FUNCTION	SPISTE DATA DIR	SPICLK DATA IN	SPICLK DATA OUT	SPICLK FUNCTION	SPICLK DATA DIR	SPIPC1
0704Eh	SPISIMO DATA IN	SPISIMO DATA OUT	SPISIMO FUNCTION	SPISIMO DATA DIR	SPISOMI DATA IN	SPISOMI DATA OUT	SPISOMI FUNCTION	SPISOMI DATA DIR	SPIPC2
0704Fh	—	SPI PRIORITY	SPI ESPEN	—	_		_	_	SPIPRI



register file compilation (continued)

ADDR	BIT 15	BIT 14	BIT 13	BIT 12	BIT 11	BIT 10	BIT 9	BIT 8	REG		
	BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0			
		SERIAL COM	IMUNICATIONS	INTERFACE (S	SCI) CONFIGUR	RATION CONTR	OL REGISTERS	6			
07050h	STOP BITS	EVEN/ODD PARITY	PARITY ENABLE	SCI ENA	ADDR/IDLE MODE	SCI CHAR2	SCI CHAR1	SCI CHAR0	SCICCR		
07051h	_	RX ERR INT ENA	SW RESET	CLOCK ENA	TXWAKE	SLEEP	TXENA	RXENA	SCICTL1		
07052h	BAUD15 (MSB)	BAUD14	BAUD13	BAUD12	BAUD11	BAUD10	BAUD9	BAUD8	SCIHBAUD		
07053h	BAUD7	BAUD6	BAUD5	BAUD4	BAUD3	BAUD2	BAUD1	BAUD0 (LSB)	SCILBAUD		
07054h	TXRDY	TX EMPTY	—	—	—	—	RX/BK INT ENA	TX INT ENA	SCICTL2		
07055h	RX ERROR	RXRDY	BRKDT	FE	OE	PE	RXWAKE	—	SCIRXST		
07056h	ERXDT7	ERXDT6	ERXDT5	ERXDT4	ERXDT3	ERXDT2	ERXDT1	ERXDT0	SCIRXEMU		
07057h	RXDT7	RXDT6	RXDT5	RXDT4	RXDT3	RXDT2	RXDT1	RXDT0	SCIRXBUF		
07058h				Re	served				7		
07059h	TXDT7	TXDT6	TXDT5	TXDT4	TXDT3	TXDT2	TXDT1	TXDT0	SCITXBUF		
0705Ah to 0705Dh	h Reserved										
0705Eh	SCITXD DATA IN	SCITXD DATA OUT	SCITXD FUNCTION	SCITXD DATA DIR	SCIRXD DATA IN	SCIRXD DATA OUT	SCIRXD FUNCTION	SCIRXD DATA DIR	SCIPC2		
0705Fh	_	SCITX PRIORITY	SCIRX PRIORITY	SCI ESPEN	_	_	_	—	SCIPRI		
07060h to 0706Fh				Re	served						
			EXTER	NAL INTERRUP	T CONTROL R	EGISTERS			-		
070701	XINT1 FLAG	_	_	_	_	_	_	_			
07070h	—	XINT1 PIN DATA	0	—	—	XINT1 POLARITY	XINT1 PRIORITY	XINT1 ENA	XINTICR		
07071h				Re	served						
070725	NMI FLAG	—	—	—	—	—	—	—			
070720	_	NMI PIN DATA	1	_	—	NMI POLARITY	_	—	NIVIICK		
07073h to 07077h	3h Reserved 7h										
0707 <u>9</u> 5	XINT2 FLAG	_	_	_	_	_	_	_			
070701	_	XINT2 PIN DATA	-	XINT2 DATA DIR	XINT2 DATA OUT	XINT2 POLARITY	XINT2 PRIORITY	XINT2 ENA			
07079h	Reserved										



register file compilation (continued)

ADDR	BIT 15	BIT 14	BIT 13	BIT 12	BIT 11	BIT 10	BIT 9	BIT 8	REG	
	BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0		
		E	XTERNAL INT	ERRUPT CONT	ROL REGISTE	RS (CONTINUE	D)			
	XINT3 FLAG	—	—	—	—	—	—	-		
0707Ah	_	XINT3 PIN DATA	—	XINT3 DATA DIR	XINT3 DATA OUT	XINT3 POLARITY	XINT3 PRIORITY	XINT3 ENA	XINT3CR	
0707Bh to 0708Fh				Res	erved			I		
			Di	GITAL I/O CON	TROL REGIST	ERS			-	
	CRA.15	CRA.14	CRA.13	CRA.12	CRA.11	CRA.10	CRA.9	CRA.8		
07090h	_	_	_	_	CRA.3	CRA.2	CRA.1	CRA.0	OCRA	
07091h Reserved										
070006	—	—	—	—	—	—	—	—		
07092h	CRB.7	CRB.6	CRB.5	CRB.4	CRB.3	CRB.2	CRB.1	CRB.0	UCRB	
07093h to				Res	erved					
07097h		i	i	i	40010	40DID		4000		
07098h		_	_	_	A3DIR	A2DIR	A1DIR	AUDIR	PADATDIR	
07000		_	_		IUPA3	IOPAZ	IOPAT	IOPAU	_	
07099h	BZDID	DEDID	DEDID	Res	erved	DODID		PADID	-	
0709Ah								BUDIR	PBDATDIR	
0700Dh	ЮРВЛ	IOP B0	IOPBo	IUPB4	IUPB3	IOPBZ	ЮРВТ	ЮРВО	-	
070960	CZDIR	CEDIR				CODIR		CODIR		
0709Ch									PCDATDIR	
070006	IOP C7	IOF CO	10F 03	10F 04	10F 03	IOF 02	IOFCI	IOFCU	-	
to 073FFh				Res	erved					
		GENER	AL-PURPOSE (GP) TIMER CO	NFIGURATION	CONTROL RE	GISTERS			
	T3STAT	T2STAT	T1STAT	тзтс	DADC	T2TC	ADC	T1TOADC(1)		
07400h	T1TOADC(0)	TCOMPOE	T3I	PIN	T2	PIN	Т	1PIN	GPTCON	
	D15	D14	D13	D12	D11	D10	D9	D8	1	
07401h	D7	D6	D5	D4	D3	D2	D1	D0	T1CNT	
	D15	D14	D13	D12	D11	D10	D9	D8		
07402h	D7	D6	D5	D4	D3	D2	D1	D0	TICMPR	
	D15	D14	D13	D12	D11	D10	D9	D8		
07403h	D7	D6	D5	D4	D3	D2	D1	D0	TIPR	
074046	FREE	SOFT	TMODE2	TMODE1	TMODE0	TPS2	TPS1	TPS0	T1CON	
07404N	TSWT1	TENABLE	TCLKS1	TCLKS0	TCLD1	TCLD0	TECMPR	SELT1PR		
074054	D15	D14	D13	D12	D11	D10	D9	D8	TOONIT	
074050	D7	D6	D5	D4	D3	D2	D1	D0	T2CNT	
074065	D15	D14	D13	D12	D11	D10	D9	D8	TOCMOD	
074001	D7	D6	D5	D4	D3	D2	D1	D0		



register file compilation (continued)

ADDR	BIT 15	BIT 14	BIT 13	BIT 12	BIT 11	BIT 10	BIT 9	BIT 8	REG					
	BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0						
		GENERAL-PU	RPOSE (GP) TI	MER CONFIGU	RATION CONT	ROL REGISTER	RS (CONTINUE	D)						
07407	D15	D14	D13	D12	D11	D10	D9	D8	TOPP					
07407h	D7	D6	D5	D4	D3	D2	D1	D0	12PR					
074005	FREE	SOFT	TMODE2	TMODE1	TMODE0	TPS2	TPS1	TPS0	TOCON					
0740011	TSWT1	TENABLE	TCLKS1	TCLKS0	TCLD1	TCLD0	TECMPR	SELT1PR	1200N					
074006	D15	D14	D13	D12	D11	D10	D9	D8	TOONT					
0740911	D7	D6	D5	D4	D3	D2	D1	D0	TSCINT					
074046	D15	D14	D13	D12	D11	D10	D9	D8	TOMOR					
0740411	D7	D6	D5	D4	D3	D2	D1	D0	ISCINPR					
0740Ph	D15	D14	D13	D12	D11	D10	D9	D8	7200					
074060	D7	D6	D5	D4	D3	D2	D1	D0	ISPR					
074006	FREE	SOFT	TMODE2	TMODE1	TMODE0	TPS2	TPS1	TPS0	TROOM					
0740Ch	TSWT1	TENABLE	TCLKS1	TCLKS0	TCLD1	TCLD0	TECMPR	SELT1PR	13CON					
0740Dh														
to 07410b				Re	served									
0741011	FULL AND SIMPLE COMPARE UNIT REGISTERS													
	CENABLE	CLD1					FCOMPOF	SCOMPOE	-					
07411h	SELTMR	SCI D1	SCLDO			SELCMP3	SELCMP2	SELCMP1	COMCON					
07/12h	OLLIMIN	GOLDI	GOLDU	Bo	served	SELCIVII 5		SELCIVII 1	-					
0741211	SVRDIR	D2	D1				CMP5ACT1	CMP5ACT0	-					
07413h	CMP4ACT1		CMP3ACT1		CMP2ACT1	CMP2ACT0	CMP1ACT1	CMP1ACT0	ACTR					
								_	-					
07414h			SCMP3-	SCMP3-	SCMP2-	SCMP2-	SCMP1-	SCMP1-	SACTR					
	—	—	ACT1	ACT0	ACT1	ACT0	ACT1	ACT0	0,10111					
	DBT7	DBT6	DBT5	DBT4	DBT3	DBT2	DBT1	DBT0						
07415h	EDBT3	EDBT2	EDBT1	DBTPS1	DBTPS0	_	_	_	DBICON					
07416h				Re	served									
	D15	D14	D13	D12	D11	D10	D9	D8						
07417h	D7	D6	D5	D4	D3	D2	D1	D0	CMPR1					
	D15	D14	D13	D12	D11	D10	D9	D8						
07418h	D7	D6	D5	D4	D3	D2	D1	D0	CMPR2					
	D15	D14	D13	D12	D11	D10	D9	D8						
07419h	D7	D6	D5	D4	D3	D2	D1	D0	CMPR3					
074441	D15	D14	D13	D12	D11	D10	D9	D8						
0741Ah	D7	D6	D5	D4	D3	D2	D1	D0	SCMPR1					
	D15	D14	D13	D12	D11	D10	D9	D8						
0741Bh	D7	D6	D5	D4	D3	D2	D1	D0	SCMPR2					
074/01	D15	D14	D13	D12	D11	D10	D9	D8						
0741Ch	D7	D6	D5	D4	D3	D2	D1	D0	SCMPR3					
0741Dh to 0741Fh				Re	served]					



register file compilation (continued)

ADDR	BIT 15	BIT 14	BIT 13	BIT 12	BIT 11	BIT 10	BIT 9	BIT 8	REG		
	BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0			
				CAPTURE U	NIT REGISTER	s					
074006	CAPRES	CAPO	QEPN	CAP3EN	CAP4EN	CAP34TSEL	CAP12TSEL	CAP4TOADC	CARCON		
074200	CAP1	EDGE	CAP2	EDGE	CAP3	EDGE	CAP	4EDGE	CAPCON		
07421h				Re	served						
074226	CAP4	IFIFO	CAP3	SFIFO	CAP	2FIFO	CAF	1FIFO	CAREIEO		
0742211	CAPFIFO15	CAPFIFO14	CAPFIFO13	CAPFIFO12	CAPFIFO11	CAPFIFO10	CAPFIFO9	CAPFIF08	CAFTILO		
074226	D15	D14	D13	D12	D11	D10	D9	D8			
0742311	D7	D6	D5	D4	D3	D2	D1	D0	CAFILIO		
074246	D15	D14	D13	D12	D11	D10	D9	D8	CAROFIED		
074240	D7	D6	D5	D4	D3	D2	D1	D0	CAFZFIFU		
07425h	D15	D14	D13	D12	D11	D10	D9	D8	CARSEIEO		
0742311	D7	D6	D5	D4	D3	D2	D1	D0	CAFSIIIO		
07426h	D15	D14	D13	D12	D11	D10	D9	D8	CARAFIEO		
0742011	D7	D6	D5	D4	D3	D2	D1	D0	CAF4FIFU		
07427h				_							
to 0742Bh				Re	served						
or izbii	EVENT MANAGER (EV) INTERRUPT CONTROL REGISTERS										
				- ()		T10FINT	T1UFINT	T1CINT	_		
074006	_	_	_	_	_	ENA	ENA	ENA			
0742011	T1PINT	SCMP3INT	SCMP2INT	SCMP1INT	CMP3INT	CMP2INT	CMP1INT	PDPINT	EVIIVIKA		
	ENA	ENA	ENA	ENA	ENA	ENA	ENA	ENA	_		
074001			—	—	—	—	—				
0742Dh	T3OFINT ENA	T3UFINT ENA	T3CINT FNA	T3PINT FNA	T2OFINT ENA	T2UFINT ENA	T2CINT FNA	T2PINT ENA	EVIMRB		
				_							
0742Eh					CAP4INT	CAP3INT	CAP2INT	CAP1INT	EVIMRC		
		—	—	—	ENA	ENA	ENA	ENA			
		_	_	_	_	T10FINT	T1UFINT	T1CINT			
0742Fh						FLAG	FLAG	FLAG	EVIFRA		
	T1PINT FLAG	SCMP3INT FLAG	SCMP2INT FLAG	SCMP1INT FLAG	CMP3INT FLAG	CMP2INT FLAG	CMP1INT FLAG	PDPINT FLAG			
		_	_	_	_	_	_	_			
07430h	T3OFINT	T3UFINT	T3CINT	T3PINT	T2OFINT	T2UFINT	T2CINT	T2PINT	EVIFRB		
	FLAG	FLAG	FLAG	FLAG	FLAG	FLAG	FLAG	FLAG			
	-	—	—	—	—	—	—	_			
07431h	_	—	—	—	CAP4INT FLAG	CAP3INT FLAG	CAP2INT FLAG	CAP1INT FLAG	EVIFRC		
	0	0	0	0	0	0	0	0			
07432h	0	0	D5	D4	D3	D2	D1	D0	EVIVRA		
	0	0	0	0	0	0	0	0	_		
07433h	0	0	D5	D4	D3	D2	D1	D0	EVIVRB		
	0	0	0	0	0	0	0	0	1		
07434h	0	0	D5	D4	D3	D2	D1	D0	EVIVRC		
07435h to 0743Fh	Reserved										



register file compilation (continued)

ADDR	BIT 15	BIT 14	BIT 13	BIT 12	BIT 11	BIT 10	BIT 9	BIT 8	REG	
	BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0		
I/O MEMORY SPACE										
	FLASH CONTROL MODE REGISTER [†]									
055051	—	—	—	—	—	_	—	—	FOMP	
UFFUFN		—		—	—		—		FCIVIR	
WAIT-STATE GENERATOR CONTROL REGISTER										
	_	—	-	—	—	-	—	_	WECH	
UFFFFII	_	—	_	—	AVIS	ISWS	DSWS	PSWS	WSGR	

Table 20. Register File Compilation (Continued)

[†] See the **flash control mode register** section.



SPRS042E - OCTOBER 1996 - REVISED NOVEMBER 2002

MECHANICAL DATA

PLASTIC QUAD FLATPACK

PQ (S-PQFP-G***) 100 LEAD SHOWN



- NOTES: A. All linear dimensions are in inches (millimeters).
 - B. This drawing is subject to change without notice.
 - C. Falls within JEDEC MO-069



PACKAGING INFORMATION

Orderable Device	Status ⁽¹⁾	Package Type	Package Drawing	Pins	Package Qty	e Eco Plan ⁽²⁾	Lead/Ball Finish	MSL Peak Temp ⁽³⁾
TMS320F240PQ	NRND	BQFP	PQ	132	36	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-4-260C-72HR
TMS320F240PQA	NRND	BQFP	PQ	132	36	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-4-260C-72HR
TMS320F240PQG4	NRND	BQFP	PQ	132	36	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-4-260C-72HR
TMS320F240PQS	NRND	BQFP	PQ	132	36	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-4-260C-72HR
TMS32F240PQAG4	NRND	BQFP	PQ	132	36	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-4-260C-72HR

⁽¹⁾ The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details. **TBD**: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

⁽³⁾ MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

Important Information and Disclaimer:The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments

Post Office Box 655303 Dallas, Texas 75265

Copyright © 2006, Texas Instruments Incorporated