




ACCESSORIES (SUPPLIED WITH KIT)



| Table | | | | |
|----------------------------|---------------------------|-------------|-------------------------|--------------------------------|
| Diode Turn on Voltage (mv) | Peak AC Input Voltage (v) | Input C(pF) | Bandwidth | DC Isolation V incl. Peak AC V |
| 200 | 50 | 5 | 100kHz to 800MHz | 300 |

FEATURES:

- Model 5815A is a miniature RF Detector Probe intended for use with a wide range of oscilloscopes.
- This probe is very useful in measuring RF signals up to 800 MHz.
- Provides an output of 1 VDC for an input of 1 VRMS sinewave

RATINGS: CAT I, 300 V

ORDERING INFORMATION: Model 5815A

All dimensions are in inches. Tolerances (except noted): .xx = $\pm .02$ " (.51 mm), .xxx = $\pm .005$ " (.127 mm).
All specifications are to the latest revisions. Specifications are subject to change without notice.
Registered trademarks are the property of their respective companies. Made in USA