

# SAW Components

Data Sheet B7824







Dimensions in mm, approx. weight 0,01 g

### **Pin configuration**

2	Input
1	Input - ground
3	Output
4	Output - ground



Туре	Ordering code	Marking and Package according to	Packing according to
B7824	B39202-B7824-A510	C61157-A7-A63	F61074-V8154-Z000

Electrostatic Sensitive Device (ESD)

# **Maximum ratings**

Operating temperature range	Т	- 40/+ 85	°C	
Storage temperature range	T <sub>stg</sub>	- 40/+ 85	°C	
DC voltage	V <sub>DC</sub>	5	V	
ESD voltage	V <sub>ESD</sub>	50	V	
Input power at	-			
GSM850, GSM900	P <sub>IN</sub>	15	dBm	peak power of GSM signal,
GSM1800, GSM1900	P <sub>IN</sub>	12	dBm	duty cycle 4:8
Tx bands				



SAW Component	ts						B7824
Low-Loss Filter f	1960,00 MHz						
Data Sheet		=N					
Characteristics							
Operating temperatu		Т	= +25 +	2°C			
Terminating source	•		= 50 Ω				
Terminating load im	pedance:	$Z_{L}$	= 50 Ω				
				min.	typ.	max.	
Center frequency			f <sub>c</sub>		1960,0		MHz
Maximum insertior	attenuation		$\alpha_{max}$				
	1930,01990	,0 MHz		_	2,7	3,3	dB
Amplitude ripple (p	p-p)		Δα				
	1930,01990	,0 MHz		—	1,3	1,9	dB
Input VSWR							
	1930,01990	,0 MHz		—	1,85	2,0	
Output VSWR							
	1930,01990	,0 MHz		_	1,85	2,0	
Attenuation			α				
	10,01500			19,0	21,0	—	dB
	1500,01800			23,0	27,0	—	dB
	1800,01910			13,0	22,0	—	dB
	2010,02070			11,0	18,0	—	dB
	2070,02800			21,0	23,0	—	dB
	2800,06000	,0 MHz		16,0	18,0	—	dB



SAW Component	S							B7824
Low-Loss Filter f	1960,00 MHz							
Data Sheet			SM					
Characteristics								
Operating temperatu			Т	= -10 to	o +80° C			
Terminating source i	•	:		= 50 Ω				
Terminating load imp	bedance:		$Z_{L}$	= 50 Ω				
					min.	typ.	max.	
Center frequency				f <sub>c</sub>	—	1960,0	—	MHz
Maximum insertion	attenuati	on		$\alpha_{max}$				
	1930,0	1990,0	MHz	ar	—	3,2	4,0	dB
Amplitude ripple (p	-p)			Δα				
	1930,0	1990,0	MHz		_	1,7	2,5	dB
Input VSWR								
	1930,0	1990,0	MHz		—	1,85	2,0	
Output VSWR								
	1930,0	1990,0	MHz		—	1,85	2,0	
Attenuation				α				
	10,0	1500,0	MHz		19,0	21,0		dB
	1500,0		MHz		23,0	27,0		dB
		1910,0	MHz		8,0	15,0	_	dB
		2070,0	MHz		8,0	14,0		dB
		2800,0	MHz		21,0	23,0	_	dB
	2800,0	6000,0	MHz		16,0	18,0	—	dB



SAW Components								B7824
Low-Loss Filter for Mobile Communication								00 MHz
Data Sheet								
Characteristics								
Operating temperature r Terminating source imperation Terminating load impeda	dance	:	$Z_{S}$	= -30 to = 50 Ω = 50 Ω	o +85°C			
					min.	typ.	max.	
Center frequency				f <sub>c</sub>	_	1960,0	—	MHz
Maximum insertion atte		<b>on</b> 1990,0	MHz	$\alpha_{max}$	_	3,3	4,3	dB
Amplitude ripple (p-p) 19	930,0	1990,0	MHz	Δα	_	1,7	2,7	dB
Input VSWR 1	930,0	1990,0	MHz		_	1,85	2,0	
Output VSWR	930,0	1990,0	MHz		_	1,85	2,0	
Attenuation	10.0	4500.0		α	10.0	24.0		
1	10,0 500,0	1500,0 1800,0	MHz MHz		19,0 23,0	21,0 27,0	_	dB dB
		1910,0	MHz		23,0 7,5	14,0	_	dB
		2070,0	MHz		7,0	12,0	—	dB
20	070,0	2800,0	MHz		21,0	23,0	_	dB
28	800,0	6000,0	MHz		16,0	18,0	_	dB





Transfer Function(25°C spec)



# Transfer function (wideband)



Jul 03, 2002 6



**Reflection functions** 





SAW Components		B7824
Low-Loss Filter for Mobile Comm	nunication	1960,00 MHz
Data Sheet	SMD	

#### Published by EPCOS AG

# Surface Acoustic Wave Components Division, SAW MC WT P.O. Box 80 17 09, 81617 Munich, GERMANY

© EPCOS AG 2002. Reproduction, publication and dissemination of this brochure and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.

This brochure replaces the previous edition.

For questions on technology, prices and delivery please contact the Sales Offices of EPCOS AG or the international Representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our Sales Offices.