

SAW Filters for Mobile Communications

Series/Type: B7835

The following products presented in this data sheet are being withdrawn.

Ordering Code	Substitute Product	Date of Withdrawal	Deadline Last Orders	Last Shipments
B39212B7835C710	B39212B9408K610	2010-01-15	2010-04-30	2010-07-30

For further information please contact your nearest EPCOS sales office, which will also support you in selecting a suitable substitute. The addresses of our worldwide sales network are presented at www.epcos.com/sales.

SAW Components	B7835
Low-Loss Filter for Mobile Communication	2140,0 MHz
Data Sheet	
	Chip sized SAW package QCS5C
Features	
 Low-loss RF filter for mobile telephone W-CDMA system, receive path Low amplitude ripple Usable passband 60 MHz Unbalanced to balanced operation Impedance transformation from 50Ω to 200Ω Package for Surface Mounted Technology (SMT) 	0.735 0.735 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38 0.38

Chip Sized SAW Package (CSSP)

Terminals

Gold-plated Ni



Dimensions in mm, approx. weight 0,012 g

Pin configuration

- 1 Input, unbalanced
- 3, 4 Output, balanced
- 2, 5 To be grounded



Туре	Ordering code	Marking and Package according to	Packing according to
B7835	B39212-B7835-C710	C61157-A7-A111	F61074-V8151-Z000

Electrostatic Sensitive Device (ESD)

Maximum ratings

Operating temperature range	Т	- 20/+ 85	°C	
Storage temperature range	T_{stg}	- 40/+ 85	°C	
DC voltage	V _{DC}	5	V	
ESD voltage	V_{ESD}^{*}	50	V	Machine Model, 10 pulses
Source power	Ps	10	dBm	

* - acc. to JESD22-A115A (Machine Model), 10 negative & 10 positive pulses

☆TDK

SAW Components							B7835
Low-Loss Filter for Mobile	Commun	icatio	n			2140,0 MHz	
Data Sheet		=n					
Characteristics							
Operating temperature range: Terminating source impedance: Terminating load impedance:	Z_{S}	= +25°C = 50 Ω = 200 Ω	; (balanced)	22 nH			
				min.	typ.	max.	
Center frequency			f _C	_	2140,0	—	MHz
Movimum incontion attenuation	-						
Maximum insertion attenuation	n 2170,0	N/⊔→	α_{max}		2,6	3,0	dB
2110,0	2170,0				2,0	3,0	UD
Amplitude ripple (p-p)			Δα				
	2170,0	MHz		—	0,7	1,2	dB
Amplitude ripple per 5MHz cha			$\Delta lpha_{5MHz}$				
2110,0	2170,0	MHz		—	0,3	0,6	dB
Input VSWR							
-	2170,0	MHz			1,5	2,0	
2110,0	2170,0	1011 12			1,0	2,0	
Output VSWR							
-	2170,0	MHz		—	1,7	2,1	
Output amplitude balance(S ₃₁							
	2170,0			-1,6		1,6	dB
Output phase balance($\phi(S_{31})$ - ϕ				10.0		10.0	dograa
2110,0	2170,0	IVIHZ		-12,0		12,0	degree
Attenuation			α				
	200,0	MHz	~	60	68	_	dB
	1000,0	MHz		39	42	—	dB
	1880,0	MHz		29	32		dB
	1920,0	MHz		34	38	—	dB
	1980,0	MHz		42	46	—	dB
	2050,0	MHz		25	29		dB
	2255,0	MHz		15	22	—	dB
	2300,0 2490,0	MHz MHz		20 31	23 35		dB dB
	2490,0	MHz		31	35 40	_	dВ
	3200,0	MHz		35	40 39	_	dB
,	6000,0	MHz		40	52	_	dB
,							

SAW Components						B7835	
Low-Loss Filter for Mobile Communication						2140,0 MHz	
Data Sheet							
Characteristics							
Operating temperature range: Terminating source impedance:		= -20 to = 50 Ω	+85 °C				
Terminating load impedance:	Z_{L}	= 200 Ω	(balanced)	22 nH			
			min.	typ.	max.		
Center frequency		f _C		2140,0		MHz	
		0					
Maximum insertion attenuation		α_{max}					
2110,0 2170,0	MHz		—	2,8	3,3	dB	
		A or					
Amplitude ripple (p-p) 2110,0 2170,0	MHz	Δα		0,9	1,5	dB	
2110,0 2110,0	101112			0,0	1,0		
Amplitude ripple per 5MHz channel (p-p))	$\Delta \alpha_{5MHz}$					
2110,0 2170,0	MHz		—	0,4	0,6	dB	
Input VSWR 2110,0 2170,0	МНт			1,6	2,0		
2110,0 2170,0				1,0	2,0		
Output VSWR							
2110,0 2170,0	MHz		—	1,7	2,1		
Output amplitude balance(S ₃₁ /S ₂₁) 2110,0 2170,0	N∕ILI→		16		16	dB	
Output phase balance($\phi(S_{31})-\phi(S_{21})+180$			-1,6		1,6	UD	
2110,0 2170,0			-12,0		12,0	degree	
Attenuation		α					
180,0 200,0	MHz		60	67		dB	
200,0 1000,0 1000,0 1880,0	MHz MHz		39 20	42		dB	
1000,0 1880,0 1880,0 1920,0	MHz		29 34	32 38	_	dB dB	
1920,0 1920,0	MHz		34 42	30 46	_	dВ	
1920,0 1930,0	MHz		25	40 26	_	dB	
2205,0 2255,0	MHz		15	20	_	dB	
2255,0 2300,0	MHz		20	23		dB	
2300,0 2490,0	MHz		31	35		dB	
2490,0 2550,0	MHz		37	40	_	dB	
2550,0 3200,0	MHz		35	39	_	dB	
3200,0 6000,0	MHz		40	52		dB	



Transfer function (wide band):



5

Jan 26, 2004

SAW Components	B7835	
Low-Loss Filter for M	2140,0 MHz	
Data Sheet	SMD	

Published by EPCOS AG Surface Acoustic Wave Components Division, SAW MC P.O. Box 80 17 09, D-81617 München

© EPCOS AG 2004. Reproduction, publication and dissemination of this brochure and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.

This brochure replaces the previous edition.

For questions on technology, prices and delivery please contact the Sales Offices of EPCOS AG or the international Representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our Sales Offices.



Jan 26, 2004