# SKYWORKS

#### DATA SHEET

# SMV1763-079LF Hyperabrupt Junction Tuning Varactor

# **Applications**

- Low-noise and wideband UHF and VHF VCOs
- · High-volume, low-cost batteries

### **Features**

- Low series resistance
- High capacitance ratio at low reverse voltage
- Ultra-small SC-79 package (MSL1, 260 °C per JEDEC J-STD-020)



Skyworks offers lead (Pb)-free, RoHS (Restriction of Hazardous Substances) compliant packaging.



# Description

The SMV1763-079LF is a silicon hyperabrupt junction varactor diode specifically designed for 3 V platforms. The specified high capacitance ratio and low reverse voltage make this varactor appropriate for low phase noise Voltage-Controlled Oscillators (VCOs) used at frequencies in wireless systems up to and above 2.5 GHz.

Table 1 describes the package and marking of the SMV1763-079LF varactor.

#### Table 1. Packaging and Marking

Innovation to Go™

	Single					
	SC-79					
	♦ SMV1763-079LF Marking: Cathode					
	Ls = 0.7 nH					
Ø	LF denotes lead (Pb)-free, RoHS-compliant packaging option as an alternative to the standard Skyworks tin/lead (Sn/Pb) packaging.					

Select Linear Products (indicated by ♦) now available for purchase online.

Skyworks Solutions, Inc. • Phone [781] 376-3000 • Fax [781] 376-3100 • sales@skyworksinc.com • www.skyworksinc.com 200072D • Skyworks Proprietary Information • Products and Product Information are Subject to Change Without Notice • September 25, 2009

Table 2. SMV	1763-079LF	Absolute	Maximum	Ratings
--------------	------------	----------	---------	---------

Parameter	Symbol	Minimum	Typical	Maximum	Units
Reverse voltage	VR			15	V
Forward current	lF			20	mA
Power dissipation	Pdis			250	mW
Operating temperature	Тор	-55		+125	°C
Storage temperature	Тѕтс	-55		+150	٥C

Note: Exposure to maximum rating conditions for extended periods may reduce device reliability. There is no damage to device with only one parameter set at the limit and all other parameters set at or below their nominal value. Exceeding any of the limits listed here may result in permanent damage to the device.

*CAUTION*: Although this device is designed to be as robust as possible, Electrostatic Discharge (ESD) can damage this device. This device must be protected at all times from ESD. Static charges may easily produce potentials of several kilovolts on the human body or equipment, which can discharge without detection. Industry-standard ESD precautions should be used at all times. The SMV1763-079LF varactor is a Class 0 Human Body Model (HBM) ESD device.

# Table 3. SMV1763-079LF Electrical Specifications (Note 1)

(Top = 25 °C, Unless Otherwise Noted)

Parameter	Symbol	Test Condition	Min	Typical	Мах	Units
Reverse current	Ir	$V_R = 20 V$			20	nA
Capacitance	Ст	F = 1 MHz				
		$\begin{array}{l} V_R=0.5 \ V \\ V_R=2.5 \ V \end{array}$	22.1 7.7	23.6 8.6	25.1 9.8	pF pF
Capacitance ratio	Ctr	Ст @ 0.5 V/Ст @ 2.5 V	2.3	2.7		-
Series resistance	Rs	F = 470 MHz, Vr = 1 V		0.7		Ω
Breakdown voltage	VBR	IR = 10 μA	20			V

Note 1: Performance is guaranteed only under the conditions listed in this Table and is not guaranteed over the full operating or storage temperature ranges. Operation at elevated temperatures may reduce reliability of the device.

#### **Electrical and Mechanical Specifications**

The absolute maximum ratings of the SMV1763-079LF varactor are provided in Table 2. Electrical specifications are provided in Table 3. Typical capacitance values are listed in Table 4. Typical performance characteristics for the SMV1763-079LF varactor are illustrated in Figures 1 and 2.

The SPICE model for the SMV1763-079LF varactor is shown in Figure 3 and the associated model parameters are provided in Table 5.

Package dimensions are shown in Figure 4, and tape and reel dimensions are provided in Figure 5.

#### **Package and Handling Information**

Instructions on the shipping container label regarding exposure to moisture after the container seal is broken must be followed.

Otherwise, problems related to moisture absorption may occur when the part is subjected to high temperature during solder assembly.

The SMV1763-079LF varactor is rated to Moisture Sensitivity Level 1 (MSL1) at 260 °C. It can be used for lead or lead-free soldering. For additional information, refer to the Skyworks Application Note, *Solder Reflow Information*, document number 200164.

Care must be taken when attaching this product, whether it is done manually or in a production solder reflow environment. Production quantities of this product are shipped in a standard tape and reel format. For packaging details, refer to the Skyworks Application Note *Discrete Devices and IC Switch/Attenuators Tape and Reel Package Orientation*, document number 200083.

VR (V)	Ст (pF)
0	9.0
0.5	6.7
1.0	5.2
1.5	4.0
2.0	3.2
2.5	2.6
3.0	2.2
3.5	2.0
4.0	1.9
4.5	1.8
5.0	1.8

#### **Table 4. Capacitance vs Reverse Voltage**

# **Typical Performance Characteristics**




Figure 1. Capacitance vs Voltage






Figure 2. Relative Capacitance Change vs Temperature



**Figure 3. SPICE Model** 

#### **Table 5. SPICE Model Parameters**

Part Number	Cjo (pF)	VJ (V)	М	СР (р <b>F</b> )	Rs (Ω)	Ls (nH)
SMV1763-079LF	8.2	15	9.5	0.67	0.5	0.8



Dimensions are in inches (millimeters shown in parentheses) **\$1652** 

Figure 4. SC-79 Package Dimensions




Figure 5. SC-79 Tape and Reel Dimensions

Skyworks Solutions, Inc. • Phone [781] 376-3000 • Fax [781] 376-3100 • sales@skyworksinc.com • www.skyworksinc.com 200072D • Skyworks Proprietary Information • Products and Product Information are Subject to Change Without Notice • September 25, 2009

Copyright © 2002-2006, 2009 Skyworks Solutions, Inc. All Rights Reserved.

Information in this document is provided in connection with Skyworks Solutions, Inc. ("Skyworks") products or services. These materials, including the information contained herein, are provided by Skyworks as a service to its customers and may be used for informational purposes only by the customer. Skyworks assumes no responsibility for errors or omissions in these materials or the information contained herein. Skyworks may change its documentation, products, services, specifications or product descriptions at any time, without notice. Skyworks makes no commitment to update the materials or information and shall have no responsibility whatsoever for conflicts, incompatibilities, or other difficulties arising from any future changes.

No license, whether express, implied, by estoppel or otherwise, is granted to any intellectual property rights by this document. Skyworks assumes no liability for any materials, products or information provided hereunder, including the sale, distribution, reproduction or use of Skyworks products, information or materials, except as may be provided in Skyworks Terms and Conditions of Sale.

THE MATERIALS, PRODUCTS AND INFORMATION ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, WHETHER EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE, INCLUDING FITNESS FOR A PARTICULAR PURPOSE OR USE, MERCHANTABILITY, PERFORMANCE, QUALITY OR NON-INFRINGEMENT OF ANY INTELLECTUAL PROPERTY RIGHT; ALL SUCH WARRANTIES ARE HEREBY EXPRESSLY DISCLAIMED. SKYWORKS DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. SKYWORKS SHALL NOT BE LIABLE FOR ANY DAMAGES, INCLUDING BUT NOT LIMITED TO ANY SPECIAL, INDIRECT, INCIDENTAL, STATUTORY, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS THAT MAY RESULT FROM THE USE OF THE MATERIALS OR INFORMATION, WHETHER OR NOT THE RECIPIENT OF MATERIALS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

Skyworks products are not intended for use in medical, lifesaving or life-sustaining applications, or other equipment in which the failure of the Skyworks products could lead to personal injury, death, physical or environmental damage. Skyworks customers using or selling Skyworks products for use in such applications do so at their own risk and agree to fully indemnify Skyworks for any damages resulting from such improper use or sale.

Customers are responsible for their products and applications using Skyworks products, which may deviate from published specifications as a result of design defects, errors, or operation of products outside of published parameters or design specifications. Customers should include design and operating safeguards to minimize these and other risks. Skyworks assumes no liability for applications assistance, customer product design, or damage to any equipment resulting from the use of Skyworks products outside of stated published specifications or parameters.

Skyworks, the Skyworks symbol, and "Breakthrough Simplicity" are trademarks or registered trademarks of Skyworks Solutions, Inc., in the United States and other countries. Third-party brands and names are for identification purposes only, and are the property of their respective owners. Additional information, including relevant terms and conditions, posted at www.skyworksinc.com, are incorporated by reference.