

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

Telephone: 773.869 www.tripplite.com

# SmartOnline S3MX Series 3-Phase 380/400/415V 80kVA 72kW On-Line Double-Conversion UPS

# MODEL NUMBER: \$3M80KX











Highly efficient 94% on-line UPS with compact design protects mission-critical equipment against downtime due to power disturbances.

#### **Features**

#### **Battery Backup and VFI Operation Protect Critical Loads**

The SmartOnline® S3M80KX IGBT UPS supports the continuous availability of your most important loads through all power conditions, providing a compact backup power platform that's easy to manage and inexpensive to operate. Sophisticated voltage and frequency independent (VFI) operation and advanced IGBT rectifier technology with DSP control deliver reliable output power quality. Providing up to 80kVA of clean, continuous power, this 3-phase UPS system is perfect for critical applications in IT, communications, corporate, commercial, retail, financial, security, transportation, emergency and light industrial environments.

#### Best-in-Class Footprint for Easy Integration into Your Network Application

This on-line double-conversion UPS system has a very small footprint of just 0.28 square meters. It requires less valuable space in your facility, and you can install the UPS system in spaces that would previously have required expensive retrofitting.

# Efficient Operation and Design Reduces Cost of Ownership

This IGBT UPS benefits from highly efficient transformer-free double-conversion technology that delivers operating cost savings. It achieves 94% efficiency in double-conversion mode and up to 98% in ECO mode, reducing your power and cooling costs. A low THDi (<3%) improves generator compatibility. A low THDv (2%) and active power factor correction improve output performance. The hardware and firmware platform design reduces the number of unique boards, improving mean time to repair (MTTR) and resulting in reduced downtime. Built-in static and maintenance bypass transfer UPS load to utility power during faults, overloads and maintenance, which also avoids costly system downtime.

# External Batteries Supply Reliable Backup with Expandable Runtime Options

The S3M80KX uses external scalable battery cabinets, such as BP480V65 and BP480V100 (sold separately), to provide up to three hours of backup support in case of a power failure. The UPS system automatically restarts after a lengthy power outage.

#### Intuitive LCD Interface Delivers Important Performance Information at a Glance

The interactive front-panel LCD interface displays critical operating conditions and diagnostic data, including operating mode, input/output voltage, load, battery voltage, backup runtime and fault conditions. Four LEDs provide information about line, bypass, battery and fault status.

# **Network Management Card Offers Remote Monitoring and Control**

The optional Java-free WEBCARDLX network management card (sold separately) enables remote

# **Highlights**

- Best-in-class footprint and power density minimize space requirements for up to 80kVA
- Intuitive LCD interface offers key performance, configuration and diagnostics info
- High efficiency (94% on-line, 98% ECO mode) helps reduce operating costs
- Optional WEBCARDLX network management card allows costeffective remote management
- Parallel capability provides increased capacity and redundancy up to 3 units

# **Applications**

- Save space in tight data center environments with best-in-class small footprint
- Back up essential equipment in network, telecom, financial and light industrial applications
- Maintain critical data-center, automation-system and production-line operations during all power conditions

#### Package Includes

- S3M80KX SmartOnline S3MX
   Series 3-Phase 380/400/415V
   80kVA 72kW On-Line Double-Conversion UPS
- P3080KIT parallel cable kit
- RS-232 cable
- Owner's manual



management through embedded HTML5 web, SSH/telnet and SNMP interfaces, as well as integration with a wide range of network management systems and DCIM platforms. A Remote Emergency Power Off (REPO) port allows shutdown from a safe distance during emergencies.

Parallel Capability Provides Additional Capacity and Redundancy up to 3 Units Connect up to three S3M80KX units in parallel using separate/shared battery cabinets for increased capacity.

# **Specifications**

OVERVIEW			
UPC Code	037332225412		
UPS Type	On-Line		
INPUT			
Rated input current (Maximum Load)	122.2A		
Nominal Input Voltage(s) Supported	220/380V 3-PH Wye; 230/400V 3-PH Wye; 240/415V 3-PH Wye		
Nominal Input Voltage Description	3-Phase Wye, 4 wire plus ground (L1, L2, L3, N, G)		
UPS Input Connection Type	Hardwire		
Input Circuit Breakers	6 x 30A fuses/Phase		
Input Phase	3-Phase		
Power Factor (Input)	.99PF (100% load)		
THDi	<3% (100% load)		
оитрит			
Output Volt Amp Capacity (VA)	80000		
Output kVA Capacity (kVA)	80.00		
Output Watt Capacity (Watts)	72000		
Output kW Capacity (kW)	72.00		
Power Factor	0,9		
Crest Factor	3:1		
Frequency Compatibility	50 / 60 Hz; Supports 50 to 60 Hz and 60 to 50 Hz conversion		
Frequency Compatibility Details	Automatic frequency selection		
Output Voltage Regulation (Line Mode)	+/- 1%		
Output Voltage Regulation (Economy Line Mode)	+/-11V of nominal		
Output Voltage Regulation (Battery Mode)	+/- 1%		





Output AC Waveform (AC Mode)	Pure Sine wave	
Output AC Waveform (Battery Mode)	Pure Sine wave	
Output Capacity Details	Supports up to 100% load continuously in double conversion mode; Supports 100-110% load for 10 minutes, 110 to 130% load for 1 minute and greater than 130% for 1 second before switching to bypass mode; Inverter mode is automatically restored as load levels are reduced to less than 70%; Configuration options support up to 3 S3M30KX systems wired in parallel for increased capacity or fault-tolerant, redundant operation	
Nominal Output Voltage(s) Supported	220/380V 3-PH Wye; 230/400V 3-PH Wye; 240/415V 3-PH Wye	
Output Receptacles	Hardwire	
Individually Controllable Load Banks	No	
BATTERY		
Expandable Battery Runtime	Supports extended runtime with optional external battery packs. Please consult the owners manual.	
External Battery Pack Compatibility	<a class="productLink" href="//www.tripplite.com/external-ups-battery-pack-40-100-Ah-battery~BP480V100">BP480V100</a> \and hosp;; <a class="productLink" href="//www.tripplite.com/external-ups-battery-pack-40-100-Ah-battery~BP480V100">BP480V100</a> \and hosp;\nlip \text{ knbsp};\nlip \text{ knbsp};\nlip \text{ class="productLink" href="//www.tripplite.com/external-ups-battery-pack-40-40-Ah-battery~BP480V40">BP480V40\and hosp;\nlip \text{ knbsp};\nlip \text{ knbsp};\nlip \text{ aclass="productLink" href="//www.tripplite.com/external-ups-battery-pack-40-Ah-battery~BP480V40">BP480V40\and hosp;\nlip \text{ knbsp};\nlip \text{ knbsp};\nlip  class="productLink" href="//www.tripplite.com/external-ups-battery-pack-40-65-Ah-battery~BP480V65">BP480V65\and hosp;	
DC System Voltage (VDC)	+/- 240	
Battery Recharge Rate (Included Batteries)	9 hours to 90% (Internal batteries)	
Expandable Runtime	Yes	
VOLTAGE REGULATION		
Voltage Regulation Description	Online, double-conversion power conditioning maintains output within 1% of the selected nominal voltage in online mode	
USER INTERFACE, ALERTS & CONTROLS		
Front Panel LCD Display	LCD DISPLAY: offers a variety of graphical, text and numeric information to indicate a wide range of UPS operation and fault / warning conditions, including current operating mode, alarm status, load level, battery charge, input / output voltage & frequency, estimated runtime and more (see user manual for a detailed listing)	
Switches	ON / ENTER BUTTON: turns the UPS on and confirms a selection from the settings menu; OFF / ESC BUTTON: turns off the UPS and returns to the previous item in the settings menu; TEST / UP BUTTON: initiates UPS self-test operation and advances to the next item in the settings menu; MUTE / DOWN BUTTON: silences the audible alarm and advances to the previous item in the settings menu; Press TEST/UP & MUTE/DOWN buttons simultaneously for 1 second to enter or exit the settings menu (See user manual for detailed information)	
Audible Alarm	Alarms warn users of a variety of operational conditions: BYPASS MODE (beeps every 2 seconds), BATTERY MODE (beeps every 4 seconds), FAULT MODE (beeps continuously), OVERLOAD (beeps twice per second), OTHER WARNINGS (beeps once per second), FAULT (beeps continuously); All alarms can be silenced, except OVERLOAD & OTHER WARNINGS conditions	
LED Indicators	4 LEDs report BYPASS / LINE / BATTERY / FAULT modes	
PHYSICAL		
Cooling Method	Fans	
Installation Form Factors Supported with Included Accessories	Tower	



B:	_
Primary Form Factor	Tower
Primary UPS Depth (mm)	790
Primary UPS Height (mm)	1,010
Primary UPS Width (mm)	360
Shipping Dimensions (hwd / cm)	119.99 x 47.98 x 90.98
Shipping Dimensions (hwd / in.)	47.24 x 18.89 x 35.82
Shipping Weight (kg)	134.72
Shipping Weight (lbs.)	297.00
UPS Housing Material	Steel
UPS Power Module Dimensions (Height x Width x Depth, mm)	1010 x 360x 790
UPS Power Module Dimensions (hwd, cm)	100.99 x 35.99 x 78.99
UPS Power Module Dimensions (hwd, in.)	39.76 x 14.17 x 31.10
UPS Power Module Weight (kg)	112.94
UPS Power Module Weight (lbs.)	249
ENVIRONMENTAL	
Operating Temperature Range	0 to +40C (32-104F)
Storage Temperature Range	0 to +35C (32 to 95F) with battery; -15 to 60C (5 to +140F) without battery
Relative Humidity	5 to 95%, non-condensing
Operating Elevation (ft.)	< 3280ft (Capacity de-rates by 1% for every 328ft over 3280ft )
Audible Noise	<75BA at 1meter
Operating Elevation (m)	< 1000m (Capacity de-rates by 1% for every 100m over 1000m)
COMMUNICATIONS	
Network Management Cards	<a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card~WEBCARDLX">WEBCARDLX</a> ; <a class="productLink" href="//www.tripplite.com/Programmable-RS-485-Management-Accessory-Card-for-Select-3-Phase-UPS-Systems~MODBUSCARDSV">MODBUSCARDSV</a> ; <a class="productLink" href="//www.tripplite.com/Programmable-Relay-I-O-Card-Tripp-Lite-SVTX-SVX-SV-UPS-Systems~RELAYCARDSV">RELAYCARDSV</a>
Network Monitoring Port Description	Card accessory slot supports network management interface or programmable I/O relay card options
Communications Cable	DB9/RS-232 cable included
Communications Interface	DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface
LINE / BATTERY TRANSFER	
Transfer Time	Zero transfer time Online to Battery, Inverter to Bypass 0ms (Synchronous), and Inverter to ECO mode < 10ms.
Low Voltage Transfer to Battery Power (Setpoint)	120V(Ph-N), 208V (Ph-Ph) @ 50% load / 176V (Ph-N), 305V (Ph-Ph) @ 100% load.



**Tripp Lite**1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

High Voltage Transfer to Battery Power (Setpoint)	276 (Ph-N), 478V (Ph-Ph) @ 50% or 100% load.		
SPECIAL FEATURES			
Grounding Lug	Yes		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
High Availability UPS Features	Automatic inverter bypass; Manual bypass switch; Auto Probe Monitoring (requires WEBCARDLX); Zero transfer time; On-Line/Double-Conversion		
Green Energy-Saving Features	High efficiency economy mode operation		
STANDARDS & COMPLIANCE			
UPS Certifications	CE		
UPS Certification Details	IEC/EN 62040-1:2008+A1 (Safety); IEC/EN 62040-2:2006 (Category C3)		
WARRANTY			
Product Warranty Period (International)	2-year limited warranty		
3-Phase Warranty Statement	Tripp Lite 3-Phase UPS Factory Warranty		

© 2020 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>