

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

SmartPro Tower UPS System - Intelligent, lineinteractive battery backup and network power management

MODEL NUMBER: SMART700





Description

Tripp Lite's SMART 700 intelligent, line interactive UPS system protects servers, networking accessories and telecommunications equipment from blackouts, voltage fluctuations and transient surges. Large internal batteries offer 20 minutes half load runtime and 6 minutes at full load during power failures. 700VA/450 watt power handling capability supports a variety of networking, telecom and various other application types, including the support of multiple network workstations. Includes a total of 6 UPS supported outlets. Supports remote monitoring of UPS and site power conditions via built-in USB monitoring port. Includes PowerAlert UPS monitoring and unattended shutdown software with complete cabling. Built-in audible alarm and 5 front panel LEDs indicate status of line power, battery power, battery low/replace, voltage regulation and load level. Wall mountable with UPSWM wallmount bracket. Network-grade AC surge suppression protects equipment from damage and performance problems resulting from transient surges. Attractive, small-footprint tower housing uses less than 53 square inches of floor or desktop space. Two year warranty with \$250,000 connected equipment insur.

Features

- 700VA/450 watt power handling capability supports a variety of networking, telecom and various other application types
- Built-in voltage regulation and battery support, plus complete AC line surge suppression prevents equipment damage, data loss and downtime
- Large internal batteries offer 20 minutes half load runtime and 6 minutes at full load during power failures
- Automatic Voltage Regulation (AVR) circuits with two boost and one voltage reduction level maintains usable 120V nominal output over an input voltage range of 75-147V
- Includes a total of 6 NEMA5-15R outlets
- Includes USB communications port for remote monitoring of UPS status and site power conditions
- Communications port enables safe unattended shutdown without data loss during extended power failures

Highlights

- 700VA line interactive tower
 LIPS
- Maintains 120V nominal output over an input range of 75 to 147V
- Network communications supported via USB port
- Current monitoring
- Input: NEMA 5-15P (120V 15A)
 / Output: 6 NEMA 5-15R (120V)
- 2 year product warranty / \$250,000 Ultimate Lifetime Insurance (USA, Puerto Rico & Canada only)

Package Includes

- SMART 700 UPS System
- · Monitoring cable
- PowerAlert unattended shutdown and UPS/Power monitoring software
- Instruction manual with warranty information



- Communications port supports messaging of UPS and line power status, including on-battery, lowbattery, power-restored, AC line voltage, DC battery voltage and battery capacity
- Communications ports support timed inverter shutoff after unattended shutdown, activate self-test and
 10 second reboot of connected equipment
- PowerAlert UPS monitoring and unattended shutdown software with complete cabling included
- Battery replacement door
- Supports Tripp Lite's WatchDog software application to restore unresponsive programs by automatically restarting them and rebooting completely locked computers by automatically switching UPS power off and back on again
- Notification of system status via 5 LEDs and multi-function audible alarms
- Wall mountable with UPSWM wallmount bracket
- Attractive small footprint black tower housing uses less than 53 square inches
- Hot-swappable batteries allow on-site battery replacement
- Cold start capability enables UPS turn-on in battery mode during blackout conditions
- UL (USA), cUL (Canada), NOM (Mexico), Class A (Emissions) Listed
- \$250,000 Ultimate Lifetime Insuran.
- 2 year manufacturers product warranty

Specifications

OVERVIEW		
UPC Code	037332033765	
INPUT		
Rated input current (Maximum Load)	4.4A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
UPS Input Cord Length (ft.)	6	
UPS Input Cord Length (m)	1.8	
Recommended Electrical Service	15A 120V	
Input Cord Length (ft.)	6	
Input Cord Length (m)	1.83	
OUTPUT		
Output Volt Amp Capacity (VA)	700	
Output Watt Capacity (Watts)	450	
Power Factor	0.6	





Output Voltage Regulation (Line Mode) 115V (+/- 5%) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) PWM sine wave Output AC Waveform (Battery PWM sine wave) Nominal Output Voltage(s) Supported 115V; 120V Output Receptacles (6) 5-15R BATTERY Full Load Runtime (min.) E min. (450w) Half Load Runtime (min.) C system Voltage (VDC) Battery Recharge Rate (Included Eastery Activities) Battery Recharge Rate (Included Eastery Easter) Settler(s) Internal UPS Replacement Battery Eastery Access Battery Access Battery Access Battery Access Battery Access Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 75 and 92 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation	E 0 (11.11)	2011	
Mode) Cottput Voltage Regulation (Battery Mode) Cottput Act Waverform (AC Mode) Sine wave Cottput AC Waverform (Battery PWM sine wave Mode) Nominal Output Voltage(s) Supported 115V; 120V Output Receptacies (6) 5-15R BATTERY Full Load Runtime (min.) B min. (450w) Half Load Runtime (min.) 20 min. (225w) DC System Voltage (NDC) 12 Battery Recharge Rate (Included Battery Cartridge States) Internal UPS Replacement Battery Cartridge Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 128 and 147 are reduced by 12% Severe Undervoltage Correction Input voltages between 33 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERRACE, ALERTS & CONTROLS Switches 2 Switches alarm and be silenced using alarm-cancel/self-test operation Audible Alarm Audible Alarm Audible alarm indicates power-failure and low-battery conditions UPS AC Suppression Joule Rating VSPS AC Suppression Joule Rating VSPS AC Suppression Joule Rating VSPS AC Suppression Joule Rating Instantianeous Instantianeous Instantianeous Instantianeous	Frequency Compatibility	60 Hz	
Output AC Waveform (AC Mode) Sine wave Dutput AC Waveform (Battery pWM sine wave Nominal Output Voltage(s) Supported Output Receptacles (6) 5-15R BATTERY Full Load Runtime (min.) 5 min. (450w) Holf Load Runtime (min.) Co system Voltage (VPC) DC System Voltage (VPC) Battery Recharge Rate (Included Batteries) Battery Replacement Battery Cartridge Battery Access Battery access door Battery Access Battery access Battery access door Battery Replacement Description Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control offion power status and alarm-cancel/self-test operation Audible Alarm Audible Alarm Audible alarm indicates power-failure and low-battery conditions UPS AC Suppression Joule Rating Instantianeous	Output Voltage Regulation (Line Mode)	-18%, +8%	
Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported 115V; 120V Output Receptacles (6) 5-15R BATTERY Full Load Runtime (min.) 6 min. (450w) Half Load Runtime (min.) 20 min. (225w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Battery Recharge Rate (Included Batteries) Abstracting Battery Another UPS - Replacement Battery Another Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status UPS AC Suppression Joule Rating 1758 AC Suppression Response 1768 Instantaneous		115V (+/- 5%)	
Nominal Output Voltage(s) Supported 115V; 120V Output Receptacles (6) 5-15R BATTERY Full Load Runtime (min.) 6 min. (450w) Half Load Runtime (min.) 20 min. (225w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Battery Access Battery Replacement Battery Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches ontrol off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators S LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION LIPS AC Suppression Joule Rating 450 Instantaneous	Output AC Waveform (AC Mode)	Sine wave	
Output Receptacles (6) 5-15R BATTERY Full Load Runtime (min.)		PWM sine wave	
BATTERY Full Load Runtime (min.) 6 min. (450w) Half Load Runtime (min.) 20 min. (225w) DC System Voltage (VDC) 12 Less than 6 hours from 10% to 90% Battery Recharge Rate (Included Batteries) Internal UPS Replacement Battery Liebert-Minuteman-orther-UPS-RBC52*/s-BC52*/a-8.nbsp; (x2) Battery Access Battery access door Battery Aminuteman-orther-UPS-RBC52*/s-BC52*/a-8.nbsp; (x2) Battery Access Battery access door Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 33 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Nominal Output Voltage(s) Supported	115V; 120V	
Full Load Runtime (min.) 6 min. (450w) Half Load Runtime (min.) 20 min. (225w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Internal UPS Replacement Battery Less than 6 hours from 10% to 90% Internal UPS Replacement Battery Less than 6 hours from 10% to 90% Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control offion power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Output Receptacles	(6) 5-15R	
Half Load Runtime (min.) 20 min. (225w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Internal UPS Replacement Battery Liebert-Minuteman-other-UPS-RBC52'>RBC52-/a>- (x2) Battery Access Battery access door Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions SLEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	BATTERY		
DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Internal UPS Replacement Battery Lebert-Minuteman-other-UPS-RBC52'>RBC52-/a> (x2) Battery Access Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions SLEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating Instantaneous Instantaneous	Full Load Runtime (min.)	6 min. (450w)	
Battery Recharge Rate (Included Batteries) Less than 6 hours from 10% to 90% Internal UPS Replacement Battery Liebert-Minuteman-other-UPS-RBC52*>RBC52*>Replacement-Battery-Cartridge-select-Tripp-Lite-Best-Liebert-Minuteman-other-UPS-RBC52*>RBC52*>RBC52*/as- (x2) Battery Access Battery access door Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating Instantaneous	Half Load Runtime (min.)	20 min. (225w)	
Internal UPS Replacement Battery Liebert-Minuternan-other-UPS-RBC52*SRBC52*Aa- (x2) Battery Access Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators S LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status UPS AC Suppression Joule Rating Instantaneous Instantaneous	DC System Voltage (VDC)	12	
Eattery Access Battery access door Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Time Instantaneous	Battery Recharge Rate (Included Batteries)	Less than 6 hours from 10% to 90%	
Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Internal UPS Replacement Battery Cartridge	RBC52 (x2)	
VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Battery Access	Battery access door	
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating Instantaneous Instantaneous	Battery Replacement Description	Hot-swappable, user replaceable batteries	
Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	VOLTAGE REGULATION		
Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75V to 147V	
Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Overvoltage Correction	Input voltages between 128 and 147 are reduced by 12%	
USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Undervoltage Correction	Input voltages between 93 and 107 are boosted by 14%	
Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Severe Undervoltage Correction	Input voltages between 75 and 92 are boosted by 30%	
Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	USER INTERFACE, ALERTS & CONTROLS		
Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Time Instantaneous	Switches	2 Switches control off/on power status and alarm-cancel/self-test operation	
LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 450 UPS AC Suppression Response Instantaneous	Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status	
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	Audible Alarm	Audible alarm indicates power-failure and low-battery conditions	
UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	LED Indicators	5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status	
UPS AC Suppression Response Time Instantaneous	SURGE / NOISE SUPPRESSION		
Time Installations	UPS AC Suppression Joule Rating	450	
EMI / RFI AC Noise Suppression Yes		Instantaneous	
	EMI / RFI AC Noise Suppression	Yes	





AC Suppression Joule Rating	1800	
AC Suppression Response Time	Instantaneous	
PHYSICAL		
Installation Form Factors Supported with Included Accessories	Tower	
Installation Form Factors Supported with Optional Accessories	Wallmount (UPSWM - tower mounting kit)	
Primary Form Factor	Tower	
Primary UPS Depth (mm)	191	
Primary UPS Height (mm)	300	
Primary UPS Width (mm)	183	
Shipping Dimensions (hwd / cm)	39.37 x 27.94 x 28.58	
Shipping Dimensions (hwd / in.)	15.50 x 11.00 x 11.25	
Shipping Weight (kg)	11.34	
Shipping Weight (lbs.)	25.00	
UPS Housing Material	PVC	
UPS Power Module Dimensions (hwd, cm)	29.97 x 18.29 x 19.05	
UPS Power Module Dimensions (hwd, in.)	11.8 x 7.2 x 7.5	
UPS Power Module Weight (kg)	9.98	
UPS Power Module Weight (lbs.)	22	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	133	
Battery Mode BTU / Hr. (Full Load)	565.9	
AC Mode Efficiency Rating (100% Load)	92%	
COMMUNICATIONS		
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions	
PowerAlert Software	Included	
Communications Cable	USB cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Communications Interface	USB	





LINE / BATTERY TRANSFER		
Transfer Time	2-4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	75	
High Voltage Transfer to Battery Power (Setpoint)	147	
SPECIAL FEATURES		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS	
STANDARDS & COMPLIANCE		
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Meets FCC Part 15 Category A (EMI); ROHS (Restriction of Hazardous Substances)	
WARRANTY		
Product Warranty Period (Worldwide)	2-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance	

© 2020 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies