# **DIAZED (BOTTLE)**

Diazed Fuses, commonly called "Bottle" Fuses, are available in five sizes, ND to 35 Amps, DII to 35 Amps, DIII to 100 Amps, DIV to 100 Amps and DV to 200 Amps. Fuse accessories are sized to match. Each size fuse body has a different diameter to fit only into the appropriate Screw Cap and Fuse Base. (See illustration pg 10.)

Also, the fuse tips have different diameters, depending on their current rating. The diameter of the tip matches the diameter of the hole in the Adapter Screw to insure that no fuse with a higher rating than intended for the circuit can be installed. This prevents damage to the circuit or equipment the fuse protects. Additionally, fuses and Adapter Screws are color coded to avoid mismatching; for example: 10 Amp Diazed fuses have red pop-out indicators on their head, matching the red ring of the 10 Amp Adapter Screw.

When a Diazed fuse has blown, the color coded indicator on the head of the fuse will pop out, giving visible indication through a glass window in the Screw Cap.

The Fuse is held in place by the Screw Cap, which is screwed into the Fuse Base. Diazed Fuse Bases are available in one and three pole designs. Fuse Bases can be panel mounted or snapped onto a standard 35mm DIN rail.

## **Operating Classes**

### gL/gG - Slow Blow

Protect cable, equipment, and conductors from damage due to overloads and short circuits.

Typical Markings: "T", Trage, gL/gG, Vollschutz,

#### - Fast Blow

Fast Blow fuses are typically used to protect equipment.

Typical Markings: "F", Flink, (the absence of the snail symbol)

#### gR - Semiconductor Protection

Typically used for protecting semiconductors like diodes, SCRs, etc. Current limiting.

Typical Markings: Ultra Rapid™, Ultra Quick™, Silized™, Recticur™, gR,

Mostly red, orange, or blue imprint.

Not standard rating.

and ordering information.

Refer to page indicated for additional selection



## **ND-E 16**

	ND-L 10						
Ordering Information	Current/ Voltage	Cat. No.	Color Code	Std. Pk.			
Slow Blow - Operating Class gL/gG (VDE 0636 / IEC 269) Cable, Equipment, and Line Protection, up to 500V AC (660V and 750V available)	2/500V AC 4/500V AC 6/500V AC 10/500V AC 16/500V AC 20/500V AC 25/500V AC 30/500V AC 35/500V AC	2D16SB 4D16SB 6D16SB 10D16SB 16D16SB 20D16SB 25D16SB 30D16SB *		25 25 25 25 25 25 25 25 25 25 25			
Fast Blow (CEE-16) - old standard for Equipment Protection, up to 500V AC (750V available)	2/500V AC 4/500V AC 6/500V AC 10/500V AC 16/500V AC 20/500V AC 25/500V AC 30/500V AC 35/500V AC	2D16FB 4D16FB 6D16FB 10D16FB 16D16FB 20D16FB 25D16FB 30D16FB *	Pink Brown Green Red Gray Blue Yellow Silver Black	25 25 25 25 25 25 25 25 25 25 25			
Semiconductor Protection - Operating Class gR (VDE 0636 / IEC 269) Semiconductor Protection, up to 500V AC, 440V DC	2/500V AC 4/500V AC 6/500V AC 10/500V AC 16/500V AC 20/500V AC 25/500V AC 30/500V AC	2D16SC 4D16SC 6D16SC 10D16SC 16D16SC 20D16SC 25D16SC 30D16SC	Pink Brown Green Red Gray Blue Yellow Black	25 25 25 25 25 25 25 25 25			
<b>Screw Cap</b> (pgs 10-11)**		D16C		1			
Adapter Screw (pgs 10-11)** (Install only with Adapter Screw Tool)	N	Not Available					
Adapter Screw Tool (pgs 10-11)** (for inserting or removing all Adapter Screws)	N	Not Available					
Fuse Base, Single Pole (pgs 10-11)** Fuse Base, Three Pole (pgs 10-11)**		D16B D16B3		1 1			
Fuse Base Cover, Single Pole (pgs 10-11)** Fuse Base Cover, Three Pole (pgs 10-11)**		D16BC D16BC3		1 1			
	Ø13.2mm (.52 in.)						

Dimensions to DIN 49360





**DII-E 27** 



**DIII-E 33** 

D33BC

D33BC3


Dimensions to DIN 49515

- Ø27mm (1.07 in.)

- 50mm – (1.97in.)



**DIV-R 1.25** 




For DIV fuses, please consult Altech.

DII-E 21			DIII-E 33					
	Current/ Voltage	Cat. No.	Color Code S	td. Pk.	Current/ Voltage	Cat. No.	Color Code S	td. Pk.
	2/500V AC 4/500V AC 6/500V AC 10/500V AC 16/500V AC 20/500V AC 25/500V AC 30/500V AC 35/500V AC	2D27SB 4D27SB 6D27SB 10D27SB 16D27SB 20D27SB 25D27SB 30D27SB* 35D27SB*	Pink Brown Green Red Gray Blue Yellow Silver Black	5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5	35/500V AC 40/500V AC 50/500V AC 63/500V AC 80/500V AC 100/500V AC	35D33SB 40D33SB* 50D33SB 63D33SB 80D33SB* 100D33SB*	White Copper Silver	5 5 5 5 5 5
	2/500V AC 4/500V AC 6/500V AC 10/500V AC 16/500V AC 20/500V AC 25/500V AC 30/500V AC 35/500V AC	2D27FB 4D27FB 6D27FB 10D27FB 16D27FB 20D27FB 25D27FB 30D27FB* 35D27FB*	Pink Brown Green Red Grey Blue Yellow Silver Black	5 5 5 5 5 5 5 5 5	35/500V AC 40/500V AC 50/500V AC 63/500V AC 80/500V AC 100/500V AC	35D33FB 40D33FB* 50D33FB 63D33FB 80D33FB* 100D33FB*	Black Black White Copper Silver Silver	5 5 5 5 5 5
	2/500V AC 4/500V AC 6/500V AC 10/500V AC 16/500V AC 20/500V AC 25/500V AC 30/500V AC	2D27SC 4D27SC 6D27SC 10D27SC 16D27SC 20D27SC 25D27SC 30D27SC	Pink Brown Green Red Grey Blue Yellow Black	5 5 5 5 5 5 5 5 5	35/500V AC 50/500V AC 63/500V AC	35D33SC 50D33SC 63D33SC	Black White Copper	5 5 5
		D27C		1		D33C		1
	Re	efer to pgs 10-	·11		Re	efer to pgs 10-	-11	
		DAT		1		DAT		1
		D27B D27B3		1 1		D33B D33B3		1 1

1



**DV-R2** 



For DV fuses, please consult Altech.

Dimensions to DIN 49515

D27BC

Ø22mm (.87 in.)

- 50mm – (1.97in.)

D27BC3