

SERIES: VPU-S200 | DESCRIPTION: AC-DC POWER SUPPLY

FEATURES

- up to 200 W continuous power
- U-Frame
- universal input (85-264 Vac / 120-340 Vdc)
- 12V fan drive
- single output from 3.3 to 48 V
- active power correction
- remote on/off
- power good signal
- remote sense
- short circuit, over voltage, over load, and over current protections
- UL/cUL and TUV safety approvals
- efficiency up to 81%



.....

| MODEL | output voltage | output current | output power | ripple and noise | efficiency |
|--------------|-------------------|-------------------|-----------------|-----------------------|-------------------|
| | (Vdc) | max (A) | max (W) | max (mVp-p) | typ (%) |
| VPU-S200-3.3 | 3.3 | 30 | 73 | 60 | 75 |
| VPU-S200-5 | 5 | 30 | 150 | 60 | 75 |
| VPU-S200-12 | 12 | 16.7 | 200 | 120 | 75 |
| VPU-S200-15 | 15 | 13.3 | 200 | 150 | 78 |
| VPU-S200-24 | 24 | 8.3 | 200 | 240 | 81 |
| VPU-S200-36 | 36 | 5.5 | 200 | 360 | 81 |
| VPU-S200-48 | 48 | 4.2 | 200 | 480 | 81 |



.....

INPUT

| parameter | conditions/description | min | typ | max | units |
|----------------|--|-----------|------------|------------|------------|
| voltage | | 85 120 | | 264 340 | Vac Vdc |
| frequency | | 47 | | 63 | Hz |
| current | at 115 Vac, full load at 230 Vac, full load | | | 1.4 0.7 | A A |
| inrush current | at 115 Vac, 25°C, full load, cold start at 230 Vac, 25°C, full load, cold start | | | 20 40 | A A |
| power factor | at 100 Vac, full load at 200 Vac, full load | | .99 .95 | | |

| OUTPUT | | | | | | |
|-------------------------|-----------------------------------|---------|-----|-------|--|--|
| parameter | conditions/description | min typ | max | units | | |
| line regulation | full load | 0.5 | 1 | % | | |
| load regulation | at 230 Vac | 3 | 5 | % | | |
| temperature coefficient | all output | ±0.05 | | %/°C | | |
| transient response | full load to half load at 100 Vac | | 4 | ms | | |
| adjustability | Adjustable with built-in trim pot | | ±10 | % | | |
| switching frequency | | 100 | | KHz | | |
| start-up time | full load at 100 Vac | | 0.5 | S | | |
| hold-up time | full load at 110 Vac | 20 | | ms | | |

PROTECTIONS

| conditions/description | min | typ | max | units |
|---|---|--|--|--|
| recovers automaticly | 105 | | | % |
| | 115 | | 140 | % |
| Protected, long term short circuit may reduce | e reliability | | | |
| recovers automaticly | 105 | | | % |
| | recovers automaticly Protected, long term short circuit may reduce | recovers automaticly 105 115 Protected, long term short circuit may reduce reliability | recovers automaticly 105 115 Protected, long term short circuit may reduce reliability | recovers automaticly 105 115 140 Protected, long term short circuit may reduce reliability |

SAFETY & COMPLIANCE

| parameter | conditions/description | min | typ | max | units |
|--------------------------|-----------------------------------|---------|-----|-----|-------|
| | Primary to secondary: | 4242 | | | Vdc |
| isolation voltage | Primary to transformer core: | 2000 | | | Vac |
| | Primary to earth ground: | 2000 | | | Vac |
| isolation resistance | test voltage of 500 Vdc | 50 | | | MΩ |
| safety appr ovals | UL/cUL 60950, TUV EN60950, CE, CB | | | | |
| EMI/EMC | FCC class B, EN55022 class B | | | | |
| eakage current | full load at 240 Vac | | | 1.5 | mA |
| 4TBF | MIL-HDSK-217F, 25°C ambient | 450,000 | | | hrs |
| RoHS | 2011/65/EU | | | | |
| | | | | | |

.....

.....

ENVIRONMENTAL

| conditions/description | min | typ | max | units |
|--|--|---|--|---|
| (10 ~ 55 Hz, 1 hour per axis, 3 hours total) | | 2 | | G |
| | -10 | | 65 | °C |
| | -20 | | 75 | °C |
| non-condensing | 20 | | 90 | % |
| non-condensing | 0 | | 75 | % |
| | (10 ~ 55 Hz, 1 hour per axis, 3 hours total) non-condensing | (10 ~ 55 Hz, 1 hour per axis, 3 hours total) -10 -20 non-condensing 20 | (10 ~ 55 Hz, 1 hour per axis, 3 hours total) 2 -10 -20 non-condensing 20 | (10 ~ 55 Hz, 1 hour per axis, 3 hours total) 2 -10 65 -20 75 non-condensing 20 90 |

DERATING CURVES

.....



MECHANICAL DRAWING



| | CN1 | C | N2 | C | :N3 | С | N4 | F |
|---|-------------|---|--|--|--|---|--|--|
| 1 | N | 1 | -Vo | 1 | FAN+ | 1 | RTN | F |
| 2 | n/c | 2 | -Vo | 2 | FAN- | 2 | on/off | F |
| 3 | L | 3 | -Vo | | | 3 | PG | F |
| 4 | n/c | 4 | -Vo | | | 4 | RTN | |
| 5 | FG | 5 | -Vo | | | 5 | RS+ | |
| | | 6 | -Vo | | | 6 | RS- | |
| | | 7 | +Vo | | | | | - |
| | | 8 | +Vo | | | | | |
| | | 9 | +Vo | | | | | |
| | | 10 | +Vo | | | | | |
| | | 11 | +Vo | | | | | |
| | | 12 | +Vo | | | | | |
| | 2 3 4 | 1 N 2 n/c 3 L 4 n/c | 1 N 1 2 n/c 2 3 L 3 4 n/c 4 5 FG 5 6 7 8 9 10 11 | 1 N 1 -Vo 2 n/c 2 -Vo 3 L 3 -Vo 4 n/c 4 -Vo 5 FG 5 -Vo 6 -Vo 7 +Vo 8 +Vo 9 +Vo 10 +Vo 11 +Vo | $\begin{array}{c c c c c c c c c c c c c c c c c c c $ | 1 N 1 -Vo 1 FAN+ 2 n/c 2 -Vo 2 FAN- 3 L 3 -Vo 4 -Vo 4 n/c 4 -Vo 5 FG 5 -Vo 5 FG 5 -Vo 6 -Vo 7 +Vo 8 +Vo 9 +Vo 10 +Vo 11 +Vo | 1 N 1 -Vo 1 FAN+ 1 2 n/c 2 -Vo 2 FAN- 2 3 L 3 -Vo 3 3 4 n/c 4 -Vo 4 4 5 FG 5 -Vo 5 5 6 -Vo 7 +Vo 6 7 +Vo 8 +Vo 6 9 +Vo 10 +Vo 11 +Vo | 1 N 1 -Vo 1 FAN+ 1 RTN 2 n/c 2 -Vo 2 FAN- 2 on/off 3 L 3 -Vo 2 FAN- 2 on/off 4 n/c 4 -Vo 3 PG 5 FG 5 -Vo 4 RTN 5 FG 5 -Vo 5 RS+ 6 -Vo 6 RS- 7 +Vo 8 +Vo 9 +Vo 10 +Vo 11 +Vo 11 +Vo |

.....

RTN: Return terminals for logic signals. Same electrical potential as -Vo. RS+: Remote Sense positive terminals. RS-: Remote Sense negative terminals. PG: Power good signal.

REVISION HISTORY

| rev. | description | date |
|------|-----------------------------|------------|
| 1.0 | initial release | 01/30/2006 |
| 1.01 | new template applied | 12/19/2011 |
| 1.02 | V-Infinity branding removed | 08/22/2012 |
| 1.03 | corrected output power data | 10/12/2012 |
| 1.04 | updated isolation voltage | 01/08/2014 |

The revision history provided is for informational purposes only and is believed to be accurate.



Headquarters 20050 SW 112th Ave. Tualatin, OR 97062 800.275.4899

Fax 503.612.2383 cui.com techsupport@cui.com

CUI offers a two (2) year limited warranty. Complete warranty information is listed on our website.

CUI reserves the right to make changes to the product at any time without notice. Information provided by CUI is believed to be accurate and reliable. However, no responsibility is assumed by CUI for its use, nor for any infringements of patents or other rights of third parties which may result from its use.

CUI products are not authorized or warranted for use as critical components in equipment that requires an extremely high level of reliability. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.