



■ Features :

- Universal AC input / Full range
- No load power consumption<0.3W
- ErP step2 compliant
- NRCan compliant
- Meet EISA 2007 (Energy Independence and Security Act)
- 3 pole AC inlet IEC320-C14
- Class I power (with earth pin)
- Protections: Short circuit / Overload / Over voltage
- Fully enclosed plastic case
- LED indicator for power on
- Approvals: UL / CUL / TUV / BSMI / CCC / PSE / CB / FCC / CE
- Pass LPS
- 2 years warranty

SPECIFICATION



ION									
	GS18A05-P1J	GS18A07-P1J			GS18A15-P1J		GS18A24-P1J		GS18A48-P1J
FETY MODEL NO.	GS18A05	GS18A07	GS18A09	GS18A12	GS18A15	GS18A18	GS18A24	GS18A28	GS18A48
VOLTAGE Note.2	5V	7.5V	9V	12V	15V	18V	24V	28V	48V
TED CURRENT	3.0A	2.0A	2.0A	1.50A	1.20A	1.0A	0.75A	0.64A	0.375A
RRENT RANGE	0 ~ 3.0A	0 ~ 2.0A	0~2.0A	0 ~ 1.50A	0 ~ 1.20A	0 ~ 1.0A	0 ~ 0.75A	0 ~ 0.64A	0 ~ 0.375A
TED POWER (max.)	15W	15W	18W	18W	18W	18W	18W	18W	18W
PPLE & NOISE (max.) Note.3	50mVp-p	80mVp-p	80mVp-p	80mVp-p	100mVp-p	150mVp-p	180mVp-p	240mVp-p	240mVp-p
LTAGE TOLERANCE Note.4	±5.0%	±5.0%	±5.0%	±3.0%	±3.0%	±3.0%	±2.0%	±2.0%	±2.0%
IE REGULATION Note.5	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%
AD REGULATION Note.6	±5.0%	±5.0%	±5.0%	±3.0%	±3.0%	±3.0%	±2.0%	±2.0%	±2.0%
TUP, RISE, HOLD UP TIME	500ms, 20ms	50ms/230VAC	500ms,	20ms, 15ms/1	5VAC at full lo	ad			
LTAGE RANGE	90 ~ 264VAC 135 ~ 370VDC								
EQUENCY RANGE	47 ~ 63Hz								
FICIENCY (Typ.)	79.5%	82%	83%	85%	85%	85%	86%	86.5%	87%
CURRENT	0.5A / 100VA	0					'		
RUSH CURRENT (max.)	45A / 230VAC								
AKAGE CURRENT(max.)	0.75mA / 240VAC								
PROTECTION OVER VOLTAGE	110 ~ 150% rated output power								
	Protection type: Hiccup mode, recovers automatically after fault condition is removed								
	105 ~ 135% rated output voltage								
	Protection type : Clamp by zener diode, output short								
ORKING TEMP.	0 ~ +50°C (Refer to "Derating Curve")								
ORKING HUMIDITY	20% ~ 90% RH non-condensing								
ORAGE TEMP., HUMIDITY	-20 ~ +85℃, 10 ~ 95% RH								
MP. COEFFICIENT	±0.03% / °C (0 ~ 50°C)								
BRATION	10 ~ 500Hz, 2G 10min./1cycle, period for 60min. each along X, Y, Z axes								
FETY STANDARDS	UL60950-1, CSA C22.2, TUV EN60950-1, BSMI CNS14336, PSE J60950-1(5~28V only), CCC GB4943 approved								
THSTAND VOLTAGE	I/P-O/P:4242VDC , I/P-FG:2121VDC								
DLATION RESISTANCE	I/P-O/P, I/P-FG:100M Ohms / 500VDC / 25°C / 70% RH								
IC EMISSION	Compliance to EN55022, EN61000-3-2,3, FCC PART 15 / CISPR22 class B, CNS13438 class B, GB9254								
IC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, light industry level, criteria A								
BF	500Khrs min. MIL-HDBK-217F(25°C)								
MENSION	93*54*36mm (L*W*H)								
CKING	230g; 60pcs	/ 15kg / CARTO	ON						
UG	See page2								
BLE	See page2								
.DC voltage: The output vol Ripple & noise are measure Tolerance: includes set up Line regulation is measure Load regulation is measure	age set at point age at 20MHz be tolerance, line of from low line do from 20% to	nt measure by y using a 12" regulation, loa to high line at 100% rated lo	plug terminal twisted pair ter d regulation. rated load. pad	& 50% load. rminated with a		·	whole system o	complies with t	he
.DC volta .Ripple & .Toleran .Line reg .Load re .The pov	age: The output volt & noise are measure ce: includes set up gulation is measure gulation is measure wer supply is consid	age: The output voltage set at point and an accept a point and a community and	age: The output voltage set at point measure by a noise are measured at 20MHz by using a 12" ce: includes set up tolerance, line regulation, lo a juitation is measured from low line to high line at gulation is measured from 20% to 100% rated lo wer supply is considered as an independent unit	age: The output voltage set at point measure by plug terminal a noise are measured at 20MHz by using a 12" twisted pair terminates: includes set up tolerance, line regulation, load regulation. Joulation is measured from low line to high line at rated load. gulation is measured from 20% to 100% rated load wer supply is considered as an independent unit, but the final expressions.	ce: includes set up tolerance, line regulation, load regulation. gulation is measured from low line to high line at rated load. gulation is measured from 20% to 100% rated load wer supply is considered as an independent unit, but the final equipment still	age: The output voltage set at point measure by plug terminal & 50% load. A noise are measured at 20MHz by using a 12" twisted pair terminated with a 0.1uf & 47uf ce: includes set up tolerance, line regulation, load regulation. juilation is measured from low line to high line at rated load. gulation is measured from 20% to 100% rated load wer supply is considered as an independent unit, but the final equipment still need to re-cor	age: The output voltage set at point measure by plug terminal & 50% load. A noise are measured at 20MHz by using a 12" twisted pair terminated with a 0.1uf & 47uf capacitor. ce: includes set up tolerance, line regulation, load regulation. juilation is measured from low line to high line at rated load. gulation is measured from 20% to 100% rated load wer supply is considered as an independent unit, but the final equipment still need to re-confirm that the v	age: The output voltage set at point measure by plug terminal & 50% load. A noise are measured at 20MHz by using a 12" twisted pair terminated with a 0.1uf & 47uf capacitor. ce: includes set up tolerance, line regulation, load regulation. gulation is measured from low line to high line at rated load. gulation is measured from 20% to 100% rated load wer supply is considered as an independent unit, but the final equipment still need to re-confirm that the whole system of	age: The output voltage set at point measure by plug terminal & 50% load. A noise are measured at 20MHz by using a 12" twisted pair terminated with a 0.1uf & 47uf capacitor. ce: includes set up tolerance, line regulation, load regulation. julation is measured from low line to high line at rated load. gulation is measured from 20% to 100% rated load wer supply is considered as an independent unit, but the final equipment still need to re-confirm that the whole system complies with t



