

February 2014

74VHC74 Dual D-Type Flip-Flop with Preset and Clear

Features

- High Speed: f_{MAX} = 170MHz (typ.) at T_A = 25°C
- High noise immunity: $V_{NIH} = V_{NIL} = 28\% V_{CC}$ (min.)
- Power down protection is provided on all inputs
- Low power dissipation: I_{CC} = 2µA (max.) at T_A = 25°C
- Pin and function compatible with 74HC74

General Description

The VHC74 is an advanced high speed CMOS Dual D-Type Flip-Flop fabricated with silicon gate CMOS technology. It achieves the high speed operation similar to equivalent Bipolar Schottky TTL while maintaining the CMOS low power dissipation. The signal level applied to the D input is transferred to the Q output during the positive going transition of the CK pulse. CLR and PR are independent of the CK and are accomplished by setting the appropriate input LOW.

An input protection circuit ensures that 0V to 7V can be applied to the input pins without regard to the supply voltage. This device can be used to interface 5V to 3V systems and two supply systems such as battery backup. This circuit prevents device destruction due to mismatched supply and input voltages.

Ordering mon	nation	
Order Number	Package Number	Package Description
74VHC74M	M14A	14-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-012, 0.150" Narrow
74VHC74SJ	M14D	14-Lead Small Outline Package (SOP), EIAJ TYPE II, 5.3mm Wide
74VHC74MTC	MTC14	14-Lead Thin Shrink Small Outline Package (TSSOP), JEDEC MO-153, 4.4mm Wide
74VHC74N	N14A	14-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide

Ordering Information

Device also available in Tape and Reel. Specify by appending suffix letter "X" to the ordering number.

All packages are lead free per JEDEC: J-STD-020B standard.

Connection Diagram



Pin Description

Pin Names	Description
D ₁ , D ₂	Data Inputs
CK ₁ , CK ₂	Clock Pulse Inputs
$\overline{\text{CLR}}_1, \overline{\text{CLR}}_2$	Direct Clear Inputs
$\overline{PR}_1, \overline{PR}_2$	Direct Preset Inputs
$Q_1, \overline{Q}_1, Q_2, \overline{Q}_2$	Output

Logic Symbol



Truth Table

	Inputs				Outputs		
CLR	PR	D	СК	Q	Q	Function	
L	Н	Х	Х	L	Н	Clear	
Н	L	Х	Х	Н	L	Preset	
L	L	Х	Х	H ⁽¹⁾	H ⁽¹⁾		
Н	Н	L	~	L	Н		
Н	Н	Н	~	Н	L		
Н	Н	Х	\sim	Q _n	\overline{Q}_{n}	No Change	

Note:

1. This configuration is nonstable; that is, it will not persist when preset and clear inputs return to their inactive (HIGH) state.

Absolute Maximum Ratings

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only.

Symbol	Parameter	Rating
V _{CC}	Supply Voltage	-0.5V to +7.0V
V _{IN}	DC Input Voltage	-0.5V to +7.0V
V _{OUT}	DC Output Voltage	-0.5V to V _{CC} + 0.5V
I _{IK}	Input Diode Current	–20mA
I _{OK}	Output Diode Current	±20mA
I _{OUT}	DC Output Current	±25mA
I _{CC}	DC V _{CC} /GND Current	±50mA
T _{STG}	Storage Temperature	–65°C to +150°C
TL	Lead Temperature (Soldering, 10 seconds)	260°C

Recommended Operating Conditions⁽²⁾

The Recommended Operating Conditions table defines the conditions for actual device operation. Recommended operating conditions are specified to ensure optimal performance to the datasheet specifications. Fairchild does not recommend exceeding them or designing to absolute maximum ratings.

Symbol	Parameter	Rating
V _{CC}	Supply Voltage	2.0V to +5.5V
V _{IN}	Input Voltage	0V to +5.5V
V _{OUT}	Output Voltage	0V to V _{CC}
T _{OPR}	Operating Temperature	–40°C to +85°C
t _r , t _f	Input Rise and Fall Time, $V_{CC} = 3.3V \pm 0.3V$ $V_{CC} = 5.0V \pm 0.5V$	0ns/V ~ 100ns/V 0ns/V ~ 20ns/V

Note:

2. Unused inputs must be held HIGH or LOW. They may not float.

					T _A = 25°C			T _A = -40°C to +85°C		
Symbol	Parameter	V _{CC} (V)	Conditions		Min. Typ.	Max.	Min.	Max.	Units	
V _{IH}	HIGH Level Input	2.0			1.50			1.50		V
	Voltage	3.0–5.5	1		0.7 x V _{CC}			0.7 x V _{CC}		1
V _{IL}	/IL LOW Level Input 2.0						0.50		0.50	V
	Voltage	3.0–5.5					0.3 x V _{CC}		0.3 x V _{CC}	1
V _{OH} HIGH Level Output Voltage	2.0	$V_{IN} = V_{IH}$ or V_{IL}	I _{OH} = -50μA	1.9	2.0		1.9		V	
	3.0			2.9	3.0		2.9			
		4.5			4.4	4.5		4.4		1
		3.0		$I_{OH} = -4mA$	2.58			2.48		1
		4.5	1	I _{OH} = -8mA	3.94			3.80		1
V _{OL}	LOW Level	2.0	$V_{IN} = V_{IH}$	I _{OL} = 50μA		0.0	0.1		0.1	V
	Output Voltage	3.0	or V _{IL}	L		0.0	0.1		0.1	1
		4.5				0.0	0.1		0.1	
		3.0		$I_{OL} = 4mA$			0.36		0.44	1
		4.5		I _{OL} = 8mA			0.36		0.44	
I _{IN}	Input Leakage Current	0–5.5	V _{IN} = 5.5V	or GND			±0.1		±1.0	μA
I _{CC}	Quiescent Supply Current	5.5	$V_{IN} = V_{CC}$	or GND			2.0		20.0	μA

74VHC74 — Dual D-Type Flip-Flop with Preset and Clear

AC Electrical Characteristics

				T _A = 25°C		T _A = -40°C to +85°C			
Symbol	Parameter	V _{CC} (V)	Conditions	Min.	Тур.	Max.	Min.	Max.	Units
f _{MAX}	Maximum Clock	3.3 ± 0.3	$C_L = 15 pF$	80	125		70		MHz
	Frequency		$C_L = 50 pF$	50	75		45		
		5.0 ± 0.5	$C_L = 15 pF$	130	170		110		
			$C_L = 50 pF$	90	115		75		
t _{PLH} , t _{PHL}	Propagation Delay	3.3 ± 0.3	$C_L = 15 pF$		6.7	11.9	1.0	14.0	ns
Time (CK-Q	Time (CK-Q, \overline{Q})		$C_L = 50 pF$		9.2	15.4	1.0	17.5	
		5.0 ± 0.5	$C_L = 15 pF$		4.6	7.3	1.0	8.5	
			$C_L = 50 pF$		6.1	9.3	1.0	10.5	
t _{PLH} , t _{PHL}	t _{PLH} , t _{PHL} Propagation Delay		$C_L = 15 pF$		7.6	12.3	1.0	14.5	ns
	Time (\overline{CLR} , \overline{PR} -Q, \overline{Q})		$C_L = 50 pF$		10.1	15.8	1.0	18.0	
		5.0 ± 0.5	$C_L = 15 pF$		4.8	7.7	1.0	9.0	
			$C_L = 50 pF$		6.3	9.7	1.0	11.0	
C _{IN}	Input Capacitance		V _{CC} = Open		4	10		10	pF
C _{PD}	Power Dissipation Capacitance		(3)		25				pF

Note:

3. C_{PD} is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load. Average operating current can be obtained from the equation: I_{CC} (opr.) = C_{PD} • V_{CC} • f_{IN} + I_{CC} / 2 (per F/F).

AC Operating Requirements

			T _A =	25°C	T _A = -40°C to +85°C	
Symbol	Parameter	V _{CC} (V) ⁽⁴⁾	Тур.		aranteed inimum	Units
t _W (L), t _W (H)	Minimum Pulse Width (CK)	3.3		6.0	7.0	ns
		5.0		5.0	5.0	
t _W (L)	Minimum Pulse Width (CLR, PR)	3.3		6.0	7.0	ns
		5.0		5.0	5.0	
t _S	Minimum Setup Time	3.3		6.0	7.0	ns
		5.0		5.0	5.0	
t _H	Minimum Hold Time	3.3		0.5	0.5	ns
		5.0		0.5	0.5	
t _{REC}	Minimum Recovery Time (CLR, PR)	3.3		5.0	5.0	ns
		5.0		3.0	3.0	1

Note:

4. V_{CC} is 3.3 \pm 0.3V or 5.0 \pm 0.5V



specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings:

http://www.fairchildsemi.com/packaging/

74VHC74 — Dual D-Type Flip-Flop with Preset and Clear



http://www.fairchildsemi.com/packaging/

74VHC74 — Dual D-Type Flip-Flop with Preset and Clear





FAIRCHILD

SEMICONDUCTOR

TRADEMARKS

AccuPower™

Build it Now™

CorePLUS™

DEUXPEED®

Dual Cool™

EcoSPARK[®]

EfficientMax™

R

Fairchild®

FACT

FPS™

FAST®

FastvCore™

FETBench™

FACT Quiet Series™

ESBC™

CorePOWER™

CROSSVOLT™

AX-CAP®

BitSiC™

CTL™

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

F-PFS™ FRFET® Global Power ResourceSM GreenBridge™ Green FPS™ Green FPS™ e-Series™ Gmax™ **GTO™** Current Transfer Logic™ IntelliMAX™ **ISOPLANAR™** Making Small Speakers Sound Louder and Better™ MegaBuck™ MICROCOUPLER™ MicroFET™ MicroPak™ MicroPak2™ Fairchild Semiconductor® MillerDrive™ MotionMax™ mWSaver OptoHiT™ **OPTOLOGIC[®] OPTOPLANAR[®]**

PowerTrench[®] PowerXS^{TI} Programmable Active Droop™ QFET QS™ Quiet Series™ RapidConfigure™ \bigcirc TM Saving our world, 1mW/W/kW at a time™ SignalWise™ SmartMax™ SMART START™ Solutions for Your Success™ SPM[®] **STEALTH™** SuperFET[®] SuperSOT™-3 SuperSOT™-6 SuperSOT™-8 SupreMOS[®] SyncFET™

GENERAL®* TinyBoost[®] TinyBuck

Sync-Lock™

TinyCalc™ TinyLogic® TINYOPTO™ TinyPower™ TinyPWM™ TinyWire™ TranSiC™ TriFault Detect™ TRUECURRENT®* μSerDes™

UHC[®] Ultra FRFET™ UniFET™ VCX™ VisualMax™ VoltagePlus™ XS™

* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- 2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms		
Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchilk Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. 166