

WTL16P-34161120A00 W16

**SMALL PHOTOELECTRIC SENSORS** 





### Ordering information

Туре	Part no.
WTL16P-34161120A00	1218945

Other models and accessories → www.sick.com/W16

Illustration may differ





#### Detailed technical data

#### **Features**

Sensor/ detection principle	Photoelectric proximity sensor, LineSpot technology, Background suppression
Dimensions (W x H x D)	20 mm x 55.7 mm x 42 mm
Housing design (light emission)	Rectangular
Sensing range max.	10 mm 500 mm <sup>1)</sup>
Type of light	Visible red light
Light source	PinPoint LED <sup>2)</sup>
Light spot size (distance)	3 mm x 30 mm (200 mm)
Wave length	635 nm
Adjustment	
Teach-Turn adjustment	BluePilot: for setting the sensing range
IO-Link	For configuring the sensor parameters and Smart Task functions
Indication	
LED indicator blue	BluePilot: sensing range indicator
LED indicator green	Operating indicator Static: power on Flashing: IO-Link mode

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033).

<sup>&</sup>lt;sup>2)</sup> Average service life: 100,000 h at  $T_U$  = +25 °C.

LED indicator yellow	Status of received light beam Static on: object present Static off: object not present
Pin 2 configuration	External input, Teach-in, switching signal
Special applications	Detecting perforated objects
Special features	Line-shaped light spot

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033).

### Mechanics/electronics

Supply voltage	10 V DC 30 V DC <sup>1)</sup>
Ripple	≤ 5 V <sub>pp</sub>
Power consumption	30 mA <sup>2)</sup> 50 mA <sup>3)</sup>
Switching output	PUSH/PULL PNP NPN
Output: Q <sub>L1</sub> / C	Switching output or IO-Link mode
Output function	Factory setting: Pin 2 / white (MF): NPN normally open (light switching), PNP normally closed (dark switching), Pin 4 / black (QL1 / C): NPN normally closed (dark switching), PNP normally open (light switching), IO-Link
Switching mode	Light/dark switching
Signal voltage PNP HIGH/LOW	Approx. V <sub>S</sub> – 2.5 V / 0 V
Signal voltage NPN HIGH/LOW	Approx. VS / < 2.5 V
Output current I <sub>max.</sub>	≤ 100 mA
Response time	≤ 500 µs <sup>4)</sup>
Switching frequency	1,000 Hz <sup>5)</sup>
Connection type	Cable with M12 male connector, 4-pin, 270 mm <sup>6)</sup>
Cable material	PVC
Circuit protection	A <sup>7)</sup> B <sup>8)</sup> C <sup>9)</sup> D <sup>10)</sup>
Protection class	III
Weight	70 g
IO-Link	✓

<sup>1)</sup> Limit values.

 $<sup>^{2)}</sup>$  Average service life: 100,000 h at T<sub>U</sub> = +25 °C.

 $<sup>^{2)}\, 16\, \</sup>text{V}\, \text{DC} \dots 30\, \text{V}\, \text{DC},$  without load.

 $<sup>^{\</sup>rm 3)}$  10 V DC ... 16 V DC, without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load in switching mode. Different values possible in COM2 mode.

<sup>5)</sup> With light/dark ratio 1:1 in switching mode. Different values possible in IO-Link mode.

 $<sup>^{6)}</sup>$  Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A = V<sub>S</sub> connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>9)</sup> C = interference suppression.

<sup>10)</sup> D = outputs overcurrent and short-circuit protected.

 $<sup>\</sup>overset{\cdot}{\text{11)}}$  Replaces IP69K with ISO 20653: 2013-03.

Housing material	Plastic, VISTAL®
Optics material	Plastic, PMMA
Enclosure rating	IP66 (According to EN 60529) IP67 (According to EN 60529) IP69 (According to EN 60529) 11)
Ambient operating temperature	-40 °C +60 °C
Ambient storage temperature	-40 °C +75 °C
UL File No.	NRKH.E181493 & NRKH7.E181493

<sup>1)</sup> Limit values.

### Safety-related parameters

MTTF <sub>D</sub>	629 years
DC <sub>avg</sub>	0%

#### Communication interface

Communication interface	IO-Link V1.1
Communication Interface detail	COM2 (38,4 kBaud)
Cycle time	2.3 ms
Process data length	16 Bit
Process data structure	Bit 0 = switching signal $Q_{L1}$ Bit 1 = switching signal $Q_{L2}$ Bit 2 15 = empty
VendorID	26
DeviceID HEX	0x800168
DeviceID DEC	8388968

#### **Smart Task**

Smart Task name	Base logics
Logic function	Direct AND OR Window Hysteresis
Timer function	Deactivated On delay Off delay ON and OFF delay Impulse (one shot)

<sup>1)</sup> SIO Direct: sensor operation in standard I/O mode without IO-Link communication and without using internal sensor logic or time parameters (set to "direct"/"deactivated").

 $<sup>^{2)}</sup>$  16 V DC ... 30 V DC, without load.

 $<sup>^{3)}</sup>$  10 V DC ... 16 V DC, without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load in switching mode. Different values possible in COM2 mode.

 $<sup>^{5)}</sup>$  With light/dark ratio 1:1 in switching mode. Different values possible in IO-Link mode.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A = V<sub>S</sub> connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>9)</sup> C = interference suppression.

<sup>10)</sup> D = outputs overcurrent and short-circuit protected.

<sup>&</sup>lt;sup>11)</sup> Replaces IP69K with ISO 20653: 2013-03.

<sup>2)</sup> SIO Logic: Sensor operation in standard I/O mode without IO-Link communication. Sensor-internal logic or timing parameters plus Automation Functions used.

<sup>3)</sup> IOL: Sensor operation with full IO-Link communication and usage of logic, timing and Automation Function parameters.

Inverter	Yes
Switching frequency	SIO Direct: $1000 \text{ Hz}^{-1)}$ SIO Logic: $800 \text{ Hz}^{-2)}$ IOL: $650 \text{ Hz}^{-3)}$
Response time	SIO Direct: $500 \ \mu s^{1)}$ SIO Logic: $600 \ \mu s^{2)}$ IOL: $750 \ \mu s^{3)}$
Repeatability	SIO Direct: 150 $\mu$ s <sup>1)</sup> SIO Logic: 300 $\mu$ s <sup>2)</sup> IOL: 400 $\mu$ s <sup>3)</sup>
Switching signal Q <sub>L1</sub>	Switching output
Switching signal Q <sub>L2</sub>	Switching output

<sup>1)</sup> SIO Direct: sensor operation in standard I/O mode without IO-Link communication and without using internal sensor logic or time parameters (set to "direct"/"deactivated").

#### Classifications

ECI@ss 5.0	27270904
ECI@ss 5.1.4	27270904
ECI@ss 6.0	27270904
ECI@ss 6.2	27270904
ECI@ss 7.0	27270904
ECI@ss 8.0	27270904
ECI@ss 8.1	27270904
ECI@ss 9.0	27270904
ECI@ss 10.0	27270904
ECI@ss 11.0	27270904
ETIM 5.0	EC002719
ETIM 6.0	EC002719
ETIM 7.0	EC002719
UNSPSC 16.0901	39121528

### Connection diagram


#### Cd-390

<sup>2)</sup> SIO Logic: Sensor operation in standard I/O mode without IO-Link communication. Sensor-internal logic or timing parameters plus Automation Functions used.

<sup>3)</sup> IOL: Sensor operation with full IO-Link communication and usage of logic, timing and Automation Function parameters.

#### Characteristic curve


#### WTL16P-xxxxx1xx



- ① Sensing range on black, 6% remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90% remission

### Light spot size


#### WTL16P-xxxxx1xx



- ① Horizontal
- ② Vertical

### Sensing range diagram


### WTL16P-xxxxx1xx



- A = Detection distance (depending on object remission)
- ① Sensing range on black, 6% remission
- $\ \ \, \mbox{\Large @}$  Sensing range on gray, 18 % remission
- ③ Sensing range on white, 90% remission

### Adjustments possible


Display and adjustment elements



- ① LED indicator green
- ② LED indicator yellow
- ③ Teach-Turn adjustment
- 4 LED indicator blue

### Dimensional drawing (Dimensions in mm (inch))

WTB16, WTL16, cable



- ① Standard direction of the material being detected
- ② Center of optical axis, sender
- ③ Center of optical axis, receiver
- 4 Mounting hole, Ø 4.1 mm
- ⑤ Connection
- ⑥ Display and adjustment elements

#### Recommended accessories

Other models and accessories → www.sick.com/W16

	Brief description	Туре	Part no.
Universal ba	r clamp systems		
	Plate N02 for universal clamp bracket, Zinc plated steel (sheet), Zinc die cast (clamping bracket), Universal clamp (5322626), mounting hardware	BEF-KHS-N02	2051608
Mounting br	ackets and plates		
y T	Adapter for mounting W16 sensors into existing W14-2 $/$ W18-3 installations, plastic, fastening screws included	BEF-AP-W16	2095677
Plug connec	tors and cables		
<b>P</b>	Head A: female connector, M12, 4-pin, straight, A-coded Head B: Flying leads Cable: Sensor/actuator cable, PVC, unshielded, 5 m	YF2A14- 050VB3XLEAX	2096235
	Head A: male connector, M12, 4-pin, straight Head B: - Cable: unshielded	STE-1204-G	6009932

### Recommended services

Additional services → www.sick.com/W16

	Туре	Part no.
Function Block Factory		
• <b>Brief description:</b> The Function Block Factory supports common programmable logic controllers (PLCs) from various manufacturers, such as Siemens, Beckhoff, Rockwell Automation and B&R. More information on the FBF can be found <a href='https://fbf.cloud.sick.comtarget="_blank"'>here</a> .	Function Block Factory	On request

## SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

